



**Recommendation ITU-R M.1319-3**  
(01/2010)

**The basis of a methodology to assess the impact of interference from a time division multiple access/frequency division multiple access (TDMA/FDMA) mobile-satellite service (MSS) space-to-Earth transmissions on the performance of line-of-sight fixed service receivers in the frequency range 1-3 GHz**

**M Series**

**Mobile, radiodetermination, amateur and related satellite services**

## Foreword

The role of the Radiocommunication Sector is to ensure the rational, equitable, efficient and economical use of the radio-frequency spectrum by all radiocommunication services, including satellite services, and carry out studies without limit of frequency range on the basis of which Recommendations are adopted.

The regulatory and policy functions of the Radiocommunication Sector are performed by World and Regional Radiocommunication Conferences and Radiocommunication Assemblies supported by Study Groups.

## Policy on Intellectual Property Right (IPR)

ITU-R policy on IPR is described in the Common Patent Policy for ITU-T/ITU-R/ISO/IEC referenced in Annex 1 of Resolution ITU-R 1. Forms to be used for the submission of patent statements and licensing declarations by patent holders are available from <http://www.itu.int/ITU-R/go/patents/en> where the Guidelines for Implementation of the Common Patent Policy for ITU-T/ITU-R/ISO/IEC and the ITU-R patent information database can also be found.

### Series of ITU-R Recommendations

(Also available online at <http://www.itu.int/publ/R-REC/en>)

Series	Title
<b>BO</b>	Satellite delivery
<b>BR</b>	Recording for production, archival and play-out; film for television
<b>BS</b>	Broadcasting service (sound)
<b>BT</b>	Broadcasting service (television)
<b>F</b>	Fixed service
<b>M</b>	<b>Mobile, radiodetermination, amateur and related satellite services</b>
<b>P</b>	Radiowave propagation
<b>RA</b>	Radio astronomy
<b>RS</b>	Remote sensing systems
<b>S</b>	Fixed-satellite service
<b>SA</b>	Space applications and meteorology
<b>SF</b>	Frequency sharing and coordination between fixed-satellite and fixed service systems
<b>SM</b>	Spectrum management
<b>SNG</b>	Satellite news gathering
<b>TF</b>	Time signals and frequency standards emissions
<b>V</b>	Vocabulary and related subjects

*Note: This ITU-R Recommendation was approved in English under the procedure detailed in Resolution ITU-R 1.*

Electronic Publication  
Geneva, 2010

© ITU 2010

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without written permission of ITU.

RECOMMENDATION ITU-R M.1319-3<sup>\*,\*\*</sup>

**The basis of a methodology to assess the impact of interference from a time division multiple access/frequency division multiple access (TDMA/FDMA) mobile-satellite service (MSS) space-to-Earth transmissions on the performance of line-of-sight fixed service receivers in the frequency range 1-3 GHz \*\***

(Questions ITU-R 201/4 and ITU-R 118/5)

(1997-2000-2003-2010)

### Scope

This Recommendation provides a methodology to assess the impact of interference from TDMA/FDMA mobile-satellite service (MSS) (space-to-Earth) transmissions on the performance of line-of-sight (LoS) fixed service (FS) receivers in the frequency range 1-3 GHz. This methodology may be used for developing computer simulation tools for use in detailed MSS/FS coordination.

The ITU Radiocommunication Assembly,

*considering*

- a) that the frequency band 1 518-1 525 MHz is allocated to the mobile-satellite service (MSS) (space-to-Earth) and the fixed service (FS) on a co-primary basis in all Regions;
- b) that the frequency band 1 525-1 559 MHz is also allocated to the MSS (space-to-Earth) on a primary basis in all Regions;
- c) that the frequency band 1 525-1 530 MHz is also allocated to the fixed service on a primary basis in Regions 1 and 3 and the frequency band 1 550-1 559 MHz is also allocated to the fixed service on a primary basis in some countries;
- d) that the frequency bands 2 170-2 200 MHz in all Regions and 2 160-2 170 MHz in Region 2 are allocated to the MSS (space-to-Earth) and the fixed service on a co-primary basis;
- e) that transmissions from MSS satellites could cause unacceptable interference to LoS fixed service receivers operating in these bands;
- f) that interference involves time-varying phenomena such as interference geometry, propagation conditions, and MSS traffic;
- g) that simulation is the most common way to evaluate such interference;
- h) that the impact and acceptability of such interference in most cases can be assessed in detailed bilateral coordination by studying via computer simulation the  $C/N$ ,  $C/I$  and  $C/(N+I)$  statistics as described in Recommendation ITU-R M.1143;

---

\* This is a joint Radiocommunication Study Group 4 and 5 Recommendation, and any revision shall be undertaken jointly.

\*\* Further study is needed for MSS networks using code division multiple access (CDMA).

j) that assistance in using such tools is particularly needed by administrations in developing countries,

*recommends*

1 that the methodology in Annex 1 should be used as a basis for developing computer simulation tools for use in detailed bilateral coordination between concerned parties to enable a detailed assessment of the impact of interference from a TDMA/FDMA MSS satellite system in the 1-3 GHz MSS allocations to analogue and digital LoS fixed service systems, taking into account the specific characteristics of the MSS and fixed service systems concerned (see Notes 1, 2 and 3).

NOTE 1 – The application of the methodology in this Recommendation will require the development of algorithms or calculation procedures to address the implementation of the considerations described. The use or adaptation of these algorithms or procedures in any bilateral coordination would be subject to agreement by the concerned parties.

NOTE 2 – In countries where a large number of fixed service systems are in operation, it may be sufficient to apply the analysis to a representative set of existing fixed service systems, using actual fixed service parameters, especially taking into account those fixed service systems that are likely to be most sensitive to interference. The most sensitive fixed service systems are usually those oriented close to the worst-case azimuth direction; this direction can be established based on the orbital characteristics of the MSS system. However, this is a matter that will require agreement between the concerned parties.

NOTE 3 – In the case of geostationary-satellite orbit (GSO) MSS systems the calculations are significantly simplified, since there is no need to simulate the orbital mechanics of the MSS constellation, however the potential of interference from multiple GSO MSS satellites may need to be considered when evaluating the impact of interference.

## Annex 1

### 1 Introduction

Sharing between MSS and fixed service involves time varying phenomena such as interference geometry, propagation conditions, etc. Simulation is the most common way to evaluate interference between MSS and fixed service systems. The output of such simulations is typically in the form of  $C/I$ ,  $C/N$  and  $C/(N+I)$  statistics presented usually as a cumulative distribution function, for example as described in Recommendation ITU-R M.1143 (see Annex 3).

The relevant baseband performance objectives for a given digital and analogue fixed service system can generally be translated into a required  $C/(N+I)$  (see Note 1 below). For example for a digital fixed service system, the baseband specification is usually a bit-error ratio (BER) requirement not to be exceeded for a certain percentage of time. The baseband BER requirement can, from reference curves such as those provided in Recommendation ITU-R SF.766 or actual modem specifications, be translated into a required  $E_b/N_0$  value, which in turn can be translated into a  $C/(N+I)$  requirement at the input to the receiver. In a similar way the baseband requirements for analogue frequency division multiplex/frequency modulation (FDM/FM) and TV-FM fixed service systems in terms of total baseband noise or baseband  $S/N$  can be translated into a  $C/(N+I)$  requirement at the input to the receiver.

NOTE 1 – While the performance of radio-relay systems should, in principle, be related to a quantity that can be described as  $C/(N + I)$ , the validity of such relationships depends on having the appropriate value for the total equivalent system noise,  $N$ .

These equivalent radio-frequency performance objectives can be plotted on the cumulative distribution plots of  $C/(N + I)$  and compared with the simulation curves of  $C/N$  and  $C/(N + I)$  to assess if the interference from MSS satellites is acceptable or not.

The method described herein, although it requires significant computer simulation is relatively straightforward to implement in software, since all calculations and comparisons are undertaken in the radio-frequency domain. The methodology herein should generally be used in the detailed coordination phase between administrations, when coordination is required and triggered in order to determine whether or not the interference can be accepted in the context of actual fixed service system information and the relevant ITU-R performance and availability objectives.

When assessing an MSS network using TDMA/FDMA, the aggregate interfering signal power within a reference bandwidth of 1 MHz (or less) for fixed stations should be assumed to be generated only by the individual network under consideration, under the assumption that the emissions of these MSS systems would not be interleaved within any 1 MHz segment of spectrum.

## 2 Methodology

### 2.1 Generation of target $C/(N + I)$ requirements for fixed service system

The relevant baseband performance objectives for a given digital and analogue fixed service system can generally be translated into a required  $C/(N + I)$  as indicated below.

Recommendation ITU-R F.393<sup>1</sup> specifies performance requirements for analogue FDM/FM fixed service systems in terms of total baseband noise in a given telephone channel for various percentages of time. These baseband requirements for the reference circuit can be translated through the standard  $C/N$  versus  $S/N$  FM equation into equivalent  $C/(N + I)$  requirements.

Recommendation ITU-R F.555<sup>2</sup> specifies performance requirements for analogue TV/FM fixed service systems in terms of required  $S/N$  in a given video channel for various percentages of time. These baseband requirements for the reference circuit can be translated through the standard  $C/N$  versus  $S/N$  FM equation into equivalent  $C/(N + I)$  requirements.

Recommendations ITU-R F.634, ITU-R F.695, ITU-R F.696, ITU-R F.697 and ITU-R F.557 specify network performance objectives (NPO) (error performance objectives and availability) for the existing digital systems in high, medium and local grade of the integrated services digital network (ISDN) in terms of required BER for various percentages of time. These baseband requirements for the reference circuit can be translated through standard reference curves provided in Recommendation ITU-R SF.766 into equivalent  $C/(N + I)$  requirements.

Generation of target  $C/(N + I)$  requirements for new digital fixed service systems should be based on Recommendation ITU-R F.1668.

---

<sup>1</sup> Recommendation ITU-R F.393 was suppressed in 2007. However some fixed systems may continue to exist for which this Recommendation would be applicable.

<sup>2</sup> Recommendation ITU-R F.555 was suppressed in 2007. However some fixed systems may continue to exist for which this Recommendation would be applicable.

The actual fixed service receiver modem characteristics should be used, where available, in the translation from baseband performance objective to  $C/(N+I)$ . Where this information is not available, theoretical characteristics from Recommendation ITU-R SF.766 can be used, and an implementation margin should be agreed between the parties.

## 2.2 Generation of $C/I$ , $C/N$ and $C/(N+I)$ statistics for fixed service system

*Step 1:* Calculation at each time step of received carrier level,  $C$ , at each receive fixed service station in a multi-hop fixed service route with multipath fading taken into account on that particular hop.

- a) The received carrier level,  $C$ , at each station is calculated from the associated transmit fixed service station e.i.r.p., the free space loss corresponding to the particular path length and multipath fading propagation loss applicable to that particular hop, the receive fixed service antenna gain and receive fixed service feed losses.
- b) Multipath fading is taken into account using a random fade depth predictor, whose output is consistent with the statistical distribution derived from the Recommendation ITU-R P.530 multipath fading model. The random fade predictor generates fade depths at each relevant time step in the simulation, such that the statistical distribution of fades generated is consistent with the distribution predicted for that path. The fade depth predictor requires information on the path length, path inclination, frequency and a number of geoclimatic factors specified in the above Recommendation appropriate to the particular geographical location of the fixed service hop. The time step specified for the fade depth predictor can in general be different from that required for interference assessment, since the latter is usually a more slowly varying process. For typical 2 GHz digital fixed service systems it is normally not necessary to include an allowance for other types of fading.
- c) In some cases, fixed service hops may not have first Fresnel Zone clearance. In such cases, it is appropriate to add an additional loss factor to the free space loss and multipath fading loss. This factor should be based on measured data, where available.
- d) In cases where statistically valid measured propagation data is available for individual fixed service hops, this data could be used in place of the propagation models given in a), b) and c) above, on agreement between the concerned parties. It may be possible in some cases (e.g. based on measured data), to take into account diurnal and/or seasonal variations in multipath fading propagation behaviour.
- e) Consideration should be given to including in the total noise,  $N$ , an allowance for intra-system and intra-service interference within the fixed service, as well as contributions from other co-primary (non-MSS) services (see Note 1 below). The value of this allowance should be determined by the concerned parties. It should be noted that Recommendation ITU-R F.1094 specifies that the maximum allowable value of error performance and availability degradation to digital fixed service systems due to emissions from services sharing frequencies on a primary basis should not exceed 10% of NPO.

NOTE 1 – Included in the total equivalent noise, in addition to the contributions to account for thermal noise and receiver noise for the receivers, are factors to account for intra-service interference and additional factors depending on the type of fixed service system. For digital systems, factors may be needed for receiver implementation imperfections where ideal modem characteristics are used. For analogue FM radio-relay systems used for telephony, factors are needed to account for intermodulation distortion noise and for contributions from such systems components as multiplexers/demultiplexers, and entrance links. For analogue radio-relay systems used for television, consideration of additional factors may be needed.

*Step 2:* Calculation at each time step of the interfering signal power,  $I$ , at each receive fixed service station in a multi-hop fixed service route due to each interfering TDMA/FDMA MSS carrier within the fixed service carrier occupied bandwidth from each spot beam of each visible MSS satellite,

taking into account MSS satellite spot beam, receive fixed service antenna discrimination, MSS satellite spot beam power/traffic loading and frequency plans.

- a) The orbital positions of each MSS satellite can be predicted by an orbit predictor taking into account the actual or forced precession of the orbits. The orbital position of a GSO satellite is fixed at a given longitude in the geostationary orbit.
- b) The free space loss on the interfering path from each visible MSS satellite to each visible fixed service station can be computed knowing the range vector magnitude.
- c) Each MSS satellite spot beam on each MSS satellite can be characterized by reference patterns or by actual measured or predicted antenna patterns.
- d) For each MSS satellite spot beam per satellite, the satellite spot beam antenna gain towards each fixed service station can be computed knowing the instantaneous relative position of the MSS satellite with respect to the fixed service station and the pointing direction of the particular satellite spot beam.
- e) Each receive fixed service antenna can usually be described by the Recommendation ITU-R F.1245 pattern or by the actual antenna pattern or formula. In the case of GSO MSS systems, Recommendation ITU-R F.699 may be more appropriate.
- f) For each receive fixed service station the receive antenna gain towards the visible satellite can be computed knowing the instantaneous relative position of the MSS satellite with respect to the fixed service station and the pointing direction of the particular fixed service antenna.
- g) Based on predicted realistic diurnal and geographic subscriber traffic distributions and system dependant satellite spot beam traffic allocation, the total traffic carried in each spot beam of each MSS satellite can be identified by the MSS party using proprietary or representative algorithms. Based on the system dependant internal frequency reuse constraints for the MSS satellite system, the nominal frequency plan applicable to each spot beam of each MSS satellite can similarly be identified if necessary.
- h) For each receive fixed service station, the interfering power from all TDMA/FDMA MSS carriers in any spot beam of any visible MSS satellite which overlaps the fixed service occupied carrier bandwidth can be accumulated taking into account MSS satellite spot beam antenna discrimination, fixed service antenna discrimination and range loss. It may suffice to take into account MSS satellite spot beams whose boresight is within a certain off-axis angle from the vector to the victim fixed service station.
- i) Since MSS satellite systems and fixed service systems will usually employ circular and linear polarizations respectively, it is relevant to consider the available polarization discrimination. Specifically if the MSS spot beam pointing vector and the receive fixed service antenna boresight vector are within a specified angular range (typically within the 3 dB beamwidths of both antennas), a polarization advantage can be computed taking into account information on the actual cross-polar patterns of the MSS satellite spot beam and fixed service antennas or alternatively.

Recommendation ITU-R F.1245 can also be used for this purpose. In the case of GSO MSS systems, Recommendation ITU-R F.699 may be more appropriate.

*Step 3:* Calculation of the total equivalent noise power  $N$  – The thermal noise at each fixed service receive station can be calculated from knowledge of the fixed service system noise temperature taking into account the receiver noise figure, the feed losses and the antenna noise temperature.

*Step 4:* Calculation at each time step of  $C/I$  (due to all relevant interfering MSS active carriers from each relevant spot beam of each visible MSS satellite),  $C/N$  and  $C/(N + I)$  at each receive fixed service station.

*Step 5:* Calculation at each time step of  $C/I$ ,  $C/N$  and  $C/(N+I)$  by inverse addition of the  $C/N$ ,  $C/I$  and  $C/(N+I)$  values calculated in Step 4 at each fixed service receive station, and calculation of the overall  $C/N$ ,  $C/I$  and  $C/(N+I)$  at the terminal fixed service receive station in the particular fixed service system.

*Step 6:* The above steps are repeated for each time step over a statistically valid period consistent with a full or equivalent orbital cycle period of the MSS satellite constellation and a representative period for the fixed service multipath fading behaviour. (In the case of GSO satellites this will be equal to the representative period for multipath fading.) One method to check for statistical validity is to ensure that statistics at the required level are not significantly influenced by additional time steps. Application of the additional methods of Recommendation ITU-R F.1108 may also be useful for this evaluation.

*Step 7:* If there are multiple fixed service systems in the country concerned, which may be affected by the MSS satellite system, it may be possible to carry out Steps 1 to 6 above in parallel for each such fixed service system during the simulation.

*Step 8:* Finally, for each fixed service system considered, the cumulative distribution of  $C/I$ ,  $C/N$  and  $C/(N+I)$  can be plotted. The  $C/N$  (in the absence of interference) and  $C/(N+I)$  curves can then be compared with the relevant ITU-R target performance objectives.

NOTE 1 – For non-GSO MSS satellites, the time step chosen for the interference assessment should be sufficiently small to allow for multiple samples of non-GSO MSS satellite visibility within the main-beam of the particular fixed service stations to be considered. The selection of appropriate time step is a function of the orbital parameters of the non-GSO MSS satellite constellation, the location of the fixed service stations and the fixed service antenna beamwidths.

NOTE 2 – For non-GSO MSS satellites, the simulation period should be sufficiently long to allow for a complete cycle period of the non-GSO MSS satellite to be considered. For consideration of the effects of the uniformity of interference from a non-GSO MSS satellite constellation in a month, the guidance of Annex 5 to Recommendation ITU-R F.1108 may be useful. Taking these factors into account, for non-GSO MSS satellite constellation which exhibit a relatively slow orbital precession, it may be preferable to establish a forced precession rate to allow for simulation of the complete cycle period within a reasonable elapsed simulation time.

NOTE 3 – Fixed service performance objectives specified in all the relevant ITU-R Recommendations are only applicable during available time, where availability is defined by the relevant ITU-R Recommendations. During periods of propagation induced unavailability, it is not relevant to consider the impact of interference. However this factor can be ignored in the present methodology if the interference from the MSS system allows the fixed service system to meet all of its requirements for ITU-R error performance objectives.

NOTE 4 – Convolution of the  $C$  and  $I$  distributions with  $N$  can also be used to generate a  $C/(N+I)$  distribution for a single hop fixed service system. For non-GSO MSS, see also Annex 6 of Recommendation ITU-R F.1108.

## 2.3 Consideration of analysis

*Step 1:* If the performance objectives in the applicable ITU-R Recommendations are met for each fixed service system considered in the presence of the incremental performance degradation induced by interference by MSS satellite system, it should facilitate satisfactory completion of the technical aspects of frequency coordination.

*Step 2:* In some cases, it may be necessary to conduct further studies to determine if interference from MSS satellite system is acceptable or not, prior to consideration of other burden sharing measures.