

Name: APELUX204V01**Description:****Type:** Earth station, Receiving and Transmitting

Earth station antenna pattern submitted by LUX for both uplinks and downlinks for analyses under Appendix 30B.

Required Input Parameters:

gain

Validation Warnings/Errors:

Type	Message
Error	D/lambda () is less than 100 ().
Error	Gmax () is less than G1 (). Square root of negative value.

Pattern Information:

The algorithm has been expanded to describe a complete pattern using the same pattern as Appendix 30B (with coefA=29) in the undefined areas.

Pattern is valid only for $D/\lambda > 100$.

BR software sets antenna efficiency to 0.7 for technical examination.

Co-Polar Component:

$$G = G_{\max} - 2.5 \times 10^{-3} (D/\lambda \cdot \varphi)^2 \quad \text{for } 0^\circ \leq \varphi < \varphi_m$$

$$G = G_1 \quad \text{for } \varphi_m \leq \varphi < \varphi_r$$

$$G = 29 - 25 \log \varphi \quad \text{for } \varphi_r \leq \varphi < 20^\circ$$

$$G = 32 - 25 \log \varphi \quad \text{for } 20^\circ \leq \varphi < \varphi_b$$

$$G = -10 \quad \text{for } \varphi_b \leq \varphi \leq 180^\circ$$

where:

$$D/\lambda = \sqrt{\frac{10 \left(\frac{G_{\max}}{10} \right)}{\eta \pi^2}}.$$

$$G_1 = -1 + 15 \log (D/\lambda).$$

$$\varphi_r = 15.85 (D/\lambda)^{-0.6}.$$

$$\varphi_m = 20 \lambda/D \sqrt{G_{\max} - G_1}.$$

$$\varphi_b = 48^\circ.$$