



Recommendation ITU-R M.1640-1
(01/2018)

**Characteristics of, and protection criteria for
sharing studies for radars operating in
the radiodetermination service
in the frequency band 33.4-36 GHz**

M Series
**Mobile, radiodetermination, amateur
and related satellite services**

Foreword

The role of the Radiocommunication Sector is to ensure the rational, equitable, efficient and economical use of the radio-frequency spectrum by all radiocommunication services, including satellite services, and carry out studies without limit of frequency range on the basis of which Recommendations are adopted.

The regulatory and policy functions of the Radiocommunication Sector are performed by World and Regional Radiocommunication Conferences and Radiocommunication Assemblies supported by Study Groups.

Policy on Intellectual Property Right (IPR)

ITU-R policy on IPR is described in the Common Patent Policy for ITU-T/ITU-R/ISO/IEC referenced in Annex 1 of Resolution ITU-R 1. Forms to be used for the submission of patent statements and licensing declarations by patent holders are available from <http://www.itu.int/ITU-R/go/patents/en> where the Guidelines for Implementation of the Common Patent Policy for ITU-T/ITU-R/ISO/IEC and the ITU-R patent information database can also be found.

Series of ITU-R Recommendations

(Also available online at <http://www.itu.int/publ/R-REC/en>)

Series	Title
BO	Satellite delivery
BR	Recording for production, archival and play-out; film for television
BS	Broadcasting service (sound)
BT	Broadcasting service (television)
F	Fixed service
M	Mobile, radiodetermination, amateur and related satellite services
P	Radiowave propagation
RA	Radio astronomy
RS	Remote sensing systems
S	Fixed-satellite service
SA	Space applications and meteorology
SF	Frequency sharing and coordination between fixed-satellite and fixed service systems
SM	Spectrum management
SNG	Satellite news gathering
TF	Time signals and frequency standards emissions
V	Vocabulary and related subjects

Note: This ITU-R Recommendation was approved in English under the procedure detailed in Resolution ITU-R 1.

Electronic Publication
Geneva, 2018

© ITU 2018

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without written permission of ITU.

RECOMMENDATION ITU-R M.1640-1

**Characteristics of, and protection criteria for sharing studies
for radars operating in the radiodetermination service
in the frequency band 33.4-36 GHz**

(Questions ITU-R 213/7 and ITU-R 226/8)

(2003-2018)

Scope

This Recommendation provides the technical characteristics and protection criteria for the radiodetermination systems operating in the band 33.4-36 GHz. The text was developed as a resource document intended to support sharing studies where sharing between the radiodetermination service and other services may be possible.

Keywords

Characteristics, protection criteria, radar, radiometric imagers, metric radar, seeker, search radar, track radar

Abbreviations/Glossary

IF: Intermediate frequency

RF: Radio frequency

RR: Radio regulations

Rx: Receive

Tx: Transmit

Related ITU Recommendations and Reports

Recommendation ITU-R M.1461 – Procedures for determining the potential for interference between radars operating in the radiodetermination service and systems in other services

The ITU Radiocommunication Assembly,

considering

- a)* the antenna, signal propagation, target detection, and large necessary bandwidth characteristics of radar to achieve their functions are optimum in certain frequency bands;
- b)* that the technical characteristics of radiodetermination radars are determined by the mission of the system and vary widely even within a band;
- c)* that representative technical and operational characteristics of radars are required to determine the feasibility of introducing new types of systems into frequency bands;
- d)* that procedures and methodologies to analyse compatibility between radars and systems in other services are provided in Recommendation ITU-R M.1461;
- e)* that radiodetermination radars operate in the frequency band 33.4-36 GHz;
- f)* that the frequency band 33.4-34.2 GHz is allocated to the radiolocation service on a primary basis;

- g) that the frequency band 34.2-34.7 GHz is allocated to the radiolocation and space research (deep space) (Earth-to-space) services on a primary basis;
- h) that the frequency band 34.7-35.2 GHz is allocated to the radiolocation service on a primary basis and to space research service on a secondary basis;
- i) that the frequency band 35.2-35.5 GHz is allocated to the meteorological aids and radiolocation services on a primary basis;
- j) that the frequency band 35.5-36 GHz is allocated to the meteorological aids, Earth exploration-satellite (active), radiolocation, and space research (active) services on a primary basis,

recommends

- 1 that the technical and operational characteristics of the radiodetermination radars described in Annex 1 should be considered representative of those operating in the frequency band 33.4-36 GHz;
- 2 that in the case of continuous (non-pulsed) interference, an interfering signal power to radar receiver noise power level, I/N , of -6 dB should be used as the required protection level for radiolocation systems for sharing studies in general, including search and track radar (F) in Table 1 of Annex 1 in the frequency range 33.4-36 GHz;
- 3 that for studies of sharing the band 33.4-36 GHz between radars (A-E) in Table 1 of Annex 1 and systems in other services, the following criteria be used:
- that for radiometric imagers the short-term protection criteria should be -137.8 dB(W/2 GHz) for not longer than 3 s, and the long-term protection criteria should be no more than -144.8 dB(W/2 GHz) for not longer than 60 s;
 - that for metric radars and seekers the short-term protection criteria should be -126.2 dB(W/6 MHz) for not longer than 5 s, and the long-term protection criteria should be no more than -136.1 dB(W/6 MHz) for not longer than 60 s.

Annex 1

Characteristics of, and protection criteria for radars operating in the radiodetermination service in the frequency band 33.4-36 GHz

1 Purpose

The characteristics and protection criteria in this Recommendation have been provided for use in sharing studies called for under Resolutions **712 (WRC-2000)** and **730 (WRC-2000)** and to assess the compatibility between the radars and other systems operating in the frequency band 33.4-36 GHz.

2 Technical characteristics

Frequencies around 35 GHz and 94 GHz, correspond roughly to the first two propagation windows in the atmospheric absorption characteristics of the millimetre wave spectrum, and use of these frequencies is required by systems in the radiodetermination service in order to achieve the high measurement accuracy and target resolution possible at millimetre wavelength. Both passive and active sensors operating in the radiodetermination service around these frequencies are used for mapping, target identification, navigation, aim-point determination, test range instrumentation, etc.

Table 1 summarizes technical characteristics of representative systems deployed in these bands. This information is sufficient for general calculation to assess the compatibility between these radars and other systems.

TABLE 1
Technical characteristics of radars around 35 GHz

Parameter	Units	Radar A	Radar B	Radar C	Radar D	Radar E	Radar F
Use		Imaging	Imaging	Metric	Metric	Seeker	Search and track
Sensor type		Passive	Active	Active	Active	Active	Active
Modulation		–	Pulse	Pulse	Pulse	Linear FM	Linear FM Pulse
Compression ratio		–	–	–	–	200	50
Pulse width	μs	–	0.05	0.25	0.05	10	20
Tx peak power	kW	–	0.5	135	1	0.001	10
Pulse repetition frequency	kHz	–	30	1	50	10	10-30
RF bandwidth	MHz	–	80	10	101	12	2000
Antenna gain	dBi	35	30	52	51	28.7	52
Beamwidth	degrees	0.5 × 3.0	0.75 × 10	0.25 × 0.25	0.5 × 0.5	4.4 × 4.4	0.25 × 0.25
Rx IF bandwidth	GHz	2	0.040	0.006	0.185	0.100	0.006
Noise temperature	K	850	–	–	–	–	–
Noise figure	dB	–	4.5	10	10	5	4
Rx sensitivity	dBm	–	–81	–95	–78	–93	–
Tuning		Fixed	Fixed	Fixed	Frequency hop	Fixed	Frequency hopping

3 Protection criteria

Short-term interference criteria are developed in the following paragraphs for the terrestrial radiolocation systems given in Table 1.

3.1 Radiometric imagers

Assuming negligible system gain variation, the minimum temperature sensitivity, ΔT of a radiometric imaging system is:

$$\Delta T = \frac{T_A + T_r}{\sqrt{B \cdot t_i}} \quad (1)$$

where:

- T_A : antenna noise temperature
- T_r : receiver noise temperature
- B : RF bandwidth
- t_i : integration time.

The radiometer threshold, ΔP is given by:

$$\Delta P = k \Delta T B \quad (2)$$

where k is Boltzman's constant = 1.38×10^{-23} , and ΔT and B are as given above. Using equations (1) and (2), we find that a radiometer with a 2 GHz bandwidth, 850 K system noise temperature and a 1 ms integration time has $\Delta P = -137.8$ dB(W/2 GHz).

Short-term protection criterion

Given that it is an unlikely event, an operator can accept a severely degraded image for several seconds. Permitting the unwanted signal level to approach the radiometer's threshold results in an allowed unwanted signal level of -137.8 dB(W/2 GHz) for no more than 3 s.

Long-term protection criterion

A lesser degradation may be considered for time periods lasting up to 1 min. In this case the degradation is not necessarily readily evident to an operator, but does cause some loss in image resolution. Permitting the unwanted signal to reach 20% of the radiometer's threshold yields an allowed interference level of -144.8 dB(W/2 GHz) for no more than 60 s.

3.2 Metric radars and seekers

For the case of terrestrial metric (instrumentation) radars and the seekers, it can be noted that two important performance parameters, angular accuracy σ_θ and target detection range R , are related to the received S/N by:

$$\sigma_\theta \propto \frac{1}{\sqrt{S/N}} \quad (3)$$

$$R \propto \frac{1}{\sqrt[4]{S/N}} \quad (4)$$

Narrow antenna beamwidth and high angular accuracy are possible with fairly small antenna sizes at millimetre wavelengths. This characteristic, in fact, is a major reason why missile seekers and instrumentation radars have been developed at these frequencies. From equations (3) and (4) it can be seen that the angular accuracy of the radar is more sensitive to the received S/N than is the detection range so this performance parameter will be used to determine allowed interference levels¹.

As in the case of the imaging system in the previous section, short term and long-term criteria can be established for allowed degradation in system performance due to unwanted signals (interference).

Short-term interference is allowed to significantly degrade the system for a period of time short enough that it may be acceptable to the operator, given that it is an unlikely event. Long-term interference is allowed to incrementally degrade system performance to an extent not readily apparent to the operator, but is otherwise acceptable for the specified duration of time.

Short-term protection criterion

A degradation in the radar S/N will cause a tracking error, which can partially negate the advantage of operating at higher frequencies, and may significantly affect the radar's mission. Permitting an unwanted signal to reach the radar noise level ($I/N = 0$ dB) will result in a 40% increase in the angle error. It can be again assumed that this degradation is not overly important – given that it is

¹ It is assumed here, for simplicity, that interfering signals will be interpreted by the victim receiver as an increase in the noise power in the IF stages. The actual response by radar systems may need to be considered, but is beyond the scope of this generalized treatment.

an unlikely event – for periods of time less than about 5 s. The allowed unwanted signal level can then be as great as -126.2 dB(W/6 MHz) for no more than 5 s (using the radar with the narrowest bandwidth given in Table 1).

Long-term protection criterion

It would seem reasonable that the radar error becomes more important over increasingly longer periods of time. For periods up to 1 min in duration it should be assumed that an increase in the angle error, due to an unwanted signal, should not exceed 5%. The long-term criterion is then an allowed unwanted signal level of -136.1 dB(W/6 MHz) for no more than 60 s.

3.3 Search and track radars

For search and track radars, the protection criteria of an interfering signal power to radar receiver noise power level, I/N , is -6 dB.
