

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

H.850.6

(11/2019)

SERIES H: AUDIOVISUAL AND MULTIMEDIA SYSTEMS

E-health multimedia systems, services and applications –
Interoperability compliance testing of personal health
systems (HRN, PAN, LAN, TAN and WAN)

**Conformance of ITU-T H.810 personal health
system: Personal Health Devices interface
Part 10F: Transcoding for Bluetooth Low
Energy: Personal Health Gateway – Pulse
oximeter**

Recommendation ITU-T H.850.6

ITU-T H-SERIES RECOMMENDATIONS
AUDIOVISUAL AND MULTIMEDIA SYSTEMS

CHARACTERISTICS OF VISUAL TELEPHONE SYSTEMS	H.100–H.199
INFRASTRUCTURE OF AUDIOVISUAL SERVICES	
General	H.200–H.219
Transmission multiplexing and synchronization	H.220–H.229
Systems aspects	H.230–H.239
Communication procedures	H.240–H.259
Coding of moving video	H.260–H.279
Related systems aspects	H.280–H.299
Systems and terminal equipment for audiovisual services	H.300–H.349
Directory services architecture for audiovisual and multimedia services	H.350–H.359
Quality of service architecture for audiovisual and multimedia services	H.360–H.369
Telepresence, immersive environments, virtual and extended reality	H.420–H.439
Supplementary services for multimedia	H.450–H.499
MOBILITY AND COLLABORATION PROCEDURES	
Overview of Mobility and Collaboration, definitions, protocols and procedures	H.500–H.509
Mobility for H-Series multimedia systems and services	H.510–H.519
Mobile multimedia collaboration applications and services	H.520–H.529
Security for mobile multimedia systems and services	H.530–H.539
Security for mobile multimedia collaboration applications and services	H.540–H.549
VEHICULAR GATEWAYS AND INTELLIGENT TRANSPORTATION SYSTEMS (ITS)	
Architecture for vehicular gateways	H.550–H.559
Vehicular gateway interfaces	H.560–H.569
BROADBAND, TRIPLE-PLAY AND ADVANCED MULTIMEDIA SERVICES	
Broadband multimedia services over VDSL	H.610–H.619
Advanced multimedia services and applications	H.620–H.629
Ubiquitous sensor network applications and Internet of Things	H.640–H.649
IPTV MULTIMEDIA SERVICES AND APPLICATIONS FOR IPTV	
General aspects	H.700–H.719
IPTV terminal devices	H.720–H.729
IPTV middleware	H.730–H.739
IPTV application event handling	H.740–H.749
IPTV metadata	H.750–H.759
IPTV multimedia application frameworks	H.760–H.769
IPTV service discovery up to consumption	H.770–H.779
Digital Signage	H.780–H.789
E-HEALTH MULTIMEDIA SYSTEMS, SERVICES AND APPLICATIONS	
Personal health systems	H.810–H.819
Interoperability compliance testing of personal health systems (HRN, PAN, LAN, TAN and WAN)	H.820–H.859
Multimedia e-health data exchange services	H.860–H.869
Safe listening	H.870–H.879

For further details, please refer to the list of ITU-T Recommendations.

Recommendation ITU-T H.850.6

Conformance of ITU-T H.810 personal health system: Personal Health Devices interface Part 10F: Transcoding for Bluetooth Low Energy: Personal Health Gateway – Pulse oximeter

Summary

Recommendation ITU-T H.850.6 provides a test suite structure (TSS) and the test purposes (TP) for the transcoding of pulse oximeter data by personal health gateways in the Personal Health Devices (PHD) interface of application-level data between the Bluetooth Low Energy Bluetooth Generic Attribute Profile (GATT) format and the IEEE 11073-20601 data format, of which Recommendation ITU-T H.810 (2016) is the base Recommendation. The objective of this test specification is to provide a high probability of interoperability at this interface.

Recommendation ITU-T H.850.6 is a transposition of clause 3.8 of Continua Test Tool DG2016, Test Suite Structure & Test Purposes, Personal Health Devices Interface; Part 10: PHD Transcoding Whitepaper. Personal Health Gateway (Version 1.7, 2017-07-18), that was developed by the Personal Connected Health Alliance. A number of versions of this specification existed before transposition.

This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

This Recommendation is part of ITU-T H.850 that was originally approved in 04/2017 as a single part, but which was split at publication time into eight sub-parts for easier use, maintenance and expandability:

- ITU-T H.850 with the general requirements;
- ITU-T H.850.1 with thermometer PHD requirements;
- ITU-T H.850.2 with blood pressure PHD requirements;
- ITU-T H.850.3 with heart rate PHD requirements;
- ITU-T H.850.4 with glucose meter PHD requirements;
- ITU-T H.850.5 with weighing scales PHD requirements;
- ITU-T H.850.6 with pulse oximeter PHD requirements;
- ITU-T H.850.7 with continuous glucose monitoring PHD requirements.

History

Edition	Recommendation	Approval	Study Group	Unique ID*
1.0	ITU-T H.850.6	2017-04-29	16	11.1002/1000/13359
2.0	ITU-T H.850.6	2019-11-29	16	11.1002/1000/14121

Keywords

Bluetooth Generic Attribute Profile, Bluetooth Low Energy (BLE), Conformance testing, Continua Design Guidelines, data format transcoding, e-health, IEEE 11073-20601, ITU-T H.810, personal area network, personal connected health devices, Personal Health Devices interface, Personal Health Gateway, pulse oximeter, touch area network.

* To access the Recommendation, type the URL <http://handle.itu.int/> in the address field of your web browser, followed by the Recommendation's unique ID. For example, <http://handle.itu.int/11.1002/1000/11830-en>.

FOREWORD

The International Telecommunication Union (ITU) is the United Nations specialized agency in the field of telecommunications, information and communication technologies (ICTs). The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of ITU. ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Assembly (WTSA), which meets every four years, establishes the topics for study by the ITU-T study groups which, in turn, produce Recommendations on these topics.

The approval of ITU-T Recommendations is covered by the procedure laid down in WTSA Resolution 1.

In some areas of information technology which fall within ITU-T's purview, the necessary standards are prepared on a collaborative basis with ISO and IEC.

NOTE

In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Compliance with this Recommendation is voluntary. However, the Recommendation may contain certain mandatory provisions (to ensure, e.g., interoperability or applicability) and compliance with the Recommendation is achieved when all of these mandatory provisions are met. The words "shall" or some other obligatory language such as "must" and the negative equivalents are used to express requirements. The use of such words does not suggest that compliance with the Recommendation is required of any party.

INTELLECTUAL PROPERTY RIGHTS

ITU draws attention to the possibility that the practice or implementation of this Recommendation may involve the use of a claimed Intellectual Property Right. ITU takes no position concerning the evidence, validity or applicability of claimed Intellectual Property Rights, whether asserted by ITU members or others outside of the Recommendation development process.

As of the date of approval of this Recommendation, ITU had not received notice of intellectual property, protected by patents, which may be required to implement this Recommendation. However, implementers are cautioned that this may not represent the latest information and are therefore strongly urged to consult the TSB patent database at <http://www.itu.int/ITU-T/ipr/>.

© ITU 2020

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without the prior written permission of ITU.

Table of Contents

	Page
1 Scope	1
2 References.....	2
3 Definitions	3
3.1 Terms defined elsewhere	3
3.2 Terms defined in this Recommendation.....	3
4 Abbreviations and acronyms	3
5 Conventions	4
6 Test suite structure	5
7 Electronic attachment	8
Annex A Test purposes	9
A.1 TP definition conventions.....	9
A.2 Subgroup 2.4.7 – Whitepaper Pulse oximeter requirements (PLX).....	11
Bibliography.....	160

Electronic attachment: This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

Introduction

This Recommendation is a transposition of clause 3.8 of Continua Test Tool DG2016, Test Suite Structure & Test Purposes, Personal Health Devices Interface; Part 10: PHD Transcoding Whitepaper. Personal Health Gateway (Version 1.7, 2017-07-18), that was developed by the Personal Connected Health Alliance. The table below shows the revision history of this test specification; it may contain versions that existed before transposition.

Version	Date	Revision history
1.0	2012-10-05	Initial release for Test Tool DG2011 based on the requirements in [b-CDG 2011].
1.1	2013-05-24	Initial release for Test Tool DG2012. It uses "TSS&TP_DG2011_LP-PAN_PART_10_v1.0.doc" as a baseline and adds new features included in [b-CDG 2012] (BPM and HR profiles).
1.2	2014-01-24	Initial release for Test Tool DG2013. It uses "TSS&TP_DG2012_LP-PAN_PART_10_v1.1.doc" as a baseline and adds new features included in [b-ITU-T H.810 (2013)]/[b-CDG 2013]: <ul style="list-style-type: none">• Adds glucose meter BLE• Adds BLE SSP support• Adds NFC new transport• Adds INR device specialization
1.3	2014-04-24	TM Lite & Doc Enhancements (Test Tool v4.0 Maintenance Release 1). It uses "TSS&TP_DG2013_LP-PAN_PART_10_v1.2.doc" as a baseline and adds new features included in Documentation Enhancements: <ul style="list-style-type: none">• "Other PICS" row has been added
1.4	2015-07-01	Initial release for Test Tool DG2015. It uses "TSS&TP_DG2013_LP-PAN_PART_10_v1.3.doc" as a baseline and adds new features included in [b-ITU-T H.810 (2015)]/[b-CDG 2015]: <ul style="list-style-type: none">• Adds WS/BCA BLE device specialization• Adds SABTE IEEE device specialization
1.5	2016-01-26	First maintenance release for Test Tool DG2015. It uses "TSS&TP_DG2015_LP-PAN_PART_10_v1.4.doc" as a baseline and adds some updates according to the Maintenance 2015 activity.
1.6	2016-09-20	Initial release for Test Tool DG2016. It uses "TSS&TP_DG2016_LP-PAN_PART_10_v1.5.doc" as a baseline and adds new features included in [ITU-T H.810 (2016)]/[b-CDG 2016]: <ul style="list-style-type: none">• Adds PLX BLE device specialization• Adds PLX CGM device specialization
1.7	2017-07-18	Second Maintenance Release for Test Tool DG2016. It uses "TSS&TP_DG2016_LP-PAN_PART_10_v1.6.doc" as a baseline and corrects minor typos.
1.8	2018-10-17	It uses version 1.7 as a baseline and adds corrections due to the inclusion of PLX BLE profile test cases.

Recommendation ITU-T H.850.6

Conformance of ITU-T H.810 personal health system: Personal Health Devices interface Part 10F: Transcoding for Bluetooth Low Energy: Personal Health Gateway – Pulse oximeter

1 Scope

The scope of this Recommendation¹ is to provide a test suite structure (TSS) and the test purposes (TP) for the Personal Health Devices interface based on the requirements defined in the Continua Design Guidelines (CDG) [ITU-T H.810 (2016)]. The objective of this test specification is to provide a high probability of interoperability at this interface.

The TSS and TP for the Personal Health Devices interface have been divided into the parts specified below. This Recommendation covers Part 10F.

- Part 1: Optimized exchange protocol. Personal Health Device
- Part 2: Optimized exchange protocol. Personal Health Gateway
- Part 3: Continua design guidelines. Personal Health Device
- Part 4: Continua design guidelines. Personal Health Gateway
- Part 5: Device specializations. Personal Health Devices interface. This document is divided into the following subparts:
 - Part 5A: Weighing scales
 - Part 5B: Glucose meter
 - Part 5C: Pulse oximeter
 - Part 5D: Blood pressure monitor
 - Part 5E: Thermometer
 - Part 5F: Cardiovascular fitness and activity monitor
 - Part 5G: Strength fitness equipment
 - Part 5H: Independent living activity hub
 - Part 5I: Adherence monitor
 - Part 5J: Insulin pump
 - Part 5K: Peak expiratory flow monitor
 - Part 5L: Body composition analyser
 - Part 5M: Basic electrocardiograph
 - Part 5N: International normalized ratio monitor
 - Part 5O: Sleep apnoea breathing therapy equipment (SABTE)
 - Part 5P: Continuous glucose monitor (CGM)
- Part 6: Device specializations. Personal Health Gateway

¹ This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

- Part 7: Continua Design Guidelines. BLE Personal Health Device
- Part 8: Continua Design Guidelines. BLE Personal Health Gateway
- Part 9: Personal Health Devices Transcoding Whitepaper. Personal Health Devices
- Part 10: Personal Health Devices Transcoding Whitepaper. Personal Health Gateway. In addition to the main part, the document is subdivided into the following subparts:
 - Part 10A: Whitepaper Thermometer requirements
 - Part 10B: Whitepaper Blood pressure requirements
 - Part 10C: Whitepaper Heart rate requirements
 - Part 10D: Whitepaper Glucose meter requirements
 - Part 10E: Whitepaper Weighing scales requirements
 - **Part 10F: Whitepaper Pulse oximeter requirements**
 - Part 10G: Whitepaper Continuous glucose monitoring requirements

2 References

The following ITU-T Recommendations and other references contain provisions which, through reference in this text, constitute provisions of this Recommendation. At the time of publication, the editions indicated were valid. All Recommendations and other references are subject to revision; users of this Recommendation are therefore encouraged to investigate the possibility of applying the most recent edition of the Recommendations and other references listed below. A list of the currently valid ITU-T Recommendations is regularly published. The reference to a document within this Recommendation does not give it, as a stand-alone document, the status of a Recommendation.

- | | |
|------------------------------|--|
| [ITU-T H.810 (2016)] | Recommendation ITU-T H.810 (2016), <i>Interoperability design guidelines for personal health systems</i> . |
| [Bluetooth PHDT v1.4] | Bluetooth SIG (2013), <i>Personal Health Devices Transcoding White Paper, v1.4</i> .
https://www.bluetooth.org/DocMan/handlers/DownloadDoc.ashx?doc_id=294539 |
| [Bluetooth PHDT v1.5] | Bluetooth SIG (2014), <i>Personal Health Devices Transcoding White Paper, v1.5</i> .
https://www.bluetooth.org/DocMan/handlers/DownloadDoc.ashx?doc_id=272346 |
| [Bluetooth PHDT v1.6] | Bluetooth SIG (2015), <i>Personal Health Devices Transcoding White Paper, v1.6</i> .
https://www.bluetooth.org/DocMan/handlers/DownloadDoc.ashx?doc_id=310657 |
| [ISO/IEEE 11073-104xx] | ISO/IEEE 11073-104xx (in force), <i>Health informatics – Personal health device communication – Device specialization</i> .
NOTE – Shorthand to refer to the collection of device specialization standards that utilize [ISO/IEEE 11073-20601-2015A], where xx can be any number from 01 to 99, inclusive. |
| [ISO/IEEE 11073-20601-2015A] | ISO/IEEE 11073-20601:2010, <i>Health informatics – Personal health device communication – Part 20601: Application profile – Optimized exchange protocol</i> , including ISO/IEEE 11073-20601:2010 Amd 1:2015.
https://www.iso.org/standard/54331.html with
https://www.iso.org/standard/63972.html |
| [ISO/IEEE 11073-20601-2016C] | ISO/IEEE 11073-20601:2016, <i>Health informatics – Personal health device communication – Part 20601: Application profile – Optimized exchange protocol</i> , including ISO/IEEE 11073-20601:2016/Cor.1:2016. |

<https://www.iso.org/standard/66717.html> with
<https://www.iso.org/standard/71886.html>

- [IHE PCD TF 1] IHE PCD TF 1 (2012), *IHE Patient Care Device Technical Framework – Revision 2.0. Volume 1: Integration Profiles*.
http://www.ihe.net/Technical_Framework/upload/IHE_PCD_TF_Rev2-0_Vol1_FT_2012-08-16.pdf
- [IHE PCD TF 2] IHE PCD TF 2 (2012), *IHE Patient Care Device Technical Framework – Revision 2.0. Volume 2: Transactions*.
http://www.ihe.net/Technical_Framework/upload/IHE_PCD_TF_Rev2-0_Vol2_FT_2012-08-16.pdf
- [IHE PCD TF 3] IHE PCD TF 3 (2012), *IHE Patient Care Device Technical Framework – Revision 2.0. Volume 3: Semantic Content*.
http://www.ihe.net/Technical_Framework/upload/IHE_PCD_TF_Rev2-0_Vol3_FT_2012-08-16.pdf

3 Definitions

3.1 Terms defined elsewhere

This Recommendation uses the following terms defined elsewhere:

3.1.1 agent [ISO/IEEE 11073-20601-2016C]: A node that collects and transmits personal health data to an associated manager.

3.1.2 manager [ISO/IEEE 11073-20601-2016C]: A node receiving data from one or more agent systems. Some examples of managers include a cellular phone, health appliance, set top box, or a computer system.

3.2 Terms defined in this Recommendation

None.

4 Abbreviations and acronyms

This Recommendation uses the following abbreviations and acronyms:

ATS	Abstract Test Suite
CDG	Continua Design Guidelines
CGM	Continuous Glucose Monitor
DUT	Device Under Test
GUI	Graphical User Interface
INR	International Normalized Ratio
IP	Insulin Pump
IUT	Implementation Under Test
LSB	Least Significant Bit
MDS	Medical Device System
MSB	Most Significant Bit
NFC	Near Field Communication
PAN	Personal Area Network
PCD	Patient Care Device

PCO	Point of Control and Observation
PCT	Protocol Conformance Testing
PHD	Personal Health Device
PHDC	Personal Healthcare Device Class
PHG	Personal Health Gateway
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation extra Information for Testing
RACP	Record Access Control Point
SABTE	Sleep Apnoea Breathing Therapy Equipment
SCR	Static Conformance Review
SDP	Service Discovery Protocol
SOAP	Simple Object Access Protocol
TCRL	Test Case Reference List
TCWG	Test and Certification Working Group
TP	Test Purposes
TSS	Test Suite Structure
USB	Universal Serial Bus
WDM	Windows Driver Model

5 Conventions

In this text, the uppercase letter L is used as the symbol for litre.

Several of the test purposes in Annex A refer to "WAN PCD-01 messages"; these messages are specified in the patient care device (PCD) technical framework defined in [IHE PCD TF 1], [IHE PCD TF 2] and [IHE PCD TF 3]. Similarly, the "IEEE 11073 Objects and Attributes" are defined in [ISO/IEEE 11073-104xx].

The key words "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "MAY", "MAY NOT" in this Recommendation are to be interpreted as in [b-ETSI SR 001 262].

- SHALL is equivalent to 'must' or 'it is required to'.
- SHALL NOT is equivalent to 'must not' or 'it is not allowed'.
- SHOULD is equivalent to 'it is recommended to'.
- SHOULD NOT is equivalent to 'it is not recommended to'.
- MAY is equivalent to 'is permitted'.
- MAY NOT is equivalent to 'it is not required that'.

NOTE – The above-mentioned key words are capitalized for illustrative purposes only and they do not appear capitalized within this Recommendation.

In this document, hexadecimal numbers are denoted either with the prefix "0x" or by "(hex)" after the number; "(dec)" after a number indicates it is expressed in decimal format.

Reference is made in the ITU-T H.800-series of Recommendations to different versions of the Continua Design Guidelines (CDG) by a specific designation. The list of terms that may be used in this Recommendation is provided in Table 1.

Table 1 – List of designations associated with the various versions of the CDG

CDG release	Transposed as	Version	Description	Designation
2016 plus errata	[ITU-T H.810 (2016)]	6.1	Release 2016 plus errata noting all ratified bugs [b-CDG 2016].	–
2016	–	6.0	Release 2016 of the CDG including maintenance updates of the CDG 2015 and additional guidelines that cover new functionalities.	Iris
2015 plus errata	[b-ITU-T H.810 (2015)]	5.1	Release 2015 plus errata noting all ratified bugs [b-CDG 2015]. The 2013 edition of ITU-T H.810 is split into eight parts in the ITU-T H.810-series.	–
2015	–	5.0	Release 2015 of the CDG including maintenance updates of the CDG 2013 and additional guidelines that cover new functionalities.	Genome
2013 plus errata	[b-ITU-T H.810 (2013)]	4.1	Release 2013 plus errata noting all ratified bugs [b-CDG 2013].	–
2013	–	4.0	Release 2013 of the CDG including maintenance updates of the CDG 2012 and additional guidelines that cover new functionalities.	Endorphin
2012 plus errata	–	3.1	Release 2012 plus errata noting all ratified bugs [b-CDG 2012].	–
2012	–	3.0	Release 2012 of the CDG including maintenance updates of the CDG 2011 and additional guidelines that cover new functionalities.	Catalyst
2011 plus errata	–	2.1	CDG 2011 integrated with identified errata.	–
2011	–	2.0	Release 2011 of the CDG including maintenance updates of the CDG 2010 and additional guidelines that cover new functionalities [b-CDG 2011].	Adrenaline
2010 plus errata	–	1.6	CDG 2010 integrated with identified errata.	–
2010	–	1.5	Release 2010 of the CDG with maintenance updates of the CDG Version 1 and additional guidelines that cover new functionalities [b-CDG 2010].	1.5
1.0	–	1.0	First released version of the CDG [b-CDG 1.0].	–

6 Test suite structure

The test purposes (TP) for the Personal Health Devices interface have been divided into the groups and subgroups specified below. Annex A describes the TPs for subgroup 2.4.7 (shown in bold).

- Group 1: Personal Health Device (PHD)
 - Group 1.1: Transport (TR)
 - Subgroup 1.1.1: Design guidelines: Common (DGC)
 - Subgroup 1.1.2: USB design guidelines (UDG)
 - Subgroup 1.1.3: Bluetooth design guidelines (BDG)
 - Subgroup 1.1.4: Pulse oximeter design guidelines (PODG)
 - Subgroup 1.1.5: Cardiovascular design guidelines (CVDG)
 - Subgroup 1.1.6: Activity hub design guidelines (HUBDG)
 - Subgroup 1.1.7: ZigBee design guidelines (ZDG)
 - Subgroup 1.1.8: Glucose meter design guidelines (GLDG)
 - Subgroup 1.1.9: Bluetooth low energy design guidelines (BLEDG)
 - Subgroup 1.1.10: Basic electrocardiograph design guidelines (ECGDG)
 - Subgroup 1.1.11: NFC design guidelines (NDG)
 - Group 1.2: IEEE 20601 Optimized exchange protocol (OXP)
 - Subgroup 1.2.1: PHD domain information model (DIM)
 - Subgroup 1.2.2: PHD service model (SER)
 - Subgroup 1.2.3: PHD communication model (COM)
 - Group 1.3: Devices class specializations (CLASS)
 - Subgroup 1.3.1: Weighing scales (WEG)
 - Subgroup 1.3.2: Glucose meter (GL)
 - Subgroup 1.3.3: Pulse oximeter (PO)
 - Subgroup 1.3.4: Blood pressure monitor (BPM)
 - Subgroup 1.3.5: Thermometer (TH)
 - Subgroup 1.3.6: Cardiovascular (CV)
 - Subgroup 1.3.7: Strength (ST)
 - Subgroup 1.3.8: Activity hub (HUB)
 - Subgroup 1.3.9: Adherence monitor (AM)
 - Subgroup 1.3.10: Insulin pump (IP)
 - Subgroup 1.3.11: Peak flow (PF)
 - Subgroup 1.3.12: Body composition analyser (BCA)
 - Subgroup 1.3.13: Basic electrocardiograph (ECG)
 - Subgroup 1.3.14: International normalized ratio (INR)
 - Subgroup 1.3.15: Sleep apnoea breathing therapy equipment (SABTE)
 - Subgroup 1.3.16: Continuous glucose monitor (CGM)
 - Group 1.4: Personal health device transcoding whitepaper (PHDTW)
 - Subgroup 1.4.1: Whitepaper general requirements (GEN)
 - Subgroup 1.4.2: Whitepaper thermometer requirements (TH)
 - Subgroup 1.4.3: Whitepaper blood pressure requirements (BPM)
 - Subgroup 1.4.4: Whitepaper heart rate requirements (HR)
 - Subgroup 1.4.5: Whitepaper glucose meter requirements (GL)
 - Subgroup 1.4.6: Whitepaper weight scale requirements (WS)

- Subgroup 1.4.7: Whitepaper pulse oximeter requirements (PLX)
- Subgroup 1.4.8: Whitepaper continuous glucose monitoring requirements (CGM)
- Group 2: Personal Health Gateway (PHG)
 - Group 2.1: Transport (TR)
 - Subgroup 2.1.1: Design guidelines: Common (DGC)
 - Subgroup 2.1.2: USB design guidelines (UDG)
 - Subgroup 2.1.3: Bluetooth design guidelines (BDG)
 - Subgroup 2.1.4: Cardiovascular design guidelines (CVDG)
 - Subgroup 2.1.5: Activity hub design guidelines (HUBDG)
 - Subgroup 2.1.6: ZigBee design guidelines (ZDG)
 - Subgroup 2.1.7: Bluetooth low energy design guidelines (BLEDG)
 - Subgroup 2.1.8: NFC design guidelines (NDG)
 - Group 2.2: IEEE 20601 Optimized exchange protocol (OXP)
 - Subgroup 2.2.1: General (GEN)
 - Subgroup 2.2.2: PHD domain information model (DIM)
 - Subgroup 2.2.3: PHD service model (SER)
 - Subgroup 2.2.4: PHD communication model (COM)
 - Group 2.3: Devices class specializations (CLASS)
 - Subgroup 2.3.1: Weighing scales (WEG)
 - Subgroup 2.3.2: Glucose meter (GL)
 - Subgroup 2.3.3: Pulse oximeter (PO)
 - Subgroup 2.3.4: Blood pressure monitor (BPM)
 - Subgroup 2.3.5: Thermometer (TH)
 - Subgroup 2.3.6: Cardiovascular (CV)
 - Subgroup 2.3.7: Strength (ST)
 - Subgroup 2.3.8: Activity hub (HUB)
 - Subgroup 2.3.9: Adherence monitor (AM)
 - Subgroup 2.3.10: Insulin pump (IP)
 - Subgroup 2.3.11: Peak flow (PF)
 - Subgroup 2.3.12: Body composition analyser (BCA)
 - Subgroup 2.3.13: Basic electrocardiograph (ECG)
 - Subgroup 2.3.14: International normalized ratio (INR)
 - Subgroup 2.3.15: Sleep apnoea breathing therapy equipment (SABTE)
 - Subgroup 2.3.16: Continuous glucose monitor (CGM)
 - Group 2.4: Personal health device transcoding whitepaper (PHDTW)
 - Subgroup 2.4.1: Whitepaper general requirements (GEN)
 - Subgroup 2.4.2: Whitepaper thermometer requirements (TH)
 - Subgroup 2.4.3: Whitepaper blood pressure measurement requirements (BPM)
 - Subgroup 2.4.4: Whitepaper heart rate requirements (HR)
 - Subgroup 2.4.5: Whitepaper glucose meter requirements (GL)
 - Subgroup 2.4.6: Whitepaper weight scale requirements (WS)

- **Subgroup 2.4.7: Whitepaper pulse oximeter requirements (PLX)**
- Subgroup 2.4.8: Whitepaper continuous glucose monitoring requirements (CGM)

7 Electronic attachment

The protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A can be downloaded from <http://handle.itu.int/11.1002/2000/12067>.

In the electronic attachment, letters "C" and "I" in the column labelled "Mandatory" are used to distinguish between "PICS" and "PIXIT" respectively during testing. If the cell is empty, the corresponding PICS is "independent". If the field contains a "C", the corresponding PICS is dependent on other PICS, and the logical expression is detailed in the "SCR_Expression" field. The static conformance review (SCR) is used in the test tool to assert whether the PICS selection is consistent.

Annex A

Test purposes

(This annex forms an integral part of this Recommendation.)

A.1 TP definition conventions

The test purposes (TPs) are defined according to the following rules:

- **TP Id:** This is a unique identifier (TP/<TT>/<DUT>/<GR>/<SGR>/<XX> – <NNN>). It is specified according to the naming convention defined below:
 - Each test purpose identifier is introduced by the prefix "TP".
 - <TT>: This is the test tool that will be used in the test case.
 - PAN: Personal area network (Bluetooth or USB)
 - LAN: Local area network (ZigBee)
 - PAN-LAN: Personal area network (Bluetooth or USB) – Local area network (ZigBee)
 - LP-PAN: Low power personal area network (Bluetooth low energy)
 - TAN: Touch area network (NFC)
 - PLT: Personal area network (Bluetooth or USB) – Local area network (ZigBee) – Touch area network (NFC)
 - <DUT>: This is the device under test.
 - PHD: Personal Health Device
 - PHG: Personal Health Gateway
 - <GR>: This identifies a group of test cases.
 - <SGR>: This identifies a subgroup of test cases.
 - <XX>: This identifies the type of testing.
 - BV: Valid behaviour test
 - BI: Invalid behaviour test
 - <NNN>: This is a sequential number that identifies a test purpose.
- **TP label:** This is the TP's title.
- **Coverage:** This contains the specification reference and clause to be checked by the TP.
 - Spec: This indicates the earliest version of the specification from which the testable items to be checked by the TP were included.
 - Testable item: This contains the testable items to be checked by the TP.
- **Test purpose:** This is a description of the requirements to be tested.
- **Applicability:** This contains the PICS items that define if the test case is applicable or not for a specific device. When a TP contains an "ALL" in this field it means that it applies to the device under test within that scope of the test (specialization, transport used, etc.).
- **Other PICS:** This contains additional PICS items (apart from the PICS specified in the Applicability row) which are used within the test case implementation and can modify the final verdict. When this row is empty, it means that only the PICS specified in the Applicability row are used within the test case implementation.
- **Initial condition:** This indicates the state to which the DUT needs to be moved at the beginning of TC execution.

- **Test procedure:** This describes the steps to be followed in order to execute the test case.
- **Pass/Fail criteria:** This provides criteria to decide whether the DUT passes or fails the test case.

A.2 Subgroup 2.4.7 – Whitepaper Pulse oximeter requirements (PLX)

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-000		
TP label		Whitepaper. Pulse Oximeter MDS Object - System-Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PLX Specific MDS 1; M		
Test purpose		Check that: PHG does not include MDS object, System-Type attribute in transcoder output.		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a measurement ready to be sent and it is in the Advertising state (it is discoverable). 2. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 3. When the pairing has been completed (Connection state) the simulated PHD sends the Measurement to the PHG under test. 4. Check in PHG transcoder output the MDS object, System-Type attribute 		
Pass/Fail criteria		In Step 4, the MDS object, System-Type attribute is not present.		
Notes (To assist manual testing)		<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes System-Type attribute is not present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: MDS Object <input type="checkbox"/> Attribute-id: MDC_ATTR_SYS_TYPE (2438) <input type="checkbox"/> Attribute-type: TYPE <input type="checkbox"/> Attribute-value: <NOT PRESENT> b) WAN PCD-01 message PCD-01 message does not include segments with System-Type attribute value (67974^MDC_ATTR_SYS_TYPE^MDC) 		

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-001		
TP label		Whitepaper. Pulse Oximeter MDS Object - Dev-Configuration-Id Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	Common MDS 17; M		
Test purpose		Check that: PHG includes MDS object, Dev-Configuration-Id attribute in transcoder output. [AND] Dev-Configuration-Id value is set to any value in range of 0x4000 to 0x7FFF (Extended Configuration)		

Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test Procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a measurement ready to be sent and it is in the Advertising state (it is discoverable). 2. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 3. When the pairing has been completed (Connection state) the simulated PHD sends the Measurement to the PHG under test. 4. Check in PHG transcoder output the MDS object, Dev-Configuration-Id attribute
Pass/Fail criteria	In Step 4, the MDS object, Dev-Configuration-Id attribute is present, its value is inside the range 0x4000 - 0x7FFF
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes Dev-Configuration-Id attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: MDS Object <input type="checkbox"/> Attribute-id: MDC_ATTR_DEV_CONFIG_ID (2628) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value inside the range 16384 - 32767 (dec) or 0x4000 – 0x7FFF (hex) b) WAN PCD-01 message According to Continua DG, the Dev-Configuration-Id shall not be transmitted in PCD-01 message, therefore it is not possible to check this attribute.

TP Id	TP/LP-PAN/PHG/PHDTW/PLX/BV-002		
TP label	Whitepaper. Pulse Oximeter MDS Object - System-Type-Spec-List Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]	
	Testable items	Common MDS 15; M	PLX Specific MDS 2; M
Test purpose	<p>Check that:</p> <p>PHG includes MDS object, System-Type-Spec-List attribute in transcoder output.</p> <p>[AND]</p> <p>System-Type-Spec-List is set to (MDC_DEV_SPEC_PROFILE_PULS_OXIM, Version 1)</p>		
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS			
Initial condition	The PHG under test and the simulated PHD are in the Standby state.		
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a measurement ready to be sent and it is in the Advertising state (it is discoverable). 2. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 3. When the pairing has been completed (Connection state) the simulated PHD sends the Measurement to the PHG under test. 		

	4. Check in PHG transcoder output the MDS object, System-Type-Spec-List attribute
Pass/Fail criteria	In Step 4, the MDS object, System-Type-Spec-List attribute is present, its value is (MDC_DEV_SPEC_PROFILE_PULS_OXIM, Version 1)
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>System-Type-Spec-List attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: MDS Object <input type="checkbox"/> Attribute-id: MDC_ATTR_SYS_TYPE_SPEC_LIST (2650) <input type="checkbox"/> Attribute-type: SEQUENCE OF [{type (INT-U16), version (INT-U16)}] <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • type: MDC_DEV_SPEC_PROFILE_PULS_OXIM, 4100 (dec) or 10 04 (hex) • version: 1 (dec) or 00 01 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with System-Type-Spec-List attribute value (check OBX-5):</p> <pre>OBX ? NM 68186^MDC_ATTR_SYS_TYPE_SPEC_LIST^MDC 1.0.0.a 528388^MDC_DEV_SPEC_PROFILE_PULS_OXIM^MDC R</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-003		
TP label		Whitepaper. Pulse Oximeter MDS Object - Reg-Cert-Data-List Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	Common MDS 14; M	Regulatory Conv 1; M	
Test purpose		<p>Check that:</p> <p>PHG transcodes IEEE 11073-20601 Regulatory Certification Data List characteristic into MDS object, Reg-Cert-Data-List attribute</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a measurement ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is: <ol style="list-style-type: none"> a. IEEE 11073-20601 Regulatory Certification Data List (0x2A2A) <ul style="list-style-type: none"> • Format: reg-cert-data-list (opaque structure) • Value: 00 02 00 12 02 01 00 08 06 01 00 01 00 02 80 04 02 02 00 02 80 00 (hex) <ol style="list-style-type: none"> i. Element: <ul style="list-style-type: none"> • auth-body-and-struct-type: <ul style="list-style-type: none"> - auth-body: 02 (hex) auth-body-continua(2) - auth-body-struct-type: 01 (hex). continua-version-struct(1) • auth-body-data: 		

	<ul style="list-style-type: none"> - major-IG-version: 06 (hex) - minor-IG-version: 01 (hex) - certified-devices: 80 04 (hex) BTLE Pulse Oximeter <p>ii. Element:</p> <ul style="list-style-type: none"> • auth-body-and-struc-type: <ul style="list-style-type: none"> - auth-body: 02 (hex). auth-body-continua(2) - auth-body-struc-type: 02 (hex). continua-reg-struct(2) • auth-body-data: <ul style="list-style-type: none"> - regulation-bit-field: 80 00 (hex). Unregulated device <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD.</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read IEEE 11073-20601 Regulatory Certification Data List characteristic.</p> <p>5. Check in PHG transcoder output the MDS object, Reg-Cert-Data-List attribute</p>
Pass/Fail criteria	In Step 5, the MDS object, Reg-Cert-Data-List attribute is present and its value matches with IEEE 11073-20601 Regulatory Certification Data List characteristic value
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Reg-Cert-Data-List attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: MDS Object <input type="checkbox"/> Attribute-id: MDC_ATTR_REG_CERT_DATA_LIST (2635) <input type="checkbox"/> Attribute-type: SEQUENCE OF [{auth-body-and-struc-type, auth-body-data}, {...}] <input type="checkbox"/> Attribute-value: 00 02 00 12 02 01 00 08 06 01 00 01 00 02 80 04 02 02 00 02 80 00 (hex) [Note that 0x00 0x02 is the number of elements in the sequence and 0x00 0x12 is the length of the sequence] <p>i. Reg-Cert-Data Element:</p> <ul style="list-style-type: none"> • auth-body-and-struc-type: <ul style="list-style-type: none"> - auth-body: 02 (hex) auth-body-continua(2) - auth-body-struc-type: 01 (hex). continua-version-struct(1) • auth-body-data: <ul style="list-style-type: none"> - major-IG-version: 06 (hex) - minor-IG-version: 01 (hex) - certified-devices: 80 04 (hex). BTLE Pulse Oximeter <p>ii. Reg-Cert-Data Element:</p> <ul style="list-style-type: none"> • auth-body-and-struc-type: <ul style="list-style-type: none"> - auth-body: 02 (hex). auth-body-continua(2) - auth-body-struc-type: 02 (hex). continua-reg-struct(2) • auth-body-data: <ul style="list-style-type: none"> - regulation-bit-field: 80 00 (hex). Unregulated device <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes five segments like these with Reg-Cert-Data-List attribute value (check OBX-5 in five segments):</p> <p>OBX ? CWE 68218^MDC_REG_CERT_DATA_AUTH_BODY^MDC 1.0.0.a 2^auth-body-continua R</p> <p>OBX ? ST 532352^MDC_REG_CERT_DATA_CONTINUA_VERSION^MDC 1.0.0.a.x 6.1 R</p>

	<p>OBX ? NA 532353^MDC_REG_CERT_DATA_CONTINUA_CERT_DEV_LIST^MDC 1.0.0.a.y 32772 R</p> <p>OBX ? CWE 68218^MDC_REG_CERT_DATA_AUTH_BODY^MDC 1.0.0.b 2^auth-body-continua R</p> <p>OBX ? CWE 532354^MDC_REG_CERT_DATA_CONTINUA_REG_STATUS^MDC 1.0.0.b.z 1^unregulated-device(0) R</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-004		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 1; O		
Test purpose		<p>Check that:</p> <p>PHG does not include SpO2 Numeric object, Handle Attribute in transcoder output when using spot-check measurement mode.</p> <p>[OR]</p> <p>If PHG includes SpO2 Numeric object, Handle attribute in transcoder output, then its value shall be different than 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported. Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric object, Handle attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric object, Handle attribute</p>		
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric object, Handle attribute is not present or, if it is present then its value is different than 0</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b</p>		
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>		

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-005		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 11; O		

Test purpose	<p>Check that:</p> <p>PHG does not include SpO2 Numeric object, Handle Attribute in transcoder output when using continuous measurements</p> <p>[OR]</p> <p>If PHG includes SpO2 Numeric object, Handle attribute in transcoder output, then its value shall be different than 0</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm)

	<ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric object, Handle attribute in all three SpO2 objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • There are three SpO2 objects (for normal, fast and slow measurement modes). • In all three objects, the SpO2 Numeric object, Handle attribute is not present or, if it is present then its value is different than 0
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present in SpO2 objects, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-006		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 2; M		
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric object, Type attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_SAT_O2}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		

Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported. ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the SpO2 Numeric object, Type attribute 7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test
-----------------------	---

	b. Check in PHG transcoder output the SpO2 Numeric object, Type attribute
Pass/Fail criteria	In Step 6, the SpO2 Numeric object, Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_SAT_O2} If the PHG supports RACP, the same criteria applies to Step 7.b
Notes (To assist manual testing)	Possible values in typical points of observation after transcoder output are: a) IEEE 11073 Objects and Attributes Type attribute is present: <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type : SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) code: MDC_PULS_OXIM_SAT_O2 or 19384 (dec) or 4B B8 (hex) b) WAN PCD-01 message PCD-01 message includes a segment like this with Type attribute (check OBX-3): OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-007		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 12; M		
Test purpose		Check that: PHG includes SpO2 Numeric object, Type attribute in transcoder output when using continuous measurements. [AND] Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_SAT_O2}		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Feature (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Field: Measurement Status Support 		

	<ul style="list-style-type: none"> • This field is not included <p>iii. Field: Device and Sensor Status Support</p> <ul style="list-style-type: none"> • This field is not included <p>b. PLX Continuous Measurement (0x2A5F)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. <p>ii. Field: SpO2PR-Normal - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iii. Field: SpO2PR-Normal – PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iv. Field: SpO2PR-Fast - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>v. Field: SpO2PR-Fast - PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>vi. Field: SpO2PR-Slow - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>vii. Field: SpO2PR-Slow - PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric object, Type attribute in all three SpO2 objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • There are three SpO2 objects (for normal, fast and slow measurement modes). • In all three objects, the SpO2 Numeric object, Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_SAT_O2}

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Type attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) • code: MDC_PULS_OXIM_SAT_O2 or 19384 (dec) or 4B B8 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes three segments like this with Type attribute (check OBX-3):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</pre>
---	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-008		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Supplemental-Types Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 3; M		
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric object, Supplemental-Types attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_SPOT}.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). Simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported. ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 		

	<p>b. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric object, Supplemental-Types attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric object, Supplemental-Types attribute</p>
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric object, Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_SPOT}.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Supplemental-Types attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object (Spot-Check measurement) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SPOT}. <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a facet OBX segment of the SpO2 measurement OBX segment</p>

	<p>with Supplemental-Types attribute (check OBX-3 and OBX-5):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</p> <p>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_SPOT^MDC R</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-009		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Supplemental-Types Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 13; M	SpO2 Numeric 14; M	SpO2 Numeric 15; M
Test purpose		<p>Check that:</p> <p>PHG does not include SpO2 Numeric object, Supplemental-Types attribute in transcoder output for the SpO2 continuous measurement object (normal).</p> <p>[AND]</p> <p>PHG includes SpO2 Numeric object, Supplemental-Types attribute in transcoder output for the SpO2 continuous measurement object (fast mode). Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_FAST}.</p> <p>[AND]</p> <p>PHG includes SpO2 Numeric object, Supplemental-Types attribute in transcoder output for the SpO2 continuous measurement object (slow mode). Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_SLOW}.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Feature (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. 		

	<ul style="list-style-type: none"> ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric object, Supplemental-Types attribute in all three SpO2 objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • The SpO2 Numeric Object (normal) – Supplemental-Types attribute is not present • The SpO2 Numeric Object (fast response) Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_FAST}. • The SpO2 Numeric Object (slow response) Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_SLOW}.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Supplemental Types attribute is not present for SpO2 Numeric Object (normal).</p> <p>Supplemental-Types attribute is present for SpO2 Numeric Object (fast response):</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object (fast response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)}

	<p>❑ Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}.</p> <p>Supplemental-Types attribute is present for SpO2 Numeric Object (slow response):</p> <p>❑ Object: SpO2 Numeric Object (slow response)</p> <p>❑ Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657)</p> <p>❑ Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)}</p> <p>❑ Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}.</p> <p>b) WAN PCD-01 message</p> <p>For SpO2 Numeric Object (normal)</p> <ul style="list-style-type: none"> PCD-01 message does not include segments with Supplemental-Types attribute. <p>For SpO2 Numeric Object (fast)</p> <ul style="list-style-type: none"> PCD-01 message includes a facet OBX segment of the SpO2 measurement OBX segment with Supplemental-Types attribute (check OBX-3 and OBX-5): <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R current_date_time]</p> <p>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_FAST^MDC R</p> <ul style="list-style-type: none"> For SpO2 Numeric Object (slow) <p>PCD-01 message includes a facet OBX segment of the SpO2 measurement OBX segment with Supplemental-Types attribute (check OBX-3 and OBX-5):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.y [value] 262688^MDC_DIM_PERCENT^MDC R current_date_time]</p> <p>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.y.z 150580^MDC_MODALITY_SLOW^MDC R</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-010		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 4; M	SpO2 Numeric 6; M	
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric object, Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x5040} when the sensor device supports measurement storage.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). Simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Spot-Check Measurement (0x2A5E) PLX Feature (0x2A60) 		

	<ul style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test with the following value:</p> <ul style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is supported. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>6. Check in PHG transcoder output the SpO2 numeric object, Metric-Spec-Small attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 numeric object, Metric-Spec-Small attribute
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Metric-Spec-Small attribute is present and its value is {0x5040} (mss-avail-stored-data mss-msmt-aperiodic mss-acc-agent-initiated).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b</p>

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 50 40 (hex) or BITS mss-avail-stored-data (1), mss- msmt - aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>
---	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-011		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 4; M	SpO2 Numeric 5; M	
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x1040} when the sensor device does not support measurement storage.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The Ssimulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 0000 (MSB → LSB). Measurement Storage for Spot-check measurements is not supported (bit 2). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to 		

	<p>read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test with the following value:</p> <p>a. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0000 (MSB → LSB). Timestamp, Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> This field is not included <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Metric-Spec-Small attribute</p>		
Pass/Fail criteria	In Step 6, the SpO2 Numeric Object – Metric-Spec-Small attribute is present and its value is {0x1040} (mss-msmt-aperiodic mss-acc-agent-initiated).		
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 10 40 (hex) or BITS mss-msmt-aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>		

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-012		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) - Metric-Spec-Small Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 16; M		
Test purpose		Check that:		

	<p>PHG includes SpO2 Numeric Object – Metric-Spec-Small attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x0040} (mss-acc-agent-initiated)</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR–Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR–Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR–Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT

	<ul style="list-style-type: none"> Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Metric-Spec-Small attribute in all three SpO2 objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> There are three SpO2 objects (for normal, fast and slow measurement modes). In all three objects, the SpO2 Numeric Object – Metric-Spec-Small attribute is present and its value is {0x0040} (mss-acc-agent-initiated).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 00 40 (hex) or BITS mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-013		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Measurement-Status Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 7; M		
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric Object – Measurement-Status attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Measurement Status field of the PLX Spot-Check characteristic to 11073 Measurement-Status attribute properly</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). Simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1101 (MSB → LSB). Measurement Status support is present (bit 0). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • Format: 16 bit • Value: 1111 1111 1110 0000 (MSB → LSB). All Measurement Status bits are supported iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. 5. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). Measurement Status and Timestamp fields are present. Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • This field is not included v. Field: Measurement Status <ul style="list-style-type: none"> • Format: 16 bit • Value: 1000 0000 0000 0000 (MSB → LSB). Invalid measurement detected (bit 15). vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%)

	<ul style="list-style-type: none"> • This field is not included
	<ol style="list-style-type: none"> 6. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 8. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0100 0000 0000 0000 (MSB → LSB), questionable measurement detected (bit 14). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 9. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 10. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 11. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0010 0000 0000 0000 (MSB → LSB), measurement not available (bit 13). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 12. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 13. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 14. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0001 0000 0000 0000 (MSB → LSB), calibration ongoing (bit 12). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 15. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 16. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 17. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 1000 0000 0000 (MSB → LSB), data for testing (bit 11). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 18. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute 19. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN

	<ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute <p>20. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0100 0000 0000 (MSB → LSB), data for demonstration (bit 10). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>21. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute</p> <p>22. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute <p>23. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 1000 0000 (MSB → LSB), fully qualified data (bit 7). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>24. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute</p> <p>25. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute <p>26. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0100 0000 (MSB → LSB), early estimated data (bit 6). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>27. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute</p> <p>28. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute <p>29. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0010 0000 (MSB → LSB), measurement ongoing (bit 5). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>30. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute</p> <p>31. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute
--	---

	attribute
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “invalid” (0x8000). If PHG supports RACP, same criteria applies to 7.b.</p> <p>In Step 9, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “questionable” (0x4000). If PHG supports RACP, same criteria applies to 10.b.</p> <p>In Step 12, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “not-available” (0x2000). If PHG supports RACP, same criteria applies to 13.b.</p> <p>In Step 15, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “calibration-ongoing” (0x1000). If PHG supports RACP, same criteria applies to 16.b.</p> <p>In Step 18, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “test-data” (0x0800). If PHG supports RACP, same criteria applies to 19.b.</p> <p>In Step 21, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “demo-data” (0x0400). If PHG supports RACP, same criteria applies to 22.b.</p> <p>In Step 24, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “validated-data” (0x0080). If PHG supports RACP, same criteria applies to 25.b.</p> <p>In Step 27, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “early-indication” (0x0040). If PHG supports RACP, same criteria applies to 28.b.</p> <p>In Step 30, the SpO2 Numeric Object – Measurement-Status attribute is present and its set to “msmt-ongoing” (0x0020). If PHG supports RACP, same criteria applies to 31.b.</p>
Notes (To assist manual testing)	<p>In step 6 (and step 7.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 80 00 (hex) <p>b) WAN PCD-01 message PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC INV X current_date_time]</pre> <p>In step 9 (and step 10.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC QUES R current_date_time]</pre> <p>In step 12 (and step 13.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes Measurement-Status attribute is present:</p>

	<div data-bbox="470 168 1018 331"> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 20 00 (hex) </div> <div data-bbox="422 344 726 376"> <p>b) WAN PCD-01 message</p> </div> <div data-bbox="470 387 1404 445"> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> </div> <div data-bbox="518 459 1281 517"> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC NAV X current_date_time]</pre> </div> <div data-bbox="422 530 1412 589"> <p>In step 15 (and step 16.b if applicable), possible values in typical points of observation after transcoder output are:</p> </div> <div data-bbox="422 602 845 631"> <p>a) IEEE 11073 Objects and Attributes</p> </div> <div data-bbox="470 645 908 674"> <p>Measurement-Status attribute is present:</p> </div> <div data-bbox="470 687 1018 851"> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 10 00 (hex) </div> <div data-bbox="422 864 726 893"> <p>b) WAN PCD-01 message</p> </div> <div data-bbox="470 907 1404 965"> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> </div> <div data-bbox="518 978 1281 1037"> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC CAL R current_date_time]</pre> </div> <div data-bbox="422 1050 1404 1108"> <p>In step 18 (and step 19.b if applicable), possible values in typical points of observation after transcoder output are:</p> </div> <div data-bbox="422 1122 845 1151"> <p>a) IEEE 11073 Objects and Attributes</p> </div> <div data-bbox="470 1164 908 1193"> <p>Measurement-Status attribute is present:</p> </div> <div data-bbox="470 1207 1018 1370"> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 08 00 (hex) </div> <div data-bbox="422 1384 726 1413"> <p>b) WAN PCD-01 message</p> </div> <div data-bbox="470 1426 1404 1485"> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> </div> <div data-bbox="518 1498 1281 1556"> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC TEST R current_date_time]</pre> </div> <div data-bbox="422 1570 1412 1628"> <p>In step 21 (and step 22.b if applicable), possible values in typical points of observation after transcoder output are:</p> </div> <div data-bbox="422 1641 845 1671"> <p>a) IEEE 11073 Objects and Attributes</p> </div> <div data-bbox="470 1684 908 1713"> <p>Measurement-Status attribute is present:</p> </div> <div data-bbox="470 1727 1018 1890"> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 04 00 (hex) </div> <div data-bbox="422 1904 726 1933"> <p>b) WAN PCD-01 message</p> </div> <div data-bbox="470 1946 1404 2004"> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> </div> <div data-bbox="518 2018 1281 2076"> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC DEMO R current_date_time]</pre> </div>
--	---

		<p>In step 24 (and step 25.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 80 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC F current_date_time]</pre> <p>In step 27 (and step 28.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 40 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC EARLY R current_date_time]</pre> <p>In step 30 (and step 31.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC BUSY X current_date_time]</pre>
--	--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-014		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Measurement-Status Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 17; M		

Test purpose	<p>Check that:</p> <p>PHG includes SpO2 Numeric Object – Measurement-Status attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Measurement Status field of the PLX Continuous Measurement characteristic to 11073 Measurement-Status attribute properly</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Continuous Measurement (0x2A5F) b. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0001 (MSB → LSB). Measurement Status support is present (bit 0). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • Format: 16 bit • Value: 1111 1111 1110 0000 (MSB → LSB). All Measurement Status bits are supported iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. 5. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> a. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0111 (MSB → LSB). Measurement Status, SpO2PR–Fast and SpO2PR–Slow fields are present. Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT

	<ul style="list-style-type: none"> • Value: Not Relevant
	<ul style="list-style-type: none"> v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant
	<ul style="list-style-type: none"> vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant
	<ul style="list-style-type: none"> vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant
	<ul style="list-style-type: none"> viii. Field: Measurement Status <ul style="list-style-type: none"> • Format: 16 bit • Value: 1000 0000 0000 0000 (MSB → LSB). Invalid measurement detected (bit 15).
	<ul style="list-style-type: none"> ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included
	<ul style="list-style-type: none"> x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included
6.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
7.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0100 0000 0000 0000 (MSB → LSB), questionable measurement detected (bit 14). All remaining fields remain equal to those in step 5.
8.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
9.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0010 0000 0000 0000 (MSB → LSB), measurement not available (bit 13). All remaining fields remain equal to those in step 5.
10.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
11.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0001 0000 0000 0000 (MSB → LSB), calibration ongoing (bit 12). All remaining fields remain equal to those in step 5.
12.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
13.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 1000 0000 0000 (MSB → LSB), data for testing (bit 11). All remaining fields remain equal to those in step 5.
14.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
15.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0100 0000 0000 (MSB → LSB), data for demonstration (bit 10). All remaining fields remain equal to those in step 5.
16.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
17.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 1000 0000 (MSB → LSB), fully qualified data (bit 7). All remaining fields remain equal to those in step 5.
18.	Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.
19.	Simulated PHD sends a Measurement to PHG under test with Measurement Status field

	<p>set to 0000 0000 0100 0000 (MSB → LSB), early estimated data (bit 6). All remaining fields remain equal to those in step 5.</p> <p>20. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.</p> <p>21. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0010 0000 (MSB → LSB), measurement ongoing (bit 5). All remaining fields remain equal to those in step 5.</p> <p>22. Check in PHG transcoder output the SpO2 Numeric Object – Measurement-Status attribute in all three SpO2 objects.</p>
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “invalid” (0x8000)</p> <p>In Step 8, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “questionable” (0x4000)</p> <p>In Step 10, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “not-available” (0x2000)</p> <p>In Step 12, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “calibration-ongoing” (0x1000)</p> <p>In Step 14, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “test-data” (0x0800)</p> <p>In Step 16, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “demo-data” (0x0400)</p> <p>In Step 18, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “validated-data” (0x0080)</p> <p>In Step 20, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “early-indication” (0x0040)</p> <p>In Step 22, the SpO2 Numeric Object – Measurement-Status attribute is present in all three SpO2 objects and its set to “msmt-ongoing” (0x0020)</p>
Notes (To assist manual testing)	<p>In step 6, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 80 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like for each SpO2 object this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC INV X current_date_time]</pre> <p>In step 8, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] </pre>

	<p>262688^MDC_DIM_PERCENT^MDC QUES R [current_date_time]</p> <p>In step 10, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 20 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p style="padding-left: 40px;">OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC NAV X [current_date_time]</p> <p>In step 12, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 10 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p style="padding-left: 40px;">OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC CAL R [current_date_time]</p> <p>In step 14, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 08 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p style="padding-left: 40px;">OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC TEST R [current_date_time]</p> <p>In step 16, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 04 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p>
--	---

	<p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC DEMO R [[current_date_time]]</p> <p>In step 18, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 80 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC F [[current_date_time]]</p> <p>In step 20, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 40 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC EARLY R [[current_date_time]]</p> <p>In step 22, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC BUSY X [[current_date_time]]</p>		
--	---	--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-015		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 8; M		
Test purpose		Check that:		

	<p>PHG includes SpO2 Numeric Object –Unit-Code attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_PERCENT</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	C_MAN_BLE_042
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: Time Stamp <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> This field is not included The PHG under test initiates a discovery process (Scanning state), it discovers the

	<p>simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <ol style="list-style-type: none"> 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the SpO2 Numeric Object – Unit-Code attribute 7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Unit-Code attribute
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Unit-Code attribute is present and its set to MDC_DIM_PERCENT.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes <p>Unit-Code attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: MDC_DIM_PERCENT or 544 (dec) or 02 20 (hex) b) WAN PCD-01 message <p>PCD-01 message includes a segment like this with Unit-Code attribute value (check OBX-6):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-016		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 18; M		
Test purpose		<p>Check that:</p> <p>PHG includes SpO2 Numeric Object – Unit-Code attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_PERCENT</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of 		

	<p>interest for this Test Case are:</p> <ol style="list-style-type: none"> a. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. 5. The simulated PHD sends the Measurement to the PHG under test.
--	---

	6. Check in PHG transcoder output the SpO2 Numeric Object – Unit-Code attribute in all three SpO2 objects (continuous normal, fast and slow).
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> There are three SpO2 objects (for normal, fast and slow measurement modes). In all three objects, the SpO2 Numeric Object – Unit-Code attribute is present and its set to MDC_DIM_PERCENT.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Unit-Code attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: MDC_DIM_PERCENT or 544 (dec) or 02 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Unit-Code attribute value (check OBX-6):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-017		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Absolute-Time-Stamp Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 9; M	Date-Time Conv 2; M	Date-Time Conv 3; M
		Date-Time Conv 4; M	Date-Time Conv 5; M	
Test purpose		Check that: PHG transcodes Time Stamp field of Spot-Check Measurement characteristic into SpO2 Numeric Object - Absolute-Time-Stamp attribute [AND] PHG transcodes the Bluetooth Time Stamp field format to Absolute Time format [AND] The fraction of seconds in Absolute Time at transcoder output is 0		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: a. PLX Features (0x2A60) i. Field: Supported Features		

	<ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). <p>ii. Field: Measurement Status Support</p> <ul style="list-style-type: none"> • This field is not included <p>iii. Field: Device and Sensor Status Support</p> <ul style="list-style-type: none"> • This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> • Format: Date and Time • Value: October 12nd, 2015, 10:39:27 <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Absolute-Time-Stamp attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric Object – Absolute-Time-Stamp attribute</p>
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Absolute-Time-Stamp attribute is present, its value matches with Time Stamp field of Spot-Check Measurement characteristic and fraction of seconds is set to 0.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Absolute-Time-Stamp attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_TIME_STAMP_ABS (2448) <input type="checkbox"/> Attribute-type: SEQUENCE {century (INT-U8), year (INT-U8), month (INT-U8), day (INT-U8), hour (INT-U8), minute (INT-U8), second (INT-U8), sec-fractions (INT-U8)} (BCD encoding) <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • century: 20 (hex) or 32 (dec) • year: 15 (hex) or 21 (dec) • month: 10 (hex) or 16 (dec) • day: 12 (hex) or 18 (dec) • hour: 10 (hex) or 16 (dec) • minute: 39 (hex) or 57 (dec) • second: 27 (hex) or 39 (dec) • sec-fractions: 00 (hex) or 0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Absolute-Time-Stamp attribute value (check OBX-14):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R 20151012103927+0000</pre>
---	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-018		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 10; M	Short Float Type 1; C	
Test purpose		Check that: PHG transcodes SpO2 value of the SpO2PR-Spot-Check field in PLX Spot-Check Measurement characteristic into SpO2 Numeric Object - Basic-Nu-Observed-Value attribute		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit 		

	<ul style="list-style-type: none"> Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). <p>ii. Field: Measurement Status Support</p> <ul style="list-style-type: none"> This field is not included <p>iii. Field: Device and Sensor Status Support</p> <ul style="list-style-type: none"> This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: 96.0 (%) <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute</p>
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the SpO2 subfield of the SpO2PR-Spot-Check field in the PLX Spot-Check Measurement characteristic (96.0%).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual	<p>Possible values in typical points of observation after transcoder output are:</p>

testing)	<p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 60 (hex) or F3C0 (hex) or 96.0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <p style="text-align: center;">OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x 96.0 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</p>
-----------------	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-019		
TP label		Whitepaper. SpO2 Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 10; M	SpO2 Numeric 20; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes SpO2 value of the SpO2PR-Spot-Check field in PLX Spot-Check Measurement characteristic into SpO2 Numeric Object - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG assigns special value NaN (0x07FF) when SpO2 value is unavailable.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags 		

	<ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute</p>
Pass/Fail criteria	<p>In Step 6, the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <p>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x</p>

	262688^MDC_DIM_PERCENT^MDC NAN X [current_date_time]
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-020		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 19; M	Short Float Type 1; C	
Test purpose		<p>Check that:</p> <p>PHG transcodes SpO2 value of the SpO2PR-Normal field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous normal response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes SpO2 value of the SpO2PR-Fast field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous fast response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes SpO2 value of the SpO2PR-Slow field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous slow response) - Basic-Nu-Observed-Value attribute</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The Simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT 		

	<ul style="list-style-type: none"> Value: 96.0 (%) <p>iii. Field: SpO2PR-Normal - PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: SpO2PR-Fast - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: 98.0 (%) <p>v. Field: SpO2PR-Fast - PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>vi. Field: SpO2PR-Slow - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: 94.0 (%) <p>vii. Field: SpO2PR-Slow - PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute in all three SpO2 objects.</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> The SpO2 Numeric Object (Continuous measurement normal) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the SpO2 subfield of the SpO2PR-Normal field in the PLX Continuous Measurement characteristic (96.0%). The SpO2 Numeric Object (Continuous measurement fast) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the SpO2 subfield of the SpO2PR-Fast field in the PLX Continuous Measurement characteristic (98.0%). The SpO2 Numeric Object (Continuous measurement slow) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the SpO2 subfield of the SpO2PR-Slow field in the PLX Continuous Measurement characteristic (94.0%).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a. IEEE 11073 Objects and Attributes</p> <p>SpO2 Numeric object (Continuous measurement normal):</p> <ul style="list-style-type: none"> Supplemental-types attribute is not present. <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636)

	<ul style="list-style-type: none"> <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 60 (hex) or F3 C0 (hex) or 96.0 (dec) <p>SpO2 Numeric object (Continuous measurement fast):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object (fast response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 62 (hex) or F3D4 (hex) or 98.0 (dec) <p>SpO2 Numeric object (Continuous measurement slow):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object (slow response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 5E (hex) or F3AC (hex) or 94.0 (dec) <p>b. WAN PCD-01 message</p> <p>SpO2 Numeric object (Continuous measurement normal):</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x 96.0 262688^MDC_DIM_PERCENT^MDC R current_date_time]</pre> <p>SpO2 Numeric object (Continuous measurement fast):</p> <p>PCD-01 message includes two segments like these for SpO2 Numeric object (Fast response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x 98.0 262688^MDC_DIM_PERCENT^MDC R current_date_time]</pre> <pre>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_FAST^MDC obx-11 of the parent]</pre> <p>SpO2 Numeric object (Continuous measurement slow):</p> <p>PCD-01 message includes two segments like these for SpO2 Numeric object (Slow response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments):</p> <pre>OBX n NM 150456^MDC_PULS_OXIM_SAT_O2^MDC m.0.0.x 94.0 262688^MDC_DIM_PERCENT^MDC R current_date_time]</pre> <pre>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_SLOW^MDC obx-11 of the parent]</pre>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-021		
TP label		Whitepaper. SpO2 Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 19; M	SpO2 Numeric 20; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes SpO2 value of the SpO2PR-Normal field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous normal response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes SpO2 value of the SpO2PR-Fast field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous fast response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes SpO2 value of the SpO2PR-Slow field in PLX Continuous Measurement characteristic into SpO2 Numeric Object (Continuous slow response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG assigns special value NaN (0x07FF) when SpO2 value is unavailable.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Feature (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: 07 FF (hex). Special value: NaN 		

	<ul style="list-style-type: none"> iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the SpO2 Numeric Object – Basic-Nu-Observed-Value attribute for all SpO2 objects.</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • The SpO2 Numeric Object (Continuous measurement normal) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN). • The SpO2 Numeric Object (Continuous measurement fast) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN). • The SpO2 Numeric Object (Continuous measurement slow) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>SpO2 Numeric object (Continuous measurement normal):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is not present. <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: SpO2 Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed)

SpO2 Numeric object (Continuous measurement fast):

- Supplemental-types attribute is present:
 - ☐ Object: SpO2 Numeric Object (fast response)
 - ☐ Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657)
 - ☐ Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)}
 - ☐ Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}.
- Basic-Nu-Observed-Value attribute is present:
 - ☐ Object: SpO2 Numeric Object
 - ☐ Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636)
 - ☐ Attribute-type: SFLOAT
 - ☐ Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed)

SpO2 Numeric object (Continuous measurement slow):

- Supplemental-types attribute is present:
 - ☐ Object: SpO2 Numeric Object (slow response)
 - ☐ Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657)
 - ☐ Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)}
 - ☐ Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}.
- Basic-Nu-Observed-Value attribute is present:
 - ☐ Object: SpO2 Numeric Object
 - ☐ Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636)
 - ☐ Attribute-type: SFLOAT
 - ☐ Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed)

b) WAN PCD-01 message

SpO2 Numeric object (Continuous measurement normal):

PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):

```
OBX|n|NM|150456^MDC_PULS_OXIM_SAT_O2^MDC|m.0.0.x  
||262688^MDC_DIM_PERCENT^MDC||NAN||||X|||current_date_time]
```

SpO2 Numeric object (Continuous measurement fast):

PCD-01 message includes two segments like these for SpO2 Numeric object (Fast response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments):

```
OBX|n|NM|150456^MDC_PULS_OXIM_SAT_O2^MDC|m.0.0.x  
||262688^MDC_DIM_PERCENT^MDC||NAN||||X|||current_date_time]
```

```
OBX|n|CWE|68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC|m.0.0.x.y|  
150580^MDC_MODALITY_FAST^MDC|||||obx-11 of the parent]
```

SpO2 Numeric object (Continuous measurement slow):

PCD-01 message includes two segments like these for SpO2 Numeric object (Slow response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments):

```
OBX|n|NM|150456^MDC_PULS_OXIM_SAT_O2^MDC|m.0.0.x  
||262688^MDC_DIM_PERCENT^MDC||NAN||||X|||current_date_time]
```

```
OBX|n|CWE|68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC|m.0.0.x.y|  
150580^MDC_MODALITY_SLOW^MDC|||||obx-11 of the parent]
```

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-022		
TP label		Whitepaper. SpO2 measurement value (Spot-Check Measurement)		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	Short Float Type 1; C	Date-Time Conv 1; M	SpO2 Numeric 9; M
		SpO2 Numeric 10; M		
Test purpose		Check that: PHG processes correctly the SpO2 value (%) of the SpO2PR-Spot-Check field and and the value of the Time Stamp field of the PLX Spot-Check characteristic		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<div>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored.</div> <div>2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are:<div>a. PLX Features (0x2A60)<div>i. Field: Supported Features<ul style="list-style-type: none">Format: 16 bitValue: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3).</div><div>ii. Field: Measurement Status Support<ul style="list-style-type: none">This field is not included</div><div>iii. Field: Device and Sensor Status Support<ul style="list-style-type: none">This field is not included</div></div><div>b. PLX Spot-Check Measurement (0x2A5E)<div>i. Field: Flags<ul style="list-style-type: none">Format: 8 bitValue: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set.</div><div>ii. Field: SpO2PR-Spot-Check - SpO2 (%)<ul style="list-style-type: none">Format: SFLOATValue: 96.0 (%)</div><div>iii. Field: SpO2PR-Spot-Check – PR (bpm)<ul style="list-style-type: none">Format: SFLOATValue: Not Relevant</div><div>iv. Field: Time Stamp<ul style="list-style-type: none">Format: Date and TimeValue: October 12nd, 2015, 10:39:27</div><div>v. Field: Measurement Status</div></div></div>		

	<ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check that the PHG accepts the measurement and decodes its value properly (SpO2 measurement value, units and time stamp).</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check that PHG accepts the measurement and decodes its value properly (SpO2 measurement value, units and time stamp)</p>
Pass/Fail criteria	<p>In Step 6, the PHG under test shows the following measurement SpO2 = 96.0 (%) with timestamp '2015-10-12 10:39:27'.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes	

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-023		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 1; O		
Test purpose		<p>Check that:</p> <p>PHG does not include Pulse Rate Numeric Object – Handle Attribute in transcoder output when using spot-check measurement mode.</p> <p>[OR]</p> <p>If PHG includes Pulse Rate Numeric Object – Handle attribute in transcoder output, then its value shall be different than 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<p>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored.</p> <p>2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are:</p> <p>a. PLX Features (0x2A60)</p>		

	<ul style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Handle attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in PHG transcoder output the SpO2 Numeric Object – Handle attribute
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Handle attribute is not present or, if it is present then its value is different than 0.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes	Possible values in typical points of observation after transcoder output are:

(To assist manual testing)	<p>a) IEEE 11073 Objects and Attributes Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message PCD-01 message does not include segments with Handle attribute value</p>
-----------------------------------	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-024		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 11; O		
Test purpose		<p>Check that:</p> <p>PHG does not include Pulse Rate Numeric Object – Handle Attribute in transcoder output when using continuous measurements</p> <p>[OR]</p> <p>If PHG includes Pulse Rate Numeric Object – Handle attribute in transcoder output, then its value shall be different than 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. 		

	<ul style="list-style-type: none"> ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Handle attribute in all three Pulse Rate objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • There are three Pulse Rate objects (for normal, fast and slow measurement modes). • In all three objects, the Pulse Rate Numeric Object – Handle attribute is not present or, if it is present then its value is different than 0
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present in SpO2 objects, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-025		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 2; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Type attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_PULS_RATE}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Type attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the SpO2 Numeric Object – Type attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_PULS_RATE}</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Type attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) code: MDC_PULS_OXIM_PULS_RATE or 18458 (dec) or 48 1A (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Type attribute (check OBX-3):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-026		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	SpO2 Numeric 12; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Type attribute in transcoder output when using continuous measurements.</p>		

	<p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_PULS_RATE}</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status

	<ul style="list-style-type: none"> This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Type attribute in all three Pulse Rate objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> There are three Pulse Rate objects (for normal, fast and slow measurement modes). In all three objects, the Pulse Rate Numeric Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_PULS_RATE}
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Type attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) code: MDC_PULS_OXIM_PULS_RATE or 18458 (dec) or 48 1A (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes three segments like this with Type attribute (check OBX-3):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-027		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Supplemental-Types Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 3; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Supplemental-Types attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_SPOT}.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the Pulse Rate Numeric Object – Supplemental-Types attribute 7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by

	<p>performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Supplemental-Types attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_SPOT}.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Supplemental-Types attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object (Spot-Check measurement) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SPOT}. <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a facet OBX segment of the SpO2 measurement OBX segment with Supplemental-Types attribute (check OBX-3 and OBX-5):</p> <p style="margin-left: 40px;">OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R current_date_time]</p> <p style="margin-left: 40px;">OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_SPOT^MDC R</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-028		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) – Supplemental-Types Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 13; M	PR Numeric 14; M	PR Numeric 15; M
Test purpose		<p>Check that:</p> <p>PHG does not include Pulse Rate Numeric Object – Supplemental-Types attribute in transcoder output for the Pulse Rate continuous measurement object (normal).</p> <p>[AND]</p> <p>PHG includes Pulse Rate Numeric Object – Supplemental-Types attribute in transcoder output for the Pulse Rate continuous measurement object (fast mode). Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_FAST}.</p> <p>[AND]</p> <p>PHG includes Pulse Rate Numeric Object – Supplemental-Types attribute in transcoder output for the Pulse Rate continuous measurement object (slow mode). Supplemental-Types attribute is set to {MDC_PART_SCADA, MDC_MODALITY_SLOW}.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<p>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable).</p>		

2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are:
 - a. PLX Features (0x2A60)
 - i. Field: Supported Features
 - Format: 16 bit
 - Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5).
 - ii. Field: Measurement Status Support
 - This field is not included
 - iii. Field: Device and Sensor Status Support
 - This field is not included
 - b. PLX Continuous Measurement (0x2A5F)
 - i. Field: Flags
 - Format: 8 bit
 - Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present.
 - ii. Field: SpO2PR-Normal - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - iii. Field: SpO2PR-Normal - PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - iv. Field: SpO2PR-Fast - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - v. Field: SpO2PR-Fast - PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - vi. Field: SpO2PR-Slow - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - vii. Field: SpO2PR-Slow - PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - viii. Field: Measurement Status
 - This field is not included
 - ix. Field: Device and Sensor Status
 - This field is not included
 - x. Field: Pulse Amplitude Index (%)
 - This field is not included
3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).
4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.

	5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in the PHG transcoder output the Pulse Rate Numeric Object – Supplemental-Types attribute in all three Pulse Rate objects (continuous normal, fast and slow).		
Pass/Fail criteria	In Step 6, <ul style="list-style-type: none"> The Pulse Rate Numeric Object (normal) – Supplemental-Types attribute is not present The Pulse Rate Numeric Object (fast response) Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_FAST}. The Pulse Rate Numeric Object (slow response) Supplemental-Types attribute is present and its value is {MDC_PART_SCADA, MDC_MODALITY_SLOW}. 		
Notes (To assist manual testing)	Possible values in typical points of observation after transcoder output are: a) IEEE 11073 Objects and Attributes Supplemental Types attribute is not present for Pulse Rate Numeric Object (normal). Supplemental-Types attribute is present for Pulse Rate Numeric Object (fast response): <input type="checkbox"/> Object: Pulse Rate Numeric Object (fast response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}. Supplemental-Types attribute is present for Pulse Rate Numeric Object (slow response): <input type="checkbox"/> Object: Pulse Rate Numeric Object (slow response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}. b) WAN PCD-01 message For Pulse Rate Numeric Object (normal) <ul style="list-style-type: none"> PCD-01 message does not include segments with Supplemental-Types attribute. For Pulse Rate Numeric Object (fast) <ul style="list-style-type: none"> PCD-01 message includes a facet OBX segment of the Pulse Rate measurement OBX segment with Supplemental-Types attribute (check OBX-3 and OBX-5): OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R current_date_time OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_FAST^MDC R For Pulse Rate Numeric Object (slow) <ul style="list-style-type: none"> PCD-01 message includes a facet OBX segment of the Pulse Rate measurement OBX segment with Supplemental-Types attribute (check OBX-3 and OBX-5): OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R current_date_time OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.y.z 150580^MDC_MODALITY_SLOW^MDC R 		

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-029		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable	PR Numeric 4; M	PR Numeric 6; M	

	items			
Test purpose	<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x5040} when the sensor device supports measurement storage.</p>			
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040			
Other PICS	C_MAN_BLE_042			
Initial condition	The PHG under test and the simulated PHD are in the Standby state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Feature (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported. ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. 5. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time 			

	<ul style="list-style-type: none"> Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included <p>6. Check in the PHG transcoder output the Pulse Rate Numeric Object – Metric-Spec-Small attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Metric-Spec-Small attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Metric-Spec-Small attribute is present and its value is {0x5040} (mss-avail-stored-data mss-msmt-aperiodic mss-acc-agent-initiated).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 50 40 (hex) or BITS mss-avail-stored-data (1), mss- msmt - aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-030		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 4; M	PR Numeric 5; M	
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x1040} when the sensor device does not support measurement storage.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Spot-Check Measurement (0x2A5E) PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0000 0000 (MSB → LSB). Measurement Storage for Spot-check measurements is not supported (bit 2). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0000 (MSB → LSB). Timestamp, Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: Time Stamp <ul style="list-style-type: none"> This field is not included Field: Measurement Status <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> This field is not included Check in the PHG transcoder output the Pulse Rate Numeric Object – Metric-Spec-Small attribute
Pass/Fail criteria	In Step 6, the Pulse Rate Numeric Object – Metric-Spec-Small attribute is present and its value is {0x1040} (mss-msmt-aperiodic mss-acc-agent-initiated).

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 10 40 (hex) or BITS mss-msmt-aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>
---	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-031		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) - Metric-Spec-Small Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 16; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Metric-Spec-Small attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x0040} (mss-acc-agent-initiated)</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are 		

	<p>present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present.</p> <ul style="list-style-type: none"> ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the Pulse Rate Numeric Object – Metric-Spec-Small attribute in all three Pulse Rate objects (continuous normal, fast and slow).
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • There are three Pulse Rate objects (for normal, fast and slow measurement modes). • In all three objects, the Pulse Rate Numeric Object – Metric-Spec-Small attribute is present and its value is {0x0040} (mss-acc-agent-initiated).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes <p>Metric-Spec-Small attribute is present in all three SpO2 objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 00 40 (hex) or BITS mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE

	b) WAN PCD-01 message PCD-01 message does not include segments with Metric-Spec-Small attribute value
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-032		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Measurement-Status Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 7; M		
Test purpose		Check that: PHG includes Pulse Rate Numeric Object – Measurement-Status attribute in transcoder output when using spot-check measurement mode. [AND] PHG transcodes the Bluetooth Measurement Status field of the PLX Spot-Check characteristic to 11073 Measurement-Status attribute properly		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1101 (MSB → LSB). Measurement Status support is present (bit 0). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • Format: 16 bit • Value: 1111 1111 1110 0000 (MSB → LSB). All Measurement Status bits are supported iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. 5. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags 		

	<ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). Timestamp and Measurement Status fields are present. Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set.
	<ul style="list-style-type: none"> ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: October 12nd, 2015, 10:39:27 <ul style="list-style-type: none"> • Format: 16 bit • Value: 1000 0000 0000 0000 (MSB → LSB). Invalid measurement detected (bit 15). vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included
	6. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
	7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
	8. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0100 0000 0000 0000 (MSB → LSB), questionable measurement detected (bit 14). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.
	9. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
	10. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
	11. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0010 0000 0000 0000 (MSB → LSB), measurement not available (bit 13). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.
	12. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
	13. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by

	<p>performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>14. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0001 0000 0000 0000 (MSB → LSB), calibration ongoing (bit 12). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>15. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>16. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>17. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 1000 0000 0000 (MSB → LSB), data for testing (bit 11). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>18. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>19. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>20. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0100 0000 0000 (MSB → LSB), data for demonstration (bit 10). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>21. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>22. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>23. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 1000 0000 (MSB → LSB), fully qualified data (bit 7). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>24. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>25. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p>
--	---

	<p>26. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0100 0000 (MSB → LSB), early estimated data (bit 6). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>27. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>28. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute <p>29. Simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0010 0000 (MSB → LSB), measurement ongoing (bit 5). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>30. Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute</p> <p>31. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test Check in PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “invalid” (0x8000). If PHG supports RACP, same criteria applies to 7.b.</p> <p>In Step 9, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “questionable” (0x4000). If PHG supports RACP, same criteria applies to 10.b.</p> <p>In Step 12, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “not-available” (0x2000). If PHG supports RACP, same criteria applies to 13.b.</p> <p>In Step 15, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “calibration-ongoing” (0x1000). If PHG supports RACP, same criteria applies to 16.b.</p> <p>In Step 18, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “test-data” (0x0800). If PHG supports RACP, same criteria applies to 19.b.</p> <p>In Step 21, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “demo-data” (0x0400). If PHG supports RACP, same criteria applies to 22.b.</p> <p>In Step 24, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “validated-data” (0x0080). If PHG supports RACP, same criteria applies to 25.b.</p> <p>In Step 27, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “early-indication” (0x0040). If PHG supports RACP, same criteria applies to 28.b.</p> <p>In Step 30, the Pulse Rate Numeric Object – Measurement-Status attribute is present and its set to “msmt-ongoing” (0x0020). If PHG supports RACP, same criteria applies to 31.b.</p>
Notes (To assist manual testing)	<p>In step 6 (and step 7.b if applicable), possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes Measurement-Status attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 80 00 (hex) WAN PCD-01 message

	<p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC INV X current_date_time]</pre> <p>In step 9 (and step 10.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC QUES R current_date_time]</pre> <p>In step 12 (and step 13.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 20 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC NAV X current_date_time]</pre> <p>In step 15 (and step 16.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 10 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC CAL R current_date_time]</pre> <p>In step 18 (and step 19.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object
--	---

	<ul style="list-style-type: none"> <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 08 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC TEST R current_date_time]</pre> <p>In step 21 (and step 22.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 04 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC DEMO R current_date_time]</pre> <p>In step 24 (and step 25.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 80 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC F current_date_time]</pre> <p>In step 27 (and step 28.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 40 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC EARLY R current_date_time]</pre> <p>In step 30 (and step 31.b if applicable), possible values in typical points of observation after</p>
--	--

	<p>transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <p style="text-align: center;">OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC BUSY X [current_date_time]</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-033		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) – Measurement-Status Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 17; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Measurement-Status attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Measurement Status field of the PLX Continuous Measurement characteristic to 11073 Measurement-Status attribute properly</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Continuous Measurement (0x2A5F) b. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0001 (MSB → LSB). Measurement Status support is present (bit 0). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • Format: 16 bit • Value: 1111 1111 1110 0000 (MSB → LSB). All Measurement Status bits are supported iii. Field: Device and Sensor Status Support 		

	<ul style="list-style-type: none"> • This field is not included
3.	The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).
4.	When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic.
5.	The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0111 (MSB → LSB). Measurement Status, SpO2PR-Fast and SpO2PR-Slow fields are present. Device and Sensor Status and Pulse Amplitude Index fields are not present. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> • Format: 16 bit • Value: 1000 0000 0000 0000 (MSB → LSB). Invalid measurement detected (bit 15). Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included
6.	Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.
7.	The simulated PHD sends a Measurement to the PHG under test with the Measurement Status field set to 0100 0000 0000 0000 (MSB → LSB), questionable measurement detected (bit 14). All remaining fields remain equal to those in step 5.
8.	Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.
9.	The simulated PHD sends a Measurement to PHG under test with Measurement Status

	<p>field set to 0010 0000 0000 0000 (MSB → LSB), measurement not available (bit 13). All remaining fields remain equal to those in step 5.</p> <p>10. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>11. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0001 0000 0000 0000 (MSB → LSB), calibration ongoing (bit 12). All remaining fields remain equal to those in step 5.</p> <p>12. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>13. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 1000 0000 0000 (MSB → LSB), data for testing (bit 11). All remaining fields remain equal to those in step 5.</p> <p>14. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>15. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0100 0000 0000 (MSB → LSB), data for demonstration (bit 10). All remaining fields remain equal to those in step 5.</p> <p>16. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>17. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 1000 0000 (MSB → LSB), fully qualified data (bit 7). All remaining fields remain equal to those in step 5.</p> <p>18. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>19. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0100 0000 (MSB → LSB), early estimated data (bit 6). All remaining fields remain equal to those in step 5.</p> <p>20. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p> <p>21. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0010 0000 (MSB → LSB), measurement ongoing (bit 5). All remaining fields remain equal to those in step 5.</p> <p>22. Check in the PHG transcoder output the Pulse Rate Numeric Object – Measurement-Status attribute in all three Pulse Rate objects.</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “invalid” (0x8000)</p> <p>In Step 8, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “questionable” (0x4000)</p> <p>In Step 10, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “not-available” (0x2000)</p> <p>In Step 12, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “calibration-ongoing” (0x1000)</p> <p>In Step 14, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “test-data” (0x0800)</p> <p>In Step 16, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “demo-data” (0x0400)</p> <p>In Step 18, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “validated-data” (0x0080)</p> <p>In Step 20, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “early-indication” (0x0040)</p> <p>In Step 22, the Pulse Rate Numeric Object – Measurement-Status attribute is present in all three Pulse Rate objects and its set to “msmt-ongoing” (0x0020)</p>
Notes (To assist manual testing)	<p>In step 6, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p>

	<p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 80 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like for each SpO2 object this with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC INV X [current_date_time]</pre> <p>In step 8, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC QUES R [current_date_time]</pre> <p>In step 10, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 20 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC NAV X [current_date_time]</pre> <p>In step 12, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 10 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC CAL R [current_date_time]</pre> <p>In step 14, possible values in typical points of observation after transcoder output are:</p>
--	---

	<p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 08 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC TEST R current_date_time]</pre> <p>In step 16, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 04 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC DEMO R current_date_time]</pre> <p>In step 18, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 80 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC F current_date_time]</pre> <p>In step 20, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 40 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC EARLY R current_date_time]</pre>
--	--

	<p>In step 22, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Measurement-Status attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_MSMT_STAT (2375) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Measurement-Status attribute value (check OBX-8 and OBX-11):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC BUSY X [[current_date_time]</pre>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-034		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 8; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object –Unit-Code attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_BEAT_PER_MIN</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags 		

	<ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Unit-Code attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Unit-Code attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Unit-Code attribute is present and its set to MDC_DIM_BEAT_PER_MIN.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Unit-Code attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: MDC_DIM_BEAT_PER_MIN or 2720 (dec) or 0A A0 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Unit-Code attribute value (check OBX-6):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-035		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 18; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulse Rate Numeric Object – Unit-Code attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_BEAT_PER_MIN</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant 		

	<ul style="list-style-type: none"> v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Unit-Code attribute in all three Pulse Rate objects (continuous normal, fast and slow).</p>
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • There are three Pulse Rate objects (for normal, fast and slow measurement modes). • In all three objects, the Pulse Rate Numeric Object – Unit-Code attribute is present and its set to MDC_DIM_BEAT_PER_MIN.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Unit-Code attribute is present in all three Pulse Rate objects:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: MDC_DIM_BEAT_PER_MIN or 2720 (dec) or 0A A0 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each Pulse Rate object with Unit-Code attribute value (check OBX-6):</p> <p style="text-align: center;">OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-036
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Absolute-Time-Stamp Attribute
Coverage	Spec	[Bluetooth PHDT v1.6]

	Testable items	PR Numeric 9; M	Date-Time Conv 2; M	Date-Time Conv 3; M
		Date-Time Conv 4; M	Date-Time Conv 5; M	
Test purpose	<p>Check that:</p> <p>PHG transcodes Time Stamp field of Spot-Check Measurement characteristic into Pulse Rate Numeric Object - Absolute-Time-Stamp attribute</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Time Stamp field format to Absolute Time format</p> <p>[AND]</p> <p>The fraction of seconds in Absolute Time at transcoder output is 0</p>			
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040			
Other PICS	C_MAN_BLE_042			
Initial condition	The PHG under test and the simulated PHD are in the Standby state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: October 12nd, 2015, 10:39:27 v. Field: Measurement Status 			

	<ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Absolute-Time-Stamp attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Absolute-Time-Stamp attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Absolute-Time-Stamp attribute is present, its value matches with Time Stamp field of Spot-Check Measurement characteristic and fraction of seconds is set to 0.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Absolute-Time-Stamp attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_TIME_STAMP_ABS (2448) <input type="checkbox"/> Attribute-type: SEQUENCE {century (INT-U8), year (INT-U8), month (INT-U8), day (INT-U8), hour (INT-U8), minute (INT-U8), second (INT-U8), sec-fractions (INT-U8)} (BCD encoding) <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • century: 20 (hex) or 32 (dec) • year: 15 (hex) or 21 (dec) • month: 10 (hex) or 16 (dec) • day: 12 (hex) or 18 (dec) • hour: 10 (hex) or 16 (dec) • minute: 39 (hex) or 57 (dec) • second: 27 (hex) or 39 (dec) • sec-fractions: 00 (hex) or 0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Absolute-Time-Stamp attribute value (check OBX-14):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x [value] 264864^MDC_DIM_BEAT_PER_MIN^MDC R 20151012103927+0000</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-037		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 10; M	Short Float Type 1; C	
Test purpose		<p>Check that:</p> <p>PHG transcodes PR value of the SpO2PR-Spot-Check field in PLX Spot-Check Measurement characteristic into Pulse Rate Numeric Object - Basic-Nu-Observed-Value attribute</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 90.0 (bpm) iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not relevant v. Field: Measurement Status 		

	<ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute</p>		
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the PR subfield of the SpO2PR-Spot-Check field in the PLX Spot-Check Measurement characteristic (90.0 bpm).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>		
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: F3 84 (hex) or 10 09 (hex) or 00 5A (hex) or 90.0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 90.0 264864^MDC_DIM_BEAT_PER_MIN^MDC R current_date_time]</pre>		

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-038		
TP label		Whitepaper. Pulse Rate Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 10; M	PR Numeric 20; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Spot-Check field in PLX Spot-Check Measurement characteristic into Pulse Rate Numeric Object - Basic-Nu-Observed-Value attribute</p>		

	<p>[AND]</p> <p>PHG assigns special value NaN (0x07FF) when Pulse Rate value is unavailable.</p>
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	C_MAN_BLE_042
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT Value: 07 FF (hex). Special value: NaN Field: Time Stamp <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> This field is not included The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to

	<p>read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <p>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 264864^MDC_DIM_BEAT_PER_MIN^MDC NaN X [current_date_time]</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-039		
TP label		Pulse Rate Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 19; M	Short Float Type 1; C	
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Normal field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous normal response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Fast field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous fast response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Slow field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous slow response) - Basic-Nu-Observed-Value attribute</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 90.0 (bpm) iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR–Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 91.0 (bpm) vi. Field: SpO2PR–Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR–Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 92.0 (bpm) viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included

	<ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to PHG under test. 6. Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute in all three Pulse Rate objects.
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • The Pulse Rate Numeric Object (Continuous measurement normal) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the PR field of the SpO2PR-Normal field in the PLX Continuous Measurement characteristic (90.0 bpm). • The Pulse Rate Numeric Object (Continuous measurement fast) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the PR subfield of the SpO2PR-Fast field in the PLX Continuous Measurement characteristic (91.0 bpm). • The Pulse Rate Numeric Object (Continuous measurement slow) – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the PR subfield of the SpO2PR-Slow field in the PLX Continuous Measurement characteristic (92.0 bpm).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Pulse Rate Numeric object (Continuous measurement normal):</p> <p>Supplemental-types attribute is not present.</p> <ul style="list-style-type: none"> • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: F3 84 (hex) or 10 09 (hex) or 00 5A (hex) or 90.0 (dec) <p>Pulse Rate Numeric object (Continuous measurement fast):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object (fast response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: F3 8E (hex) or 00 5B (hex) or 91.0 (dec) <p>Pulse Rate Numeric object (Continuous measurement slow):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object (slow response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636)

	<ul style="list-style-type: none"> ❑ Attribute-type: SFLOAT ❑ Attribute-value: F3 98 (hex) or 00 5C (hex) or 92.0(dec) <p>b) WAN PCD-01 message</p> <p>Pulse Rate Numeric object (Continuous measurement normal):</p> <ul style="list-style-type: none"> • PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5): <p>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 90.0 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</p> <p>Pulse Rate Numeric object (Continuous measurement fast):</p> <ul style="list-style-type: none"> • PCD-01 message includes two segments like these for Pulse Rate Numeric object (Fast response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments): <p>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 91.0 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</p> <p>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_FAST^MDC [obx-11 of the parent]</p> <p>Pulse Rate Numeric object (Continuous measurement slow):</p> <ul style="list-style-type: none"> • PCD-01 message includes two segments like these for Pulse Rate Numeric object (Slow response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments): <p>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 92.0 264864^MDC_DIM_BEAT_PER_MIN^MDC R [current_date_time]</p> <p>OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_SLOW^MDC [obx-11 of the parent]</p>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-040		
TP label		Whitepaper. Pulse Rate Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PR Numeric 19; M	PR Numeric 20; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Normal field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous normal response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Fast field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous fast response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG transcodes Pulse Rate value of the PR subfield of the SpO2PR-Slow field in PLX Continuous Measurement characteristic into Pulse Rate Numeric Object (Continuous slow response) - Basic-Nu-Observed-Value attribute</p> <p>[AND]</p> <p>PHG assigns special value NaN (0x07FF) when Pulse Rate value is unavailable.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow fields are present. Measurement Status, Device and Sensor Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included

	<ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to PHG under test. 6. Check in PHG transcoder output the Pulse Rate Numeric Object – Basic-Nu-Observed-Value attribute for all Pulse Rate objects.
Pass/Fail criteria	<p>In Step 6,</p> <ul style="list-style-type: none"> • The Pulse Rate Numeric Object (Continuous measurement normal) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN). • The Pulse Rate Numeric Object (Continuous measurement fast) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN). • The Pulse Rate Numeric Object (Continuous measurement slow) – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Pulse Rate Numeric object (Continuous measurement normal):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is not present. Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>Pulse Rate Numeric object (Continuous measurement fast):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object (fast response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_FAST}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>Pulse Rate Numeric object (Continuous measurement slow):</p> <ul style="list-style-type: none"> • Supplemental-types attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object (slow response) <input type="checkbox"/> Attribute-id: MDC_ATTR_SUPPLEMENTAL_TYPES (2657) <input type="checkbox"/> Attribute-type: SEQUENCE of SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: {MDC_PART_SCADA, MDC_MODALITY_SLOW}. • Basic-Nu-Observed-Value attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulse Rate Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT

	<p>❑ Attribute-value: Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed)</p> <p>b) WAN PCD-01 message</p> <p>Pulse Rate Numeric object (Continuous measurement normal):</p> <ul style="list-style-type: none"> PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5): <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 264864^MDC_DIM_BEAT_PER_MIN^MDC NAN X current_date_time]</pre> <p>Pulse Rate Numeric object (Continuous measurement fast):</p> <ul style="list-style-type: none"> PCD-01 message includes two segments like these for Pulse Rate Numeric object (Fast response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments): <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 264864^MDC_DIM_BEAT_PER_MIN^MDC NAN X current_date_time] OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_FAST^MDC obx-11 of the parent]</pre> <p>Pulse Rate Numeric object (Continuous measurement slow):</p> <ul style="list-style-type: none"> PCD-01 message includes two segments like these for Pulse Rate Numeric object (Slow response), with Basic-Nu-Observed-Value attribute and Supplemental-Types attribute values (check OBX-5 in both segments): <pre>OBX n NM 149530^MDC_PULS_OXIM_PULS_RATE^MDC m.0.0.x 264864^MDC_DIM_BEAT_PER_MIN^MDC NAN X current_date_time] OBX n CWE 68193^MDC_ATTR_SUPPLEMENTAL_TYPES^MDC m.0.0.x.y 150580^MDC_MODALITY_SLOW^MDC obx-11 of the parent]</pre>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-041		
TP label		Whitepaper. Pulse Rate measurement value (Spot-Check Measurement)		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	Short Float Type 1; C	Date-Time Conv 1; M	PR Numeric 9; M
		PR Numeric 10; M		
Test purpose		Check that: PHG processes correctly the Pulse Rate value (bpm) of the PR subfield of the SpO2PR-Spot-Check field and and the value of the Time Stamp field of the PLX Spot-Check characteristic		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<div>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored.</div> <div>2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are:<div>a. PLX Features (0x2A60)<div>i. Field: Supported Features<ul style="list-style-type: none">Format: 16 bitValue: 0000 0000 0000 1100 (MSB → LSB). Measurement Storage for spot-</div></div></div>		

	<p>check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3).</p> <ul style="list-style-type: none"> ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0001 (MSB → LSB). Timestamp field is present. Measurement Status, Device and Sensor Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 90.0 (bpm) iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: October 12nd, 2015, 10:39:27 v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check that PHG accepts the measurement and decodes its value properly (Pulse Rate measurement value, units and time stamp).</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check that the PHG accepts the measurement and decodes its value properly (Pulse Rate measurement value, units and time stamp)
Pass/Fail criteria	<p>In Step 6, the PHG under test shows the following measurement Pulse Rate = 90.0 (bpm) with timestamp '2015-10-12 10:39:27'.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes	

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-042		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 1; O		
Test purpose		<p>Check that:</p> <p>PHG does not include Pulsatile Quality Numeric Object – Handle Attribute in transcoder output when using spot-check measurement mode.</p> <p>[OR]</p> <p>If PHG includes Pulsatile Quality Numeric Object – Handle attribute in transcoder output, then its value shall be different than 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Handle attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Handle attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Handle attribute is not present or, if it is present then its value is different than 0</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-043		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 9; O		
Test purpose		<p>Check that:</p> <p>PHG does not include Pulsatile Quality Numeric Object – Handle Attribute in transcoder output when using continuous measurements</p> <p>[OR]</p> <p>If PHG includes Pulsatile Quality Numeric Object – Handle attribute in transcoder output, then</p>		

	its value shall be different than 0
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040
Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Pulse Amplitude Index field is supported. ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow and Pulse Amplitude Index fields are present. Measurement Status, and Device and Sensor Status and fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included

	<ul style="list-style-type: none"> ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Handle attribute.
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Handle attribute is not present or, if it is present then its value is different than 0.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes <p>Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 b) WAN PCD-01 message <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-044		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 2; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Type attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_SAT_O2_QUAL}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is: <ol style="list-style-type: none"> a. PLX Features (0x2A60) 		

	<ul style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Type attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Type attribute
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_SAT_O2_QUAL}</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Type attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) • code: MDC_SAT_O2_QUAL or 19248(dec) or 4B 30 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Type attribute (check OBX-3):</p> <pre>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R current_date_time]</pre>
---	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-045		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 10; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Type attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_SAT_O2_QUAL}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Pulse Amplitude Index is supported (bit 6). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags 		

	<ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow and Pulse Amplitude Index fields are present. Measurement Status, and Device and Sensor Status fields are not present. <ol style="list-style-type: none"> Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> • This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <ol style="list-style-type: none"> The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Feature characteristic. The simulated PHD sends the Measurement to the PHG under test. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Type attribute.
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_SAT_O2_QUAL}
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes Type attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value:

	<ul style="list-style-type: none"> • partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) • code: MDC_SAT_O2_QUAL or 19248(dec) or 4B 30 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes three segments like this with Type attribute (check OBX-3):</p> <p>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R current_date_time]</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-046		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 3; M	PQ Numeric 5; M	
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x5040} when the sensor device supports measurement storage.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test with the following value: 		

	<p>a. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> Format: 8 bit Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status, and Device and Sensor Status are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute is present and its value is {0x5040} (mss-avail-stored-data mss-msmt-aperiodic mss-acc-agent-initiated).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 50 40 (hex) or BITS mss-avail-stored-data (1), mss- msmt - aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-047		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) - Metric-Spec-Small Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 3; M	PQ Numeric 4; M	
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x1040} when the sensor device does not support measurement storage.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Spot-Check Measurement (0x2A5E) PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute</p>
Pass/Fail criteria	In Step 6, the SpO2 Numeric Object – Metric-Spec-Small attribute is present and its value is {0x1040} (mss-msmt-aperiodic mss-acc-agent-initiated).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 10 40 (hex) or BITS mss-msmt-aperiodic(3), mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-048		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) - Metric-Spec-Small Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 11; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Metric-Spec-Small attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x0040} (mss-acc-agent-initiated)</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				

Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Pulse Amplitude Index field is supported (bit 6) ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR–Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR–Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR–Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT

	<ul style="list-style-type: none"> Value: Not Relevant <ol style="list-style-type: none"> The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to the PHG under test. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Metric-Spec-Small attribute is present and its value is {0x0040} (mss-acc-agent-initiated).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes Metric-Spec-Small attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 00 40 (hex) or BITS mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE WAN PCD-01 message PCD-01 message does not include segments with Metric-Spec-Small attribute value

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-049		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 6; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Unit-Code attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_PERCENT</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit 		

	<ul style="list-style-type: none"> Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). <p>ii. Field: Measurement Status Support</p> <ul style="list-style-type: none"> This field is not included <p>iii. Field: Device and Sensor Status Support</p> <ul style="list-style-type: none"> This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> Format: 8 bit Value: 0000 1001 (MSB → LSB). Timestampo and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in the PHG transcoder output the Pulsatile Quality Numeric Object – Unit-Code attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Unit-Code attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Unit-Code attribute is present and its set to MDC_DIM_PERCENT.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>

Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Unit-Code attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: MDC_DIM_PERCENT or 544 (dec) or 02 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Unit-Code attribute value (check OBX-6):</p> <p style="text-align: center;">OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x [value]] 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</p>
---	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-050		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) – Unit-Code Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 12; M		
Test purpose		<p>Check that:</p> <p>PHG includes Pulsatile Quality Numeric Object – Unit-Code attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Unit-Code is set to MDC_DIM_PERCENT</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Pulse Amplitude Index field is supported (bit 6). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags 		

	<ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011(MSB → LSB). SpO2PR-Fast, SpO2PR-Slow and Pulse Amplitude Index fields are present. Measurement Status, and Device and Sensor Status fields are not present. <ol style="list-style-type: none"> Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> • This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <ol style="list-style-type: none"> The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to the PHG under test. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Unit-Code attribute.
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Unit-Code attribute is present and it is set to MDC_DIM_PERCENT.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes Unit-Code attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_UNIT_CODE (2454) <input type="checkbox"/> Attribute-type: INT-U16

	<p><input type="checkbox"/> Attribute-value: MDC_DIM_PERCENT or 544 (dec) or 02 20 (hex)</p> <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this for each SpO2 object with Unit-Code attribute value (check OBX-6):</p> <p style="text-align: center;">OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R current_date_time]</p>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-051		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) – Absolute-Time-Stamp Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 7; M	Date-Time Conv 2; M	Date-Time Conv 3; M
		Date-Time Conv 4; M	Date-Time Conv 5; M	
Test purpose		<p>Check that:</p> <p>PHG transcodes Time Stamp field of Spot-Check Measurement characteristic into Pulsatile Quality Numeric Object - Absolute-Time-Stamp attribute</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Time Stamp field format to Absolute Time format</p> <p>[AND]</p> <p>The fraction of seconds in Absolute Time at transcoder output is 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<div><div>1.</div><div>The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored.</div></div> <div><div>2.</div><div>The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is:</div><div><div>a.</div><div>PLX Features (0x2A60)</div><div><div>i.</div><div>Field: Supported Features</div><div><div>•</div><div>Format: 16 bit</div></div><div><div>•</div><div>Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3).</div></div></div><div><div>ii.</div><div>Field: Measurement Status Support</div><div><div>•</div><div>This field is not included</div></div></div><div><div>iii.</div><div>Field: Device and Sensor Status Support</div><div><div>•</div><div>This field is not included</div></div></div></div><div><div>b.</div><div>PLX Spot-Check Measurement (0x2A5E)</div><div><div>i.</div><div>Field: Flags</div><div><div>•</div><div>Format: 8 bit</div></div><div><div>•</div><div>Value: 0000 1001 (MSB → LSB). Pulse Amplitude Index and Timestamp</div></div></div></div></div>		

	<p>fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set.</p> <ul style="list-style-type: none"> ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: October 12nd, 2015, 10:39:27 v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Absolute-Time-Stamp attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Absolute-Time-Stamp attribute
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Absolute-Time-Stamp attribute is present, its value matches with Time Stamp field of Spot-Check Measurement characteristic and fraction of seconds is set to 0.</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ul style="list-style-type: none"> a) IEEE 11073 Objects and Attributes <ul style="list-style-type: none"> Absolute-Time-Stamp attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_TIME_STAMP_ABS (2448) <input type="checkbox"/> Attribute-type: SEQUENCE {century (INT-U8), year (INT-U8), month (INT-U8), day (INT-U8), hour (INT-U8), minute (INT-U8), second (INT-U8), sec-fractions (INT-U8)} (BCD encoding) <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • century: 20 (hex) or 32 (dec) • year: 15 (hex) or 21 (dec)

	<ul style="list-style-type: none"> month: 10 (hex) or 16 (dec) day: 12 (hex) or 18 (dec) hour: 10 (hex) or 16 (dec) minute: 39 (hex) or 57 (dec) second: 27 (hex) or 39 (dec) sec-fractions: 00 (hex) or 0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Absolute-Time-Stamp attribute value (check OBX-14):</p> <p>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x [value] 262688^MDC_DIM_PERCENT^MDC R 20151012103927+0000</p>
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-052		
TP label		Pulsatile Quality Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 1		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 8; M	Short Float Type 1; C	
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Amplitude Index value of the PLX Spot-Check Measurement characteristic into Pulsatile Quality Numeric Object - Basic-Nu-Observed-Value attribute</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit 		

	<ul style="list-style-type: none"> Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. <ul style="list-style-type: none"> ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> Format: SFLOAT Value: 15.0 (%) <ol style="list-style-type: none"> The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to PHG under test. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the Pulse Amplitude Index of the PLX Spot-Check Measurement characteristic (15.0 %).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 0F (hex) or F0 96 (hex) or E5 DC (hex) or 15.0 (dec) WAN PCD-01 message <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p>

	OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x 15.0 262688^MDC_DIM_PERCENT^MDC R [current_date_time]
--	---

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-053		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Spot-Check Measurement) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 8; M	PQ Numeric 14; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Amplitude Index value of the PLX Spot-Check Measurement characteristic into Pulsatile Quality Numeric Object - Basic-Nu-Observed-Value attribute [AND]</p> <p>PHG assigns special value NaN (0x07FF) when SpO2 value is unavailable.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> This field is not included PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 1001 (MSB → LSB). Timestamp and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> This field is not included <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: 07 FF (hex). Special value: NaN <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute</p>
Pass/Fail criteria	<p>In Step 6, the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <pre>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x 262688^MDC_DIM_PERCENT^MDC NAN X current_date_time]</pre>

TP Id	TP/LP-PAN/PHG/PHDTW/PLX/BV-054
TP label	Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 1
Coverage	Spec
	[Bluetooth PHDT v1.6]

	Testable items	PQ Numeric 13; M	Short Float Type 1; C	
Test purpose	Check that: PHG transcodes Pulse Amplitude Index value of the PLX Continuous Measurement characteristic into Pulsatile Quality Numeric Object - Basic-Nu-Observed-Value attribute			
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040			
Other PICS				
Initial condition	The PHG under test and the simulated PHD are in the Standby state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes and Pulse Amplitude Index fields are supported (bits 4, 5 and 6). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) 			

	<ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • This field is not included <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: 15.0 (%) <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute.</p>
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric object – Basic-Nu-Observed-Value attribute is present and its value matches with the value of the Pulse Amplitude Index field of the PLX Continuous Measurement characteristic (15.0 %).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 00 0F (hex) or F0 96 (hex) or E5 DC (hex) or 15.0 (dec) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <pre>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x 15.0 262688^MDC_DIM_PERCENT^MDC R [current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-055		
TP label		Whitepaper. Pulsatile Quality Numeric Object (Continuous Measurements) – Basic-Nu-Observed-Value Attribute 2		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	PQ Numeric 13; M	PQ Numeric 14; M	Short Float Type 2; M
Test purpose		<p>Check that:</p> <p>PHG transcodes Pulse Amplitude Index value of the PLX Continuous Measurement characteristic into Pulsatile Quality Numeric Object - Basic-Nu-Observed-Value attribute [AND]</p> <p>PHG assigns special value NaN (0x07FF) when Pulsatile Quality value is unavailable.</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		

Other PICS	
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0111 0000 (MSB → LSB). Fast and slow response modes are supported (bits 4 and 5). Pulse Amplitude Index field is supported (bit 6). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0001 0011 (MSB → LSB). SpO2PR-Fast, SpO2PR-Slow and Pulse Amplitude Index fields are present. Measurement Status and Device and Sensor Status fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included

	<ul style="list-style-type: none"> x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 07 FF (hex). Special value: NaN 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in PHG transcoder output the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute.
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Basic-Nu-Observed-Value attribute is present and its value is 0x07FF (NaN).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Basic-Nu-Observed-Value attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Pulsatile Quality Numeric Object <input type="checkbox"/> Attribute-id: MDC_ATTR_NU_VAL_OBS_BASIC (2636) <input type="checkbox"/> Attribute-type: SFLOAT <input type="checkbox"/> Attribute-value: 07 FF (hex) or NaN (note that a decimal value is not allowed) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Basic-Nu-Observed-Value attribute value (check OBX-5):</p> <pre>OBX n NM 150320^MDC_SAT_O2_QUAL^MDC m.0.0.x 262688^MDC_DIM_PERCENT^MDC NAN X current_date_time]</pre>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-056		
TP label		Whitepaper. Pulsatile Quality measurement value (Spot-Check Measurement)		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	Short Float Type 1; C	Date-Time Conv 1; M	PQ Numeric 7; M
		PQ Numeric 8; M		
Test purpose		Check that: PHG processes correctly the Pulse Amplitude Index value (%) and and the value of the Time Stamp field of the PLX Spot-Check characteristic		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<div>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a Spot-Check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored.</div> <div>2. The simulated PHD implements several BTLE characteristics. The characteristic of interest for this Test Case is:<div>a. PLX Features (0x2A60)</div></div>		

	<ul style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0100 1100 (MSB → LSB). Pulse Amplitude Index field is supported (bit 6). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • This field is not included <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1001 (MSB → LSB). Pulse Amplitude Index and Timestamp fields are present. Measurement Status and Device and Sensor Status fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • This field is not included vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: 15.0 (%) <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check that the PHG accepts the measurement and decodes its value properly (Pulse Amplitude Index value, units and time stamp).</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check that PHG accepts the measurement and decodes its value properly (Pulse Amplitude Index value, units and time stamp)
Pass/Fail criteria	In Step 6, the PHG under test shows the following measurement Pulsatile Quality = 15.0 (%)

	with timestamp '2015-10-12 10:39:27'. If the PHG supports RACP, the same criteria applies to Step 7.b
Notes	

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-057		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Spot-Check Measurement) - Handle Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 1; O		
Test purpose		<p>Check that:</p> <p>PHG does not include Device and Sensor Status Enumeration Object – Handle Attribute in transcoder output when using spot-check measurement mode.</p> <p>[OR]</p> <p>If PHG includes Device and Sensor Status Enumeration Object – Handle attribute in transcoder output, then its value shall be different than 0</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1110 (MSB → LSB). Device and Sensor Status field is supported (bit 1). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant b. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0101 (MSB → LSB). Timestamp and Device and Sensor Status fields are present. Pulse Amplitude Index and Measurement Status fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT 		

	<ul style="list-style-type: none"> Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> Format: 24 bit Value: Not Relevant <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> This field is not included. <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the measurement to the PHG under test.</p> <p>6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Handle attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Handle attribute</p>
Pass/Fail criteria	<p>In Step 6, the Device and Sensor Status Enumeration Object – Handle attribute is not present or, if it is present then its value is different than 0</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id	TP/LP-PAN/PHG/PHDTW/PLX/BV-058	
TP label	Whitepaper. Device and Sensor Status Enumeration Object (Continuous Measurements) - Handle Attribute	
Coverage	Spec	[Bluetooth PHDT v1.6]

	Testable items	DSS Enumeration 5; O		
Test purpose	<p>Check that:</p> <p>PHG does not include Device and Sensor Status Enumeration Object – Handle Attribute in transcoder output when using continuous measurements</p> <p>[OR]</p> <p>If PHG includes Device and Sensor Status Enumeration Object – Handle attribute in transcoder output, then its value shall be different than 0</p>			
Applicability	C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041			
Other PICS				
Initial condition	The PHG under test and the simulated PHD are in the Standby state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 0010 (MSB → LSB). Device and Sensor Status field is supported (bit 1). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant b. PLX Continuous Measurement (0x2A5F) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow and Device and Sensor Status fields are present. Measurement Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR–Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR–Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR–Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR–Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR–Slow - SpO2 (%) 			

	<ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>vii. Field: SpO2PR-Slow - PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>viii. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>ix. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant. <p>x. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Handle attribute.</p>
Pass/Fail criteria	In Step 6, the Device and Sensor Status Enumeration Object – Handle attribute is not present or, if it is present then its value is different than 0
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Handle attribute is not present, or if it is present then:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_HANDLE (2337) <input type="checkbox"/> Attribute-type: INT-U16 <input type="checkbox"/> Attribute-value: Any value different than 0 <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Handle attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-059		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Spot-Check Measurement) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 2; M		
Test purpose		<p>Check that:</p> <p>PHG includes Device and Sensor Status Enumeration Object – Type attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_DEV_STATUS}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		

Other PICS	C_MAN_BLE_042
Initial condition	The PHG under test and the simulated PHD are in the Standby state.
Test procedure	<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features <ul style="list-style-type: none"> Format: 16 bit Value: 0000 0000 0000 1110 (MSB → LSB). Device and Sensor Status field is supported (bit 1). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). Field: Measurement Status Support <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status Support <ul style="list-style-type: none"> Format: 24 bit Value: Not Relevant PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> Field: Flags <ul style="list-style-type: none"> Format: 8 bit Value: 0000 0101 (MSB → LSB). Timestamp and Device and Sensor Status fields are present. Pulse Amplitude Index and Measurement Status fields are not present. Device Clock is set. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> Format: SFLOAT Value: Not Relevant Field: Time Stamp <ul style="list-style-type: none"> Format: Date and Time Value: Not Relevant Field: Measurement Status <ul style="list-style-type: none"> This field is not included Field: Device and Sensor Status <ul style="list-style-type: none"> Format: 24 bit Value: Not Relevant Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> This field is not included The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristics.

	<p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Type attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Type attribute</p>
Pass/Fail criteria	<p>In Step 6, the the Device and Sensor Status Enumeration Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_DEV_STATUS}</p> <p>If the PHG supports RACP, the same criteria applies to Step 7.b.</p>
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Type attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> • partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) • code: MDC_PULS_OXIM_DEV_STATUS or 19532 (dec) or 4C 4C (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Type attribute (check OBX-3):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x [value] R</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-060		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Continuous Measurements) - Type Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 6; M		
Test purpose		<p>Check that:</p> <p>PHG includes Device and Sensor Status Enumeration Object – Type attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Type is set to {MDC_PART_SCADA, MDC_PULS_OXIM_DEV_STATUS}</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<p>1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable).</p>		

2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are:
 - a. PLX Features (0x2A60)
 - i. Field: Supported Features
 - Format: 16 bit
 - Value: 0000 0000 0011 0010 (MSB → LSB). Device and Sensor Status is supported (bit 1). Fast and slow response modes are supported (bits 4 and 5).
 - ii. Field: Measurement Status Support
 - This field is not included
 - iii. Field: Device and Sensor Status Support
 - Format: 24 bit
 - Value: Not Relevant
 - b. PLX Continuous Measurement (0x2A5F)
 - i. Field: Flags
 - Format: 8 bit
 - Value: 0000 1011 (MSB → LSB). SpO2PR–Fast, SpO2PR–Slow and Device and Sensor Status fields are present. Measurement Status and Pulse Amplitude Index fields are not present.
 - ii. Field: SpO2PR–Normal - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - iii. Field: SpO2PR–Normal – PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - iv. Field: SpO2PR–Fast - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - v. Field: SpO2PR–Fast - PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - vi. Field: SpO2PR–Slow - SpO2 (%)
 - Format: SFLOAT
 - Value: Not Relevant
 - vii. Field: SpO2PR–Slow - PR (bpm)
 - Format: SFLOAT
 - Value: Not Relevant
 - viii. Field: Measurement Status
 - This field is not included
 - ix. Field: Device and Sensor Status
 - Or Format: 24 bit
 - Value: Not Relevant.
 - x. Field: Pulse Amplitude Index (%)
 - This field is not included
3. The PHG under test initiates a discovery process (Scanning state), it discovers the

	<p>simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <ol style="list-style-type: none"> When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. The simulated PHD sends the Measurement to the PHG under test. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Type attribute.
Pass/Fail criteria	In Step 6, the Pulsatile Quality Numeric Object – Type attribute is present and its value is {MDC_PART_SCADA, MDC_PULS_OXIM_DEV_STATUS}
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> IEEE 11073 Objects and Attributes Type attribute is present: <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ID_TYPE (2351) <input type="checkbox"/> Attribute-type: SEQUENCE {partition (INT-U16), code (INT-U16)} <input type="checkbox"/> Attribute-value: <ul style="list-style-type: none"> partition: MDC_PART_SCADA or 2 (dec) or 00 02 (hex) code: MDC_PULS_OXIM_DEV_STATUS or 19532 (dec) or 4C 4C (hex) WAN PCD-01 message PCD-01 message includes a segment like this with Type attribute (check OBX-3): OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x [value] R

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-061		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Spot-Check Measurement) - Metric-Spec-Small Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 3; M		
Test purpose		<p>Check that:</p> <p>PHG includes Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute in transcoder output when using spot-check measurement mode.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x0040} (mss-acc-agent-initiated)</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The Simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> PLX Features (0x2A60) <ol style="list-style-type: none"> Field: Supported Features 		

	<ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1110 (MSB → LSB). Device and Sensor Status field is supported (bit 1). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). <p>ii. Field: Measurement Status Support</p> <ul style="list-style-type: none"> • This field is not included <p>iii. Field: Device and Sensor Status Support</p> <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant <p>b. PLX Spot-Check Measurement (0x2A5E)</p> <p>i. Field: Flags</p> <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0101 (MSB → LSB). Timestamp and Device and Sensor Status fields are present. Pulse Amplitude Index and Measurement Status fields are not present. Device Clock is set. <p>ii. Field: SpO2PR-Spot-Check - SpO2 (%)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iii. Field: SpO2PR-Spot-Check – PR (bpm)</p> <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant <p>iv. Field: Time Stamp</p> <ul style="list-style-type: none"> • Format: Date and Time • Value: Not Relevant <p>v. Field: Measurement Status</p> <ul style="list-style-type: none"> • This field is not included <p>vi. Field: Device and Sensor Status</p> <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant <p>vii. Field: Pulse Amplitude Index (%)</p> <ul style="list-style-type: none"> • This field is not included <p>3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).</p> <p>4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristics.</p> <p>5. The simulated PHD sends the Measurement to the PHG under test.</p> <p>6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute</p> <p>7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute</p>
Pass/Fail criteria	In Step 6, the Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute is

	present and its value is {0x0040} (mss-acc-agent-initiated). If the PHG supports RACP, the same criteria applies to Step 7.b.
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630) <input type="checkbox"/> Attribute-type: BITS-16 <input type="checkbox"/> Attribute-value: 00 40 (hex) or BITS mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-062		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Continuous Measurements) - Metric-Spec-Small Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 7; M		
Test purpose		<p>Check that:</p> <p>PHG includes Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute in transcoder output when using continuous measurements.</p> <p>[AND]</p> <p>Metric-Spec-Small is set to {0x0040} (mss-acc-agent-initiated)</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0010 (MSB → LSB). Device and Sensor Status is supported. Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • Format: 24 bit • Value: Not Relevant b. PLX Continuous Measurement (0x2A5F) 		

	<ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1011 (MSB → LSB). SpO2PR–Fast, SpO2PR-Slow and Device and Sensor Status fields are present. Measurement Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • Or Format: 24 bit • Value: Not Relevant. x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included <ol style="list-style-type: none"> 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 5. The simulated PHD sends the Measurement to the PHG under test. 6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute
Pass/Fail criteria	In Step 6, the the Device and Sensor Status Enumeration Object – Metric-Spec-Small attribute is present and its value is {0x0040} (mss-acc-agent-initiated).
Notes (To assist manual testing)	<p>Possible values in typical points of observation after transcoder output are:</p> <ol style="list-style-type: none"> a) IEEE 11073 Objects and Attributes <p>Metric-Spec-Small attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_METRIC_SPEC_SMALL (2630)

	<ul style="list-style-type: none"> ❑ Attribute-type: BITS-16 ❑ Attribute-value: 00 40 (hex) or BITS mss-acc-agent-initiated(9) set to TRUE and remaining BITS set to FALSE <p>b) WAN PCD-01 message</p> <p>PCD-01 message does not include segments with Metric-Spec-Small attribute value</p>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-063		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Spot-Check Measurement) – Enum-Observed-Value-Bit-Str Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 4; M		
Test purpose		<p>Check that:</p> <p>PHG transcodes Device and Sensor Status field of the PLX Spot-Check Measurement characteristic into Device and Sensor Status Enumeration Object - Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Device and Sensor Status field of the PLX Spot-Check characteristic to 11073 Enum-Observed-Value-Basic-Bit-Str attribute properly</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS		C_MAN_BLE_042		
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a spot-check measurement ready to be sent and it is in the Advertising state (it is discoverable). The simulated PHD also supports the RACP characteristic and has an identical spot-check measurement temporarily stored. 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) b. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0000 1110 (MSB → LSB). Device and Sensor Status support is present (bit 1). Measurement Storage for spot-check measurements is supported (bit 2). Timestamp for Spot-Check measurements is supported (bit 3). ii. Field: Measurement Status Support <ul style="list-style-type: none"> • This field is not included iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • Format: 24 bit • Value: 0000 0000 1111 1111 1111 1111 (MSB → LSB). All Device and Sensor Status bits are supported 3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state). 4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic. 		

	<ol style="list-style-type: none"> 5. The simulated PHD sends the Measurement to the PHG under test with the following value: <ol style="list-style-type: none"> a. PLX Spot-Check Measurement (0x2A5E) <ol style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 0101 (MSB → LSB). Device and Sensor Status and Timestamp field are present. Measurement Status, and Pulse Amplitude Index fields are not present. Device Clock is set. ii. Field: SpO2PR-Spot-Check - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Spot-Check – PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: Time Stamp <ul style="list-style-type: none"> • This field is not included v. Field: Measurement Status <ul style="list-style-type: none"> • This field is not included vi. Field: Device and Sensor Status <ul style="list-style-type: none"> • Format: 24 bit • Value: 0000 0000 0000 0000 0000 0001 (MSB → LSB). Extended Display Update Ongoing (bit 0). vii. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included 6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute 7. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute 8. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0000 0010 (MSB → LSB). Equipment Malfunction (bit 1). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 9. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute 10. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN <ol style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute 11. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0000 0100 (MSB → LSB). Signal Processing Irregularity Detected (bit 2). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement. 12. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object –
--	--

	<p>Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>13. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to the PHG under test Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>14. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0000 1000 (MSB → LSB). Inadequate Signal Detected (bit 3). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>15. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>16. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to PHG under test Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>17. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0001 0000 (MSB → LSB). Poor Signal Detected (bit 4). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>18. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>19. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>20. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0010 0000 (MSB → LSB). Low Perfusion Detected (bit 5). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>21. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>22. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>23. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0100 0000 (MSB → LSB). Erratic Signal Detected (bit 6). All remaining fields remain equal to those in step 5. Simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>24. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>25. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ol style="list-style-type: none"> The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG
--	---

	<p>under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>26. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 1000 0000 (MSB → LSB). Non-Pulsatile Signal Detected (bit 7). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>27. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>28. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>29. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0001 0000 0000 (MSB → LSB). Questionable Signal Detected (bit 8). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>30. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>31. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the Simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the Simulated PHD sends the temporarily stored spot-check measurement to PHG under test</p> <p>b) Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>32. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0010 0000 0000 (MSB → LSB). Signal Analysis Ongoing (bit 9). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>33. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>34. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>35. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0100 0000 0000 (MSB → LSB). Sensor Interference Detected (bit 10). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>36. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>37. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>38. The simulated PHD sends a Measurement to PHG under test with Measurement Status field set to 0000 0000 0000 1000 0000 0000 (MSB → LSB). Sensor Unconnected to User</p>
--	---

	<p>(bit 11). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>39. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>40. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>41. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0001 0000 0000 0000 (MSB → LSB). Unknown Sensor Connected (bit 12). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>42. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>43. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>44. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0010 0000 0000 0000 (MSB → LSB). Sensor Displaced (bit 13). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>45. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>46. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>47. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0100 0000 0000 0000 (MSB → LSB). Sensor Malfunctioning (bit 14). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>48. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>49. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p> <ul style="list-style-type: none"> a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute <p>50. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 1000 0000 0000 0000 (MSB → LSB). Sensor Disconnected (bit 15). All remaining fields remain equal to those in step 5. The simulated PHD also deletes all stored records in RACP and stores an identical measurement.</p> <p>51. Check in PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>52. IF C_MAN_BLE_042 = TRUE (PHG supports RACP) THEN</p>
--	---

	<p>a) The PHG under test requests the simulated PHD to report stored records by performing a writing operation in the Record Access Control Point (RACP) and the simulated PHD sends the temporarily stored spot-check measurement to the PHG under test</p> <p>b) Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute</p>
Pass/Fail criteria	<p>In Step 6, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “device-extended-update” (0x8000). If PHG supports RACP, same criteria applies to 7.b.</p> <p>In Step 9, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “device-equipment-malfunction” (0x4000). If PHG supports RACP, same criteria applies to 10.b.</p> <p>In Step 12, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-processing-irregularity” (0x2000). If PHG supports RACP, same criteria applies to 13.b.</p> <p>In Step 15, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-inadequate” (0x1000). If PHG supports RACP, same criteria applies to 16.b.</p> <p>In Step 18, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-poor” (0x0800). If PHG supports RACP, same criteria applies to 19.b.</p> <p>In Step 21, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-low-perfusion” (0x0400). If PHG supports RACP, same criteria applies to 22.b.</p> <p>In Step 24, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-erratic” (0x0200). If PHG supports RACP, same criteria applies to 25.b.</p> <p>In Step 27, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-non-pulsatile” (0x0100). If PHG supports RACP, same criteria applies to 28.b.</p> <p>In Step 30, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-pulse-questionable” (0x0080). If PHG supports RACP, same criteria applies to 31.b.</p> <p>In Step 33, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-searching” (0x0040). If PHG supports RACP, same criteria applies to 34.b.</p> <p>In Step 36, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-interference” (0x0020). If PHG supports RACP, same criteria applies to 37.b.</p> <p>In Step 39, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-off” (0x0010). If PHG supports RACP, same criteria applies to 40.b.</p> <p>In Step 42, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-unsupported” (0x0008). If PHG supports RACP, same criteria applies to 43.b.</p> <p>In Step 45, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-displaced” (0x0004). If PHG supports RACP, same criteria applies to 46.b.</p> <p>In Step 48, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-malfunction” (0x0002). If PHG supports RACP, same criteria applies to 49.b.</p> <p>In Step 51, Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-disconnected” (0x0001). If PHG supports RACP, same criteria applies to 52.b.</p>
Notes (To assist manual testing)	<p>In step 6 (and step 7.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p>

	<p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 80 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^device-extended-update(15) R</p> <p>In step 9 (and step 10.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^device-equipment-malfunction(14) R</p> <p>In step 12 (and step 13.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 20 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-processing-irregularity(13) R</p> <p>In step 15 (and step 16.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 10 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p>
--	--

OBX|n|CWE|150604^MDC_PULS_OXIM_DEV_STATUS^MDC|m.0.0.x|1^**signal-inadequate(12)**|||||R

In step 18 (and step 19.b if applicable), possible values in typical points of observation after transcoder output are:

a) IEEE 11073 Objects and Attributes

Enum-Observed-Value-Basic-Bit-Str attribute is present:

- ☐ Object: Device and Sensor Status Enumeration Object
- ☐ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)
- ☐ Attribute-type: BITS16
- ☐ Attribute-value: **08 00** (hex)

b) WAN PCD-01 message

PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):

OBX|n|CWE|150604^MDC_PULS_OXIM_DEV_STATUS^MDC|m.0.0.x|1^**signal-poor(11)**|||||R

In step 21 (and step 22.b if applicable), possible values in typical points of observation after transcoder output are:

a) IEEE 11073 Objects and Attributes

Enum-Observed-Value-Basic-Bit-Str attribute is present:

- ☐ Object: Device and Sensor Status Enumeration Object
- ☐ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)
- ☐ Attribute-type: BITS16
- ☐ Attribute-value: **04 00** (hex)

b) WAN PCD-01 message

PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):

OBX|n|CWE|150604^MDC_PULS_OXIM_DEV_STATUS^MDC|m.0.0.x|1^**signal-low-perfusion(10)**|||||R

In step 24 (and step 25.b if applicable), possible values in typical points of observation after transcoder output are:

a) IEEE 11073 Objects and Attributes

Enum-Observed-Value-Basic-Bit-Str attribute is present:

- ☐ Object: Device and Sensor Status Enumeration Object
- ☐ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)
- ☐ Attribute-type: BITS16
- ☐ Attribute-value: **02 00** (hex)

b) WAN PCD-01 message

PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):

OBX|n|CWE|150604^MDC_PULS_OXIM_DEV_STATUS^MDC|m.0.0.x|1^**signal-erratic(9)**|||||R

In step 27 (and step 28.b if applicable), possible values in typical points of observation after transcoder output are:

a) IEEE 11073 Objects and Attributes

Enum-Observed-Value-Basic-Bit-Str attribute is present:

- ☐ Object: Device and Sensor Status Enumeration Object
- ☐ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)
- ☐ Attribute-type: BITS16

	<p><input type="checkbox"/> Attribute-value: 01 00 (hex)</p> <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="text-align: center;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-non-pulsatile(8) R</p> <p>In step 30 (and step 31.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <p><input type="checkbox"/> Object: Device and Sensor Status Enumeration Object</p> <p><input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)</p> <p><input type="checkbox"/> Attribute-type: BITS16</p> <p><input type="checkbox"/> Attribute-value: 00 80 (hex)</p> <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="text-align: center;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-pulse-questionable(7) R</p> <p>In step 33 (and step 34.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <p><input type="checkbox"/> Object: Device and Sensor Status Enumeration Object</p> <p><input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)</p> <p><input type="checkbox"/> Attribute-type: BITS16</p> <p><input type="checkbox"/> Attribute-value: 00 40 (hex)</p> <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="text-align: center;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-searching(6) R</p> <p>In step 36 (and step 37.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <p><input type="checkbox"/> Object: Device and Sensor Status Enumeration Object</p> <p><input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662)</p> <p><input type="checkbox"/> Attribute-type: BITS16</p> <p><input type="checkbox"/> Attribute-value: 00 20 (hex)</p> <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="text-align: center;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-interference(5) R</p> <p>In step 39 (and step 40.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p>
--	---

	<p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 10 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-off(4) R</p> <p>In step 42 (and step 43.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 08 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-unsupported(3) R</p> <p>In step 45 (and step 46.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 04 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-displaced(2) R</p> <p>In step 48 (and step 49.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 02 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p>
--	--

	<p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-malfunction(1) R</p> <p>In step 51 (and step 52.b if applicable), possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 01 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-disconnected(0) R</p>
--	--

TP Id		TP/LP-PAN/PHG/PHDTW/PLX/BV-064		
TP label		Whitepaper. Device and Sensor Status Enumeration Object (Continuous Measurements) – Enum-Observed-Value-Bit-Str Attribute		
Coverage	Spec	[Bluetooth PHDT v1.6]		
	Testable items	DSS Enumeration 8; M		
Test purpose		<p>Check that:</p> <p>PHG transcodes Device and Sensor Status field of the PLX Continuous Measurement characteristic into Device and Sensor Status Enumeration Object - Enum-Observed-Value-Basic-Bit-Str attribute</p> <p>[AND]</p> <p>PHG transcodes the Bluetooth Device and Sensor Status field of the PLX Continuous characteristic to 11073 Enum-Observed-Value-Basic-Bit-Str attribute properly</p>		
Applicability		C_MAN_BLE_000 AND C_MAN_BLE_002 AND C_MAN_BLE_040 AND C_MAN_BLE_041		
Other PICS				
Initial condition		The PHG under test and the simulated PHD are in the Standby state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated PHD is configured with a Pulse Oximeter Profile (device specialization), it has a continuous measurement (including fast and slow response measurement values) ready to be sent and it is in the Advertising state (it is discoverable). 2. The simulated PHD implements several BTLE characteristics. The characteristics of interest for this Test Case are: <ol style="list-style-type: none"> a. PLX Continuous Measurement (0x2A5F) b. PLX Features (0x2A60) <ol style="list-style-type: none"> i. Field: Supported Features <ul style="list-style-type: none"> • Format: 16 bit • Value: 0000 0000 0011 0010 (MSB → LSB). Device and Sensor Status support is present (bit 1). Fast and slow response modes are supported (bits 4 and 5). ii. Field: Measurement Status Support 		

	<ul style="list-style-type: none"> • This field is not included
	<ul style="list-style-type: none"> iii. Field: Device and Sensor Status Support <ul style="list-style-type: none"> • Format: 24 bit • Value: 0000 0000 1111 1111 1111 1111 (MSB → LSB). All Device and Sensor Status bits are supported
	3. The PHG under test initiates a discovery process (Scanning state), it discovers the simulated PHD and it starts a pairing process with the simulated PHD (Initiating state).
	4. When the pairing has been completed (Connection state), force the PHG under test to read the PLX Features characteristic.
	5. The simulated PHD sends the Measurement to the PHG under test with the following value:
	<ul style="list-style-type: none"> a. PLX Continuous Measurement (0x2A5F) <ul style="list-style-type: none"> i. Field: Flags <ul style="list-style-type: none"> • Format: 8 bit • Value: 0000 1011 (MSB → LSB). Device and Sensor Status, SpO2PR-Fast and SpO2PR-Slow fields are present. Measurement Status and Pulse Amplitude Index fields are not present. ii. Field: SpO2PR-Normal - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iii. Field: SpO2PR-Normal - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant iv. Field: SpO2PR-Fast - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant v. Field: SpO2PR-Fast - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vi. Field: SpO2PR-Slow - SpO2 (%) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant vii. Field: SpO2PR-Slow - PR (bpm) <ul style="list-style-type: none"> • Format: SFLOAT • Value: Not Relevant viii. Field: Measurement Status <ul style="list-style-type: none"> • This fiels is not included ix. Field: Device and Sensor Status <ul style="list-style-type: none"> • Format: 24 bit • Value: 0000 0000 0000 0000 0000 0001 (MSB → LSB). Extended Display Update Ongoing (bit 0). x. Field: Pulse Amplitude Index (%) <ul style="list-style-type: none"> • This field is not included
	6. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.
	7. The simulated PHD sends a Measurement to the PHG under test with Measurement

	<p>Status field set to 0000 0000 0000 0000 0000 0010 (MSB → LSB). Equipment Malfunction (bit 1). All remaining fields remain equal to those in step 5.</p> <p>8. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>9. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0000 0100 (MSB → LSB). Signal Processing Irregularity Detected (bit 2). All remaining fields remain equal to those in step 5.</p> <p>10. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>11. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0000 1000 (MSB → LSB). Inadequate Signal Detected (bit 3). All remaining fields remain equal to those in step 5.</p> <p>12. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>13. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0001 0000 (MSB → LSB). Poor Signal Detected (bit 4). All remaining fields remain equal to those in step 5.</p> <p>14. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>15. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0010 0000 (MSB → LSB). Low Perfusion Detected (bit 5). All remaining fields remain equal to those in step 5.</p> <p>16. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>17. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 0100 0000 (MSB → LSB). Erratic Signal Detected (bit 6). All remaining fields remain equal to those in step 5.</p> <p>18. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>19. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0000 1000 0000 (MSB → LSB). Non-Pulsatile Signal Detected (bit 7). All remaining fields remain equal to those in step 5.</p> <p>20. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>21. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0001 0000 0000 (MSB → LSB). Questionable Signal Detected (bit 8). All remaining fields remain equal to those in step 5.</p> <p>22. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>23. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0010 0000 0000 (MSB → LSB). Signal Analysis Ongoing (bit 9). All remaining fields remain equal to those in step 5.</p> <p>24. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>25. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 0100 0000 0000 (MSB → LSB). Sensor Interference Detected (bit 10). All remaining fields remain equal to those in step 5.</p> <p>26. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>27. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0000 1000 0000 0000 (MSB → LSB). Sensor Unconnected to User (bit 11). All remaining fields remain equal to those in step 5.</p> <p>28. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>29. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0001 0000 0000 0000 (MSB → LSB). Unknown Sensor Connected (bit 12). All remaining fields remain equal to those in step 5.</p>
--	---

	<p>30. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>31. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0010 0000 0000 0000 (MSB → LSB). Sensor Displaced (bit 13). All remaining fields remain equal to those in step 5.</p> <p>32. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>33. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 0100 0000 0000 0000 (MSB → LSB). Sensor Malfunctioning (bit 14). All remaining fields remain equal to those in step 5.</p> <p>34. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p> <p>35. The simulated PHD sends a Measurement to the PHG under test with Measurement Status field set to 0000 0000 1000 0000 0000 0000 (MSB → LSB). Sensor Disconnected (bit 15). All remaining fields remain equal to those in step 5.</p> <p>36. Check in the PHG transcoder output the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute.</p>
Pass/Fail criteria	<p>In Step 6, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “device-extended-update” (0x8000).</p> <p>In Step 8, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “device-equipment-malfunction” (0x4000).</p> <p>In Step 10, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-processing-irregularity” (0x2000).</p> <p>In Step 12, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-inadequate” (0x1000).</p> <p>In Step 14, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-poor” (0x0800).</p> <p>In Step 16, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-low-perfusion” (0x0400).</p> <p>In Step 18, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-erratic” (0x0200).</p> <p>In Step 20, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-non-pulsatile” (0x0100).</p> <p>In Step 22, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-pulse-questionable” (0x0080).</p> <p>In Step 24, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-searching” (0x0040).</p> <p>In Step 26, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “signal-interference” (0x0020).</p> <p>In Step 28, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-off” (0x0010).</p> <p>In Step 30, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-unsupported” (0x0008).</p> <p>In Step 32, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-displaced” (0x0004).</p> <p>In Step 34, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-malfunction” (0x0002).</p> <p>In Step 36, the Device and Sensor Status Enumeration Object – Enum-Observed-Value-Basic-Bit-Str attribute is present and it is set to “sensor-disconnected” (0x0001).</p>
Notes (To assist manual testing)	<p>In step 6, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <p><input type="checkbox"/> Object: Device and Sensor Status Enumeration Object</p>

	<ul style="list-style-type: none"> ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 80 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^device-extended-update(15) R</p> <p>In step 8, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 40 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^device-equipment-malfunction(14) R</p> <p>In step 10, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 20 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-processing-irregularity(13) R</p> <p>In step 12, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 10 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p>OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-inadequate(12) R</p> <p>In step 14, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p>
--	--

	<ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 08 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-poor(11) R</p> <p>In step 16, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 04 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-low-perfusion(10) R</p> <p>In step 18, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 02 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-erratic(9) R</p> <p>In step 20, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 01 00 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Enum-Observed-Value-Basic-Bit-Str attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-non-pulsatile(8) R</p> <p>In step 22, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p>
--	---

	<p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 00 80 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-pulse-questionable(7) R</p> <p>In step 24, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 00 40 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^signal-searching(6) R</p> <p>In step 26, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 00 20 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-interference(5) R</p> <p>In step 28, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> ❑ Object: Device and Sensor Status Enumeration Object ❑ Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) ❑ Attribute-type: BITS16 ❑ Attribute-value: 00 10 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-off(4) R</p> <p>In step 30, possible values in typical points of observation after transcoder output are:</p>
--	---

	<p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 08 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-unsupported(3) R</p> <p>In step 32, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 04 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-displaced(2) R</p> <p>In step 34, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 02 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-malfunction(1) R</p> <p>In step 36, possible values in typical points of observation after transcoder output are:</p> <p>a) IEEE 11073 Objects and Attributes</p> <p>Enum-Observed-Value-Basic-Bit-Str attribute is present:</p> <ul style="list-style-type: none"> <input type="checkbox"/> Object: Device and Sensor Status Enumeration Object <input type="checkbox"/> Attribute-id: MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR (2662) <input type="checkbox"/> Attribute-type: BITS16 <input type="checkbox"/> Attribute-value: 00 01 (hex) <p>b) WAN PCD-01 message</p> <p>PCD-01 message includes a segment like this with Measurement-Status attribute value (check OBX-5):</p> <p style="padding-left: 40px;">OBX n CWE 150604^MDC_PULS_OXIM_DEV_STATUS^MDC m.0.0.x 1^sensor-disconnected(0) R</p>
--	---

Bibliography

- | | |
|-------------------------|--|
| [b-ITU-T H.810 (2013)] | Recommendation ITU-T H.810 (2013), <i>Interoperability design guidelines for personal health systems</i> . |
| [b-ITU-T H.810 (2015)] | Recommendation ITU-T H.810 (2015), <i>Interoperability design guidelines for personal health systems</i> . |
| [b-Bluetooth PHDT v1.3] | Bluetooth SIG (2012), <i>Personal Health Devices Transcoding White Paper</i> (version 1.3).
https://www.bluetooth.org/docman/handlers/downloaddoc.ashx?doc_id=294540 |
| [b-CDG 1.0] | Continua Health Alliance, Continua Design Guidelines v1.0 (2008), <i>Continua Design Guidelines</i> . |
| [b-CDG 2010] | Continua Health Alliance, Continua Design Guidelines v1.5 (2010), <i>Continua Design Guidelines</i> . |
| [b-CDG 2011] | Continua Health Alliance, Continua Design Guidelines (2011), "Adrenaline", <i>Continua Design Guidelines</i> . |
| [b-CDG 2012] | Continua Health Alliance, Continua Design Guidelines (2012), "Catalyst", <i>Continua Design Guidelines</i> . |
| [b-CDG 2013] | Continua Health Alliance, Continua Design Guidelines (2013), "Endorphin", <i>Continua Design Guidelines</i> . |
| [b-CDG 2015] | Continua Health Alliance, Continua Design Guidelines (2015), "Genome", <i>Continua Design Guidelines</i> . |
| [b-CDG 2016] | Personal Connected Health Alliance, Continua Design Guidelines (2016), "Iris", <i>Continua Design Guidelines</i> . |
| [b-ETSI SR 001 262] | ETSI SR 001 262 v1.8.1 (2003), <i>ETSI drafting rules</i> .
https://docbox.etsi.org/MTS/MTS/10-PromotionalMaterial/MBS-20111118/Referenced%20Documents/Drafting%20Rules.pdf |
| [b-PHD PICS & PIXIT] | PHD PICS and PIXIT Test Tool v7.0.2.0 – Excel sheet v1.13.
http://handle.itu.int/11.1002/2000/12067 |
| [b-PHG PICS & PIXIT] | PHG PICS and PIXIT Test Tool v7.0.2.0 – Excel sheet v1.11.
http://handle.itu.int/11.1002/2000/12067 |
| [b-TI] | PHD Testable items. Test Tool v7.0.2.0 – Excel sheet v1.10.
http://handle.itu.int/11.1002/2000/12067 |

SERIES OF ITU-T RECOMMENDATIONS

Series A	Organization of the work of ITU-T
Series D	Tariff and accounting principles and international telecommunication/ICT economic and policy issues
Series E	Overall network operation, telephone service, service operation and human factors
Series F	Non-telephone telecommunication services
Series G	Transmission systems and media, digital systems and networks
Series H	Audiovisual and multimedia systems
Series I	Integrated services digital network
Series J	Cable networks and transmission of television, sound programme and other multimedia signals
Series K	Protection against interference
Series L	Environment and ICTs, climate change, e-waste, energy efficiency; construction, installation and protection of cables and other elements of outside plant
Series M	Telecommunication management, including TMN and network maintenance
Series N	Maintenance: international sound programme and television transmission circuits
Series O	Specifications of measuring equipment
Series P	Telephone transmission quality, telephone installations, local line networks
Series Q	Switching and signalling, and associated measurements and tests
Series R	Telegraph transmission
Series S	Telegraph services terminal equipment
Series T	Terminals for telematic services
Series U	Telegraph switching
Series V	Data communication over the telephone network
Series X	Data networks, open system communications and security
Series Y	Global information infrastructure, Internet protocol aspects, next-generation networks, Internet of Things and smart cities
Series Z	Languages and general software aspects for telecommunication systems