

I n t e r n a t i o n a l T e l e c o m m u n i c a t i o n U n i o n

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

T.801

Amendment 2

(05/2005)

SERIES T: TERMINALS FOR TELEMATIC SERVICES

Information technology – JPEG 2000 image coding
system: Extensions

**Amendment 2: Extended capabilities marker
segment**

ITU-T Recommendation T.801 (2002) – Amendment 2



Information technology – JPEG 2000 image coding system: Extensions

Amendment 2
Extended capabilities marker segment

Summary

This amendment requires a change to the interpretation of the Rsiz parameter values within the SIZ marker segment. Specifically, the second most significant bit in the Rsiz field is no longer restricted to be equal to 0. Two new values for the Rsiz field are also defined. Finally, this amendment extends the codestream syntax by providing a new marker segment, CAP, to signal extended capabilities required to decode the codestream.

NOTE – ISO/IEC 15444-2 Amendment 1 and Technical Corrigenda 1 and 2 are already integrated in T.801 approved by ITU-T on 2002-08.

Source

Amendment 2 to ITU-T Recommendation T.801 (2002) was approved on 14 May 2005 by ITU-T Study Group 16 (2005-2008) under the ITU-T Recommendation A.8 procedure. An identical text is also published as ISO/IEC 15444-2, Amendment 2.

FOREWORD

The International Telecommunication Union (ITU) is the United Nations specialized agency in the field of telecommunications. The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of ITU. ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Assembly (WTSA), which meets every four years, establishes the topics for study by the ITU-T study groups which, in turn, produce Recommendations on these topics.

The approval of ITU-T Recommendations is covered by the procedure laid down in WTSA Resolution 1.

In some areas of information technology which fall within ITU-T's purview, the necessary standards are prepared on a collaborative basis with ISO and IEC.

NOTE

In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Compliance with this Recommendation is voluntary. However, the Recommendation may contain certain mandatory provisions (to ensure e.g. interoperability or applicability) and compliance with the Recommendation is achieved when all of these mandatory provisions are met. The words "shall" or some other obligatory language such as "must" and the negative equivalents are used to express requirements. The use of such words does not suggest that compliance with the Recommendation is required of any party.

INTELLECTUAL PROPERTY RIGHTS

ITU draws attention to the possibility that the practice or implementation of this Recommendation may involve the use of a claimed Intellectual Property Right. ITU takes no position concerning the evidence, validity or applicability of claimed Intellectual Property Rights, whether asserted by ITU members or others outside of the Recommendation development process.

As of the date of approval of this Recommendation, ITU had received notice of intellectual property, protected by patents, which may be required to implement this Recommendation. However, implementors are cautioned that this may not represent the latest information and are therefore strongly urged to consult the TSB patent database.

© ITU 2005

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without the prior written permission of ITU.

CONTENTS

	<i>Page</i>
1) Table A.2.....	1
2) New clause A.3.13.....	2

Introduction

The JPEG 2000 specification is structured in several parts: Part 1 is defined in ITU-T Rec. T.800 | ISO/IEC 15444-1 ("Core coding system"). Part 2 is defined in ITU-T Rec. T.801 | ISO/IEC 15444-2 ("Extensions"). Part 3 is defined in ITU-T Rec. T.802 | ISO/IEC 15444-3 ("Motion JPEG 2000"). Part 4 is defined in ITU-T Rec. T.803 | ISO/IEC 15444-4 ("Conformance testing"). Part 5 is defined in ITU-T Rec. T.804 | ISO/IEC 15444-5 ("Reference software"). Part 6 is defined in ISO/IEC 15444-6 ("Compound image file format"). Part 7 has been withdrawn. Part 8 is defined in ISO/IEC 15444-8 ("Secured JPEG format"). Part 9 is defined in ITU-T Rec. T.808 | ISO/IEC 15444-9 ("Interactivity tools, APIs and protocols"). Part 10 is defined in ISO/IEC 15444-10 ("3-D and floating point data"). Part 11 is defined in ISO/IEC 15444-11 ("Wireless"). Part 12 is defined in ISO/IEC 15444-12 ("ISO base media file format").

The need for this amendment arises from a lack of sufficient codespace in the Rsiz capabilities parameter in the SIZ marker segment. The Rsiz parameter contains 16 bits, which are used to signal decoding capabilities required by the encoded codestream. According to Table A.10 of ITU-T Rec. T.800 | ISO/IEC 15444-1, the only values used in Part 1 codestreams are:

$$\text{Rsiz} = 0000\ 0000\ 0000\ 00xx$$

where:

xx = 00 indicates a generic Part 1 codestream

xx = 01 indicates a profile 0 codestream

xx = 10 indicates a profile 1 codestream

In Table A.2, the first bit of Rsiz is used to indicate the presence of Part 2 features, and the bit values assigned to specific Part 2 capabilities are:

$$\text{Rsiz} = 1000\ yzzz\ zzzz\ zzzz$$

where y = 1 indicates a codestream using Part 2 (precinct-dependent quantization) and bits 6-16 (the z-bits) indicate extensions defined in the Part 2 annexes. In particular, note that there are only 3 unused bits (bits #2, 3, and 4) remaining in the Rsiz field.

Signalling Part 2 capabilities requires a full bit per capability because Part 2 features can be selected independently (i.e., in arbitrary combinations) by encoders, and this situation can be expected to continue for extensions defined in subsequent Parts of the JPEG 2000 family or in future Part 2 amendments. This includes extensions presently under development in JPEG 2000 Parts 8 (JPSEC), 10 (JP3D), and 11 (JPWL), many of which will be used in conjunction with other extensions from different Parts of JPEG 2000. Consequently, the three remaining unused bits in Rsiz are far from sufficient for signalling future JPEG 2000 codestream capabilities.

Rather than forcing future JPEG 2000 extensions to invent their own methods of signalling required codestream capabilities, this amendment defines a unified, scalable, semantically flexible framework for capabilities signalling that can be used by all future JPEG 2000 Parts and amendments. Moreover, it is fully backwards-compatible with the present capabilities signalling employed in the Rsiz parameter. The key idea is to define a new variable-length Part 2 marker segment (the CAP marker segment) that indicates the Parts and the specific extended capabilities used to encode the codestream in question. Use of the CAP marker segment is indicated by the second-most-significant bit in the Rsiz parameter.

The second bit in the Rsiz parameter can also optionally be used to indicate that a CAP marker segment is used. To a baseline decoder, this will appear as the indication of an unknown capability, which generally prevents the decoder from further decoding the codestream.

INTERNATIONAL STANDARD
ITU-T RECOMMENDATION

Information technology – JPEG 2000 image coding system: Extensions

Amendment 2
Extended capabilities marker segment

1) Table A.2

In Table A.2:

- replace all occurrences of “1000” in the four most significant bits of the index values with “1x00”; and
- add the following entries immediately preceding the entry describing variable DC offset capability:

0100 0000 0000 00xx	Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 and at least one extended capability indicated in the CAP marker segment
1100 xxxx xxxx xxxx	Extended capabilities defined in this Recommendation International Standard as indicated in this parameter, and at least one other extended capability indicated in the CAP marker segment

so that Table A.2 will now read:

Value (bits)		Capability
MSB	LSB	
0000	0000 0000 0000	Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 only
1x00	xxxx xxxx xxxx	At least one of the extended capabilities specified in this Recommendation International Standard is present
0100	0000 0000 00xx	<u>Capabilities specified in ITU-T Rec. T.800 ISO/IEC 15444-1 and at least one extended capability indicated in the CAP marker segment</u>
1100	xxxx xxxx xxxx	<u>Extended capabilities defined in this Recommendation International Standard as indicated in this parameter, and at least one other extended capability indicated in the CAP marker segment</u>
1x00	xxx0 xxxx xxx1	Variable DC offset capability is required to decode this codestream ^{a) b)}
1x00	xxxx xxxx xx1x	Variable scalar quantization capability is required to decode this codestream ^{a)}
1x00	xxxx xxxx x1xx	Trellis coded quantization capability is useful to decode this codestream ^{c)}
1x00	xxxx xxxx 1xxx	Visual masking capability is useful to decode this codestream ^{c)}
1x00	xxxx xxx1 xxxx	Single sample overlap capability is required to decode this codestream ^{a)}
1x00	xxxx xx1x xxxx	Arbitrary decomposition style capability is required to decode this codestream ^{a)}
1x00	xxxx x1xx xxxx	Arbitrary transformation kernel capability is required to decode this codestream ^{a)}
1x00	xxxx 1xxx xxxx	Whole sample symmetric transformation kernel capability is required to decode this codestream ^{a)}
1x00	xxx1 xxxx xxxx	Multiple component transformation capability is required to decode this codestream ^{a)}
1x00	xx1x xxxx xxxx	Non-linear point transformation capability is useful to decode this codestream ^{c)}
1x00	x1xx xxxx xxxx	Arbitrary shaped region of interest capability is required to decode this codestream ^{a)}
1x00	1xxx xxxx xxxx	Precinct-dependent quantization is required to decode this codestream ^{a)}
		All other values reserved
a)	"Required to decode" implies that no useful data or image can be reconstructed without the use of this capability.	
b)	Shall not be used with the multiple component transformation.	
c)	"Useful to decode" implies that use of this capability would improve the quality of the reconstructed data or image; however, the data or image may be decoded without its use.	

2) **New clause A.3.13**

Add the following A.3.13:

A.3.13 Extended capabilities (CAP)

Function: Signals that extended capabilities were used to create (and are recommended or required to decode) a codestream.

Usage: Optional. If present, must be included anywhere in the main header after the SIZ marker segment. The second-most-significant bit in Rsiz may optionally be set to 1 to indicate the presence of the CAP marker segment.

Length: Variable.



Figure A.13 – Extended capabilities syntax

CAP: Marker code. Table A.49 shows the size and values of the symbol and parameters for the extended capabilities marker segment.

Lcap: Length of the CAP marker segment (not including the marker). Length is given by the following formula:

$$Lcap = 6 + 2n \text{ bytes}$$

where *n* is the number of 1-bits occurring in Pcap.

Pcap: 32-bit field indicating the Parts containing extended capabilities that are used to encode the image. A value of 1 in the *k*th-most-significant bit of Pcap indicates the use of capabilities from Part *k* (ISO/IEC 15444-*k*). The first non-zero bit in Pcap corresponds to the first Ccap^{*i*} field (*i* = 1); the second non-zero bit in Pcap corresponds to the second Ccap^{*i*} field (*i* = 2), etc. Table A.50 shows the usage of the Pcap parameter.

Ccap^{*i*}: 16-bit field indicating capabilities specified in Part *p_i* where bit #*p_i* is the *i*th non-zero bit in Pcap. If *p_i* = 2, the bits in Ccap^{*i*} shall indicate capabilities defined in Part 2 amendments; the MSB of Rsiz may be set to the value 1 in this case. For other Parts, the bits in Ccap^{*i*} may be used to indicate capabilities defined in Part *p_i*. The precise meaning of the bits in Ccap^{*i*} shall be specified in Part *p_i* (ISO/IEC 15444-*p_i*).

Table A.49 – Extended capabilities parameter values

Parameter	Size (bits)	Value
CAP	16	0xFF50
Lcap	16	80-560
Pcap	32	See Table A.50
Ccap ^{<i>i</i>}	16	Value and meaning specified in ISO/IEC 15444- <i>k</i> , where the <i>i</i> th non-zero bit in Pcap occurs in its <i>k</i> th most significant bit

Table A.50 – Part parameter values for the Pcap parameter

Values (bits)	Part parameter
MSB	LSB
1xxx xxxx xxxx xxxx xxxx xxxx xxxx xxxx	Extended capabilities from ISO/IEC 15444-1 were used to encode the image
x1xx xxxx xxxx xxxx xxxx xxxx xxxx xxxx	Extended capabilities from ISO/IEC 15444-2 were used to encode the image
...	...
xxxx xxxx xxxx xxxx xxxx xxxx xxxx xxx1	Extended capabilities from ISO/IEC 15444-32 were used to encode the image

Guidance on usage (informative): Encoders that wish to induce baseline JPEG-2000 (Part 1) decoders to attempt best-effort decoding of a codestream containing non-Part 1 features may elect not to use the second-most-significant bit in Rsiz to signal the presence of the CAP marker segment. According to clause A.1 of ITU-T Rec. T.800 | ISO/IEC 15444-1, decoder implementations are supposed to deal with unrecognized marker segments by using the length parameter to discard the marker segment.

Because of this possibility, decoders that recognize any of the capabilities that would be indicated in a CAP marker segment may choose to parse for the CAP marker segment in all JPEG 2000 codestreams, regardless of the value of the second Rsiz bit. Encoders should facilitate this parsing by placing the CAP marker segment as close as possible to the front of the main header. It is recommended that the CAP marker segment always appear before any other marker segments that support extended capabilities indicated in the CAP marker segment, so that such capabilities will have been indicated to the decoder prior to encountering any related marker segments. Encoders that wish to deter baseline decoders from attempting to decode a codestream that truly requires capabilities indicated in the CAP marker segment should set the second Rsiz bit to 1.

SERIES OF ITU-T RECOMMENDATIONS

Series A	Organization of the work of ITU-T
Series D	General tariff principles
Series E	Overall network operation, telephone service, service operation and human factors
Series F	Non-telephone telecommunication services
Series G	Transmission systems and media, digital systems and networks
Series H	Audiovisual and multimedia systems
Series I	Integrated services digital network
Series J	Cable networks and transmission of television, sound programme and other multimedia signals
Series K	Protection against interference
Series L	Construction, installation and protection of cables and other elements of outside plant
Series M	Telecommunication management, including TMN and network maintenance
Series N	Maintenance: international sound programme and television transmission circuits
Series O	Specifications of measuring equipment
Series P	Telephone transmission quality, telephone installations, local line networks
Series Q	Switching and signalling
Series R	Telegraph transmission
Series S	Telegraph services terminal equipment
Series T	Terminals for telematic services
Series U	Telegraph switching
Series V	Data communication over the telephone network
Series X	Data networks, open system communications and security
Series Y	Global information infrastructure, Internet protocol aspects and next-generation networks
Series Z	Languages and general software aspects for telecommunication systems