



UNION INTERNATIONALE DES TÉLÉCOMMUNICATIONS

UIT-T

SECTEUR DE LA NORMALISATION
DES TÉLÉCOMMUNICATIONS
DE L'UIT

X.245

(04/95)

**RÉSEAUX POUR DONNÉES ET COMMUNICATION
ENTRE SYSTÈMES OUVERTS**

**INTERCONNEXION DES SYSTÈMES OUVERTS –
FORMULAIRES PICS**

**TECHNOLOGIES DE L'INFORMATION –
INTERCONNEXION DES SYSTÈMES
OUVERTS – PROTOCOLE DE SESSION
EN MODE CONNEXION: FORMULAIRE
DE DÉCLARATION DE CONFORMITÉ
D'INSTANCE DE PROTOCOLE**

Recommandation UIT-T X.245

(Antérieurement «Recommandation du CCITT»)

AVANT-PROPOS

L'UIT (Union internationale des télécommunications) est une institution spécialisée des Nations Unies dans le domaine des télécommunications. L'UIT-T (Secteur de la normalisation des télécommunications) est un organe permanent de l'UIT. Au sein de l'UIT-T, qui est l'entité qui établit les normes mondiales (Recommandations) sur les télécommunications, participent quelque 179 pays membres, 84 exploitations de télécommunications reconnues, 145 organisations scientifiques et industrielles et 38 organisations internationales.

L'approbation des Recommandations par les Membres de l'UIT-T s'effectue selon la procédure définie dans la Résolution n° 1 de la Conférence mondiale de normalisation des télécommunications (CMNT), (Helsinki, 1993). De plus, la CMNT, qui se réunit tous les quatre ans, approuve les Recommandations qui lui sont soumises et établit le programme d'études pour la période suivante.

Dans certains secteurs de la technologie de l'information qui correspondent à la sphère de compétence de l'UIT-T, les normes nécessaires se préparent en collaboration avec l'ISO et la CEI. Le texte de la Recommandation X.245 de l'UIT-T a été approuvé le 10 avril 1995. Son texte est publié, sous forme identique, comme Norme internationale ISO/CEI 8327-2.

NOTE

Dans la présente Recommandation, l'expression «Administration» est utilisée pour désigner de façon abrégée aussi bien une administration de télécommunications qu'une exploitation reconnue.

© UIT 1997

Droits de reproduction réservés. Aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'UIT.

RECOMMANDATIONS UIT-T DE LA SÉRIE X

RÉSEAUX POUR DONNÉES ET COMMUNICATION ENTRE SYSTÈMES OUVERTS

(Février 1994)

ORGANISATION DES RECOMMANDATIONS DE LA SÉRIE X

Domaine	Recommandations
RÉSEAUX PUBLICS POUR DONNÉES	
Services et services complémentaires	X.1-X.19
Interfaces	X.20-X.49
Transmission, signalisation et commutation	X.50-X.89
Aspects réseau	X.90-X.149
Maintenance	X.150-X.179
Dispositions administratives	X.180-X.199
INTERCONNEXION DES SYSTÈMES OUVERTS	
Modèle et notation	X.200-X.209
Définition des services	X.210-X.219
Spécifications des protocoles en mode connexion	X.220-X.229
Spécifications des protocoles en mode sans connexion	X.230-X.239
Formulaires PICS	X.240-X.259
Identification des protocoles	X.260-X.269
Protocoles de sécurité	X.270-X.279
Objets gérés de couche	X.280-X.289
Test de conformité	X.290-X.299
INTERFONCTIONNEMENT DES RÉSEAUX	
Considérations générales	X.300-X.349
Systèmes mobiles de transmission de données	X.350-X.369
Gestion	X.370-X.399
SYSTÈMES DE MESSAGERIE	X.400-X.499
ANNUAIRE	X.500-X.599
RÉSEAUTAGE OSI ET ASPECTS DES SYSTÈMES	
Réseautage	X.600-X.649
Dénomination, adressage et enregistrement	X.650-X.679
Notation de syntaxe abstraite numéro un (ASN.1)	X.680-X.699
GESTION OSI	X.700-X.799
SÉCURITÉ	X.800-X.849
APPLICATIONS OSI	
Engagement, concomitance et rétablissement	X.850-X.859
Traitement des transactions	X.860-X.879
Opérations distantes	X.880-X.899
TRAITEMENT OUVERT RÉPARTI	X.900-X.999

TABLE DES MATIÈRES

	<i>Page</i>
Résumé	iv
Introduction	iv
1 Domaine d'application	1
2 Références normatives	1
2.1 Recommandations Normes internationales identiques.....	1
2.2 Paires de Recommandations Normes internationales équivalentes par leur contenu technique	1
3 Définitions.....	2
4 Abréviations	2
5 Conformité	2
Annexe A – Formulaire de déclaration de conformité d'instance de protocole (PICS) pour le protocole de session en mode connexion.....	3
A.1 Identification of PICS proforma corrigenda	3
A.2 Instructions.....	3
A.2.1 Purpose and structure of the proforma	3
A.2.2 Symbols, terms and abbreviations.....	3
A.2.2.1 Introduction.....	3
A.2.2.2 Item numbering	4
A.2.2.3 Status column.....	4
A.2.2.4 Support column	6
A.2.2.5 Value column.....	6
A.2.2.6 Mnemonic column	6
A.2.2.7 Length column	6
A.2.3 Instructions for completion	7
A.3 Identification of the implementation.....	7
A.3.1 Date of statement	7
A.3.2 Implementation details.....	7
A.4 Protocol Identification	8
A.4.1 ITU-T Rec. X.225 ISO/IEC 8327-1 protocol details	8
A.4.2 ITU-T Rec. X.225 ISO/IEC 8327-1 protocol versions	8
A.4.3 ITU-T Rec. X.225 ISO/IEC 8327-1 technical corrigenda implemented.....	8
A.5 Global statement of conformance	8
A.6 Supported functional units and protocol mechanisms	9
A.6.1 Functional units.....	9
A.6.2 Protocol mechanisms	9
A.7 Supported SPDUs	10
A.7.1 Kernel functional unit	10
A.7.1.1 Supported roles	10
A.7.1.2 Support for the SPDUs associated with the Kernel functional unit	11
A.7.1.3 Support for the SPDUs associated with Token Exchange	11
A.7.2 Negotiated Release functional unit	11
A.7.2.1 Supported roles	11
A.7.2.2 Support for the SPDUs associated with the Negotiated Release functional unit	11
A.7.3 Half Duplex functional unit	12
A.7.3.1 Supported roles	12
A.7.3.2 Support for the SPDUs associated with the Half Duplex functional unit	12
A.7.4 Duplex functional unit	12

	<i>Page</i>
A.7.5 Expedited Data functional unit	12
A.7.5.1 Supported roles	12
A.7.5.2 Support for the SPDU associated with the Expedited Data functional unit....	12
A.7.6 Typed Data functional unit	12
A.7.6.1 Supported roles	12
A.7.6.2 Support for the SPDU associated with the Typed Data functional unit	13
A.7.7 Capability Data functional unit	13
A.7.7.1 Supported roles	13
A.7.7.2 Support for the SPDUs associated with the Capability Data functional unit..	13
A.7.8 Minor synchronize functional unit	13
A.7.8.1 Supported roles	13
A.7.8.2 Support for the SPDUs associated with the Minor synchronize functional unit	13
A.7.9 Symmetric synchronize functional unit	14
A.7.9.1 Supported roles	14
A.7.9.2 Support for the SPDUs associated with the Symmetric synchronize functional unit	14
A.7.10 Data separation functional unit	14
A.7.11 Major synchronize functional unit	14
A.7.11.1 Supported roles	14
A.7.11.2 Support for the SPDUs associated with the Major synchronize functional unit	14
A.7.12 Resynchronize functional unit	15
A.7.12.1 Supported roles	15
A.7.12.2 Supported resynchronize types	15
A.7.12.3 Support for the SPDUs associated with the Resynchronize functional unit ...	15
A.7.13 Exceptions functional unit	15
A.7.13.1 Supported roles	15
A.7.13.2 Support for the SPDUs associated with the Exceptions functional unit	16
A.7.14 Activity management functional unit	16
A.7.14.1 Supported roles	16
A.7.14.2 Support for the SPDUs associated with the Activity management functional unit	17
A.8 Supported SPDU-parameters	18
A.8.1 Connect (CN) SPDU	18
A.8.1.1 Connection Identifier	18
A.8.1.2 Connect/Accept Item	18
A.8.1.3 Single Items	19
A.8.2 Overflow Accept (OA) SPDU	19
A.8.3 Connect Data Overflow (CDO) SPDU	19
A.8.4 Accept (AC) SPDU	20
A.8.4.1 Connection Identifier	20
A.8.4.2 Connect/Accept Item	20
A.8.4.3 Single Items	21
A.8.5 Refuse (RF) SPDU	21
A.8.5.1 Connection Identifier	21
A.8.5.2 Single Items	22
A.8.6 Finish (FN) SPDU	22
A.8.7 Disconnect (DN) SPDU	22
A.8.8 Not Finish (NF) SPDU	23
A.8.9 Abort (AB) SPDU	23
A.8.10 Abort Accept (AA) SPDU	23
A.8.11 Data Transfer (DT) SPDU	23
A.8.12 Expedited Data (EX) SPDU	23
A.8.13 Typed Data (TD) SPDU	24
A.8.14 Capability Data (CD) SPDU	24
A.8.15 Capability Data Ack (CDA) SPDU	24

	<i>Page</i>
A.8.16 Give Tokens (GT) SPDU	24
A.8.17 Please Tokens (PT) SPDU	25
A.8.18 Minor Sync Point (MIP) SPDU	25
A.8.19 Minor Sync Ack (MIA) SPDU	25
A.8.20 Major Sync Point (MAP) SPDU	26
A.8.21 Major Sync Ack (MAA) SPDU	26
A.8.22 Resynchronize (RS) SPDU	26
A.8.23 Resynchronize Ack (RA) SPDU	27
A.8.24 Prepare (PR) SPDU	27
A.8.25 Exception Report (ER) SPDU	27
A.8.26 Exception Data (ED) SPDU	27
A.8.27 Give Tokens Confirm (GTC) SPDU	28
A.8.28 Give Tokens Ack (GTA) SPDU	28
A.8.29 Activity Start (AS) SPDU	28
A.8.30 Activity Resume (AR) SPDU	28
A.8.30.1 Linking Information	28
A.8.30.2 Single Items	29
A.8.31 Activity Interrupt (AI) SPDU	29
A.8.32 Activity Interrupt Ack (AIA) SPDU	29
A.8.33 Activity Discard (AD) SPDU	29
A.8.34 Activity Discard Ack (ADA) SPDU	30
A.8.35 Activity End (AE) SPDU	30
A.8.36 Activity End Ack (AEA) SPDU	30
Annexe B – Liste des déclarations conditionnelles	32
Annexe C – Liste des mnémoniques utilisés dans les déclarations conditionnelles et optionnelles	36

Résumé

La présente Recommandation | Norme internationale fournit le formulaire de déclaration de conformité d'instance de protocole (PICS) applicable aux protocoles de session en mode connexion qui est spécifié dans la Recommandation X.225. Le formulaire PICS représente sous la forme de tableaux, les éléments obligatoires et optionnels du protocole de session en mode connexion. Le formulaire PICS est utilisé pour indiquer les caractéristiques et options d'une instance particulière du protocole de session en mode connexion.

Introduction

La présente Recommandation | Norme internationale fait partie d'un ensemble de Recommandations | Normes internationales élaborées pour faciliter l'interconnexion des équipements informatiques. Les relations entre la présente Recommandation | Norme internationale et les autres Recommandations et Normes internationales de l'ensemble sont définies par le modèle de référence pour l'interconnexion des systèmes ouverts (Rec. UIT-T X.200 | ISO/CEI 7498-1). Le modèle de référence subdivise le domaine de la normalisation en vue de l'interconnexion en une série de couches de spécification, chaque couche étant de taille gérable.

L'interconnexion des systèmes ouverts vise à permettre, moyennant un minimum d'accords techniques en dehors des normes d'interconnexion, l'interconnexion des équipements informatiques:

- provenant de divers fabricants;
- gérés différemment;
- de niveaux de complexité différents;
- s'appuyant sur diverses technologies.

La Rec. UIT-T X.225 | ISO/CEI 8327-1 spécifie le protocole de session en mode connexion.

Pour évaluer la conformité d'une application particulière, il est nécessaire de disposer d'une description des capacités et des options qui ont été incluses. Une telle description est appelée déclaration de conformité d'instance de protocole (PICS).

La présente Recommandation | Norme internationale contient le formulaire PICS pour le protocole de session en mode connexion, tel qu'il est défini dans la Rec. UIT-T X.225 | ISO/CEI 8327-1.

NORME INTERNATIONALE

RECOMMANDATION UIT-T

**TECHNOLOGIES DE L'INFORMATION – INTERCONNEXION
DES SYSTÈMES OUVERTS – PROTOCOLE DE SESSION
EN MODE CONNEXION: FORMULAIRE DE DÉCLARATION
DE CONFORMITÉ D'INSTANCE DE PROTOCOLE**

1 Domaine d'application

La présente Recommandation | Norme internationale décrit le formulaire de déclaration de conformité d'instance de protocole (PICS) de session en mode connexion, tel qu'il est spécifié dans la Rec. UIT-T X.225 | ISO/CEI 8327-1, conformément aux prescriptions et directives pertinentes de la Rec. UIT-T X.296 | ISO/CEI 9646-7. L'utilisation détaillée de ce formulaire est décrite dans la présente Recommandation | Norme internationale.

Le fournisseur d'une réalisation déclarée conforme à la Rec. UIT-T X.225 | ISO/CEI 8327-1 est tenu de remplir un exemplaire du formulaire PICS fourni en Annexe A; il doit également fournir les informations nécessaires pour identifier ladite réalisation et ledit fournisseur.

2 Références normatives

Les Recommandations et Normes internationales suivantes contiennent des dispositions qui, par suite de la référence qui y est faite, constituent des dispositions valables pour la présente Recommandation | Norme internationale. Au moment de la publication, les éditions indiquées étaient en vigueur. Toutes Recommandations et Normes sont sujettes à révision et les parties prenantes aux accords fondés sur la présente Recommandation | Norme internationale sont invitées à rechercher la possibilité d'appliquer les éditions les plus récentes des Recommandations et Normes indiquées ci-après. Les membres de la CEI et de l'ISO possèdent le registre des Normes internationales en vigueur. Le Bureau de la normalisation des télécommunications de l'UIT tient à jour une liste des Recommandations de l'UIT-T en vigueur.

2.1 Recommandations | Normes internationales identiques

- Recommandation UIT-T X.200 (1994) | ISO/CEI 7498-1:1994, *Technologies de l'information – Interconnexion des systèmes ouverts – Modèle de référence de base: le modèle de référence de base.*
- Recommandation UIT-T X.214 (1993) | ISO/CEI 8072:1994, *Technologies de l'information – Interconnexion des systèmes ouverts – Définition du service de transport.*
- Recommandation UIT-T X.215 (1995) | ISO/CEI 8326:1996, *Technologies de l'information – Interconnexion des systèmes ouverts – Définition du service de session.*
- Recommandation UIT-T X.225 (1995) | ISO/CEI 8327-1:1996, *Technologies de l'information – Interconnexion des systèmes ouverts – Protocole de session en mode connexion: spécification.*

2.2 Paires de Recommandations | Normes internationales équivalentes par leur contenu technique

- Recommandation UIT-T X.290 (1995), *Cadre général et méthodologie des tests de conformité d'interconnexion des systèmes ouverts pour les Recommandations sur les protocoles pour les applications de l'UIT-T – Concepts généraux.*

ISO/CEI 9646-1:1994, *Technologies de l'information – Interconnexion des systèmes ouverts – Cadre général et méthodologie des tests de conformité OSI – Partie 1: Concepts généraux.*

- Recommandation UIT-T X.296 (1995), *Cadre général et méthodologie des tests de conformité OSI pour les Recommandations sur les protocoles pour les applications de l'UIT-T – Déclarations de conformité d'instance.*

ISO/CEI 9646-7:1995, *Technologies de l'information – Interconnexion des systèmes ouverts (OSI) – Essais de conformité – Méthodologie générale et procédures – Partie 7: Déclaration de conformité des mises en œuvre.*

3 Définitions

Pour les besoins de la présente Recommandation | Norme internationale, les définitions suivantes s'appliquent.

- 3.1** Les termes définis dans la Rec. UIT-T X.225 | ISO/CEI 8327-1.
- 3.2** Les termes suivants, définis dans la Rec. UIT-T X.290 | ISO/CEI 9646-1:
- a) déclaration de conformité d'instance de protocole (PICS);
 - b) formulaire PICS.
- 3.3** Termes additionnels:
- demandeur: machine SPM qui lance une action particulière;
 - accepteur: machine SPM qui accepte une action particulière.

4 Abréviations

- 4.1** Les abréviations sont données dans la Rec. UIT-T X.225 | ISO/CEI 8327-1 et dans l'article 8.
- 4.2** La présente Recommandation | Norme internationale utilise l'abréviation suivante définie dans la Rec. UIT-T X.290 | ISO/CEI 9646-1:
- PICS Déclaration de conformité d'instance de protocole (*protocol implementation conformance statement*).
- 4.3** Pour les besoins de la présente Recommandation | Norme internationale, les abréviations suivantes s'appliquent également:
- | | |
|------------|-------------------|
| Sts | Colonne «Status» |
| Spt | Colonne «Support» |
| Str | Emetteur |
| Rcv | Récepteur |

5 Conformité

Une déclaration PICS conforme doit être techniquement équivalente au formulaire PICS publié par l'UIT-T | ISO/CEI dont elle doit conserver la numérotation et l'ordre des items.

Une déclaration PICS conforme à la présente Recommandation | Norme internationale doit:

- a) décrire une réalisation qui est conforme à la Rec. UIT-T X.225 | ISO/CEI 8327-1;
- b) être établie selon un formulaire PICS conforme, rempli conformément aux directives indiquées en A.2;
- c) inclure les informations nécessaires pour identifier sans ambiguïté le fournisseur et la réalisation.

Annexe A

Formulaire de déclaration de conformité d'instance de protocole (PICS) pour le protocole de session en mode connexion¹⁾

(Cette annexe fait partie intégrante de la présente Recommandation | Norme internationale)

A.1 Identification of PICS proforma corrigenda

The supplier of the PICS proforma shall identify any corrigenda (i.e. Technical Corrigenda or equivalent) to the published proforma that have been applied. Suppliers of the proforma should modify the proforma, or attach relevant additional pages in order to apply the corrigenda, and then record the application of the corrigenda in the table below.

Identification of corrigenda applied to this PICS proforma	ITU-T Rec. X.245 (1995) ISO/IEC 8327-2:1996 Corr: Corr: Corr:
--	--

A.2 Instructions

A.2.1 Purpose and structure of the proforma

The purpose of this PICS proforma is to provide suppliers of implementation of ITU-T Rec. X.225 | ISO/IEC 8327-1 with a consistent means of stating which capabilities have been implemented.

The proforma is in form of a questionnaire and consists of a set of items. An item is provided for each capability for which an implementation choice is allowed. Items are also provided for major mandatory capabilities for which no implementation choice is allowed. Each item includes an item number, an item description, a status value specifying the support requirement, and room for a support answer to be provided by the supplier.

This clause provides general information and instructions for completion of the proforma.

Subclause A.3 is for identification of the implementation.

Subclause A.4 contains the means of specifying, at high level, the protocol and corrigenda that have been implemented.

Subclause A.5 contains the global statement of conformance.

Subclauses A.6 onwards contain tables in which the supplier specifies details of the implementation options chosen.

NOTE – Throughout the PICS proforma, tables specifying Requestor and Accpetor roles are inserted as required for precise definition of the status of SPDUs and SPDU parameters, but these tables shall not be used for static conformance review nor for test case selection.

A.2.2 Symbols, terms and abbreviations

A.2.2.1 Introduction

Notations have been introduced in order to reduce the size of tables in the PICS proforma. These have allowed the use of multi-column layout where the columns are headed 'Status', 'Support', 'Value', 'Mnemonic' and 'Length'. The definition of each are given below.

Additionally, the following definitions apply.

A.2.2.1.1 (PICS) item: A row in a PICS proforma table.

¹⁾ Droits de reproduction du formulaire PICS: Les utilisateurs de la présente Recommandation | Norme internationale sont autorisés à reproduire le formulaire PICS de la présente annexe pour utiliser celui-ci conformément à son objet. Ils sont également autorisés à publier le formulaire une fois celui-ci complété.

A.2.2.1.2 (PICS) question: The question to be answered in the intersection of a PICS item and either a support column (i.e. "Is this item supported in the context applying to this table and column") or supported values column (i.e. "What values are supported for this item in the context applying to this table and column") in a PICS proforma table.

A.2.2.1.3 status (value): An allowed entry in the status column for an item in a PICS proforma table.

A.2.2.1.4 (support) answer: An allowed entry in the support or supported values columns for an item in a PICS, in answer to a PICS question.

A.2.2.2 Item numbering

Each line within the PICS proforma which requires implementation detail to be entered is given an item number in the first column. The item number column provides a means of uniquely referencing each possible answer within the PICS proforma. Such referencing is necessary for specifying predicates, conditional expressions, test suite parameters, and test suite selection expressions.

The means of referencing individual answers is to specify the following sequence:

- a) if, and only if, the reference is being made from another Specification, then start with an unambiguous identifier for the relevant ICS proforma specification, enclosed in parentheses – this identifier is stated in the PICS proforma specification and is updated whenever the PICS proforma is updated – it is recommended that this identifier should be relevant Specification number and year of publication, as is used in a Normative References clause, and this is the default for such identifiers;
- b) the number of the relevant table or, if the tables are not numbered, of the smallest subclause enclosing the relevant table;
- c) a solidus character, "/";
- d) the item number or mnemonic reference to the item, to identify the row in which the answer appears;
- e) if, and only if, more than one question occurs in the row identified by the item number or mnemonic reference, then each possible answer is implicitly labelled a, b, c, etc., from left to right, and this letter is appended to the sequence, prefixed by a solidus character ("/") if a mnemonic reference is used.

If mnemonic references are specified and each uniquely identify an item in the PICS proforma, then entries b) and c) in the above sequence may be omitted.

A.2.2.3 Status column

This column indicates the level of support required for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1, the given values are taken from the Session Protocol Specification (see ITU-T Rec. X.225 | ISO/IEC 8327-1).

A.2.2.3.1 Definitions applying to the tables in clauses A.4 to A.6

The values are as follows:

- 'm' Mandatory support is required. The implementation shall support the functionalities described in ITU-T Rec. X.225 | ISO/IEC 8327-1 for the specified item.
- 'o' Optional support is permitted for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1. According to some specific reason, the implementation is not obliged to support the specified item. If implemented, it shall conform to the specifications and restrictions contained in ITU-T Rec. X.225 | ISO/IEC 8327-1. Therefore the constraints described for the mandatory support above also apply.
- 'o.n' Selectable options among a set of items (where *n* is the number which identifies the group of optionals which are linked together). The implementation shall support at least one of the given items. [For the selected item(s), the constraints described for the mandatory support above also apply.]
- 'cn' The item is conditional (where *n* is the number which identifies the condition which is applicable). The definitions for the conditional statements used in Annex A are written under the table where they are used, and indexed in Annex B.
- 'n/a' The item is not applicable.

A.2.2.3.2 Definitions applying to the tables in clause A.7 (Supported SPDUs)

The values are as follows:

Sender item:

- 'm' Mandatory support is required. The implementation shall be able:
 - to build the SPDU (i.e. to build correctly the heading and all the mandatory parameters within the SPDU) in the situations required by the Protocol Machine; and
 - to encode the SPDU into the TSDU, according to a valid encoding format.
- 'o' Optional support is permitted for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1. According to some specific reason, the implementation is not obliged to be able to build the SPDU. If implemented, it shall conform to the specifications and restrictions contained in ITU-T Rec. X.225 | ISO/IEC 8327-1. Therefore the constraints described for the mandatory support above also apply.
- 'o.n' Selectable options among a set of items (where *n* is the number which identifies the group of optionals which are linked together). The implementation shall support at least one of the given items. [For the selected item(s), the constraints described for the mandatory support above also apply.]
- 'cn' The item is conditional (where *n* is the number which identifies the condition which is applicable). The definitions for the conditional statements used in Annex A are written under the table where they are used, and indexed in Annex B. Resolution of the condition (e.g. depending on protocol version, protocol mechanism, etc.) yields to 'm', 'o' or 'n/a'.
- 'n/a' The item is not applicable.

Receiver item:

- 'm' Mandatory support is required. The implementation shall be able:
 - to syntactically identify the SPDU [i.e. to decode the heading and all of the parameters which are present (Type and Length in TLV coding scheme)]; and
 - to process it correctly.
- 'o' Optional support is permitted for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1. If implemented, it shall conform to the specifications and restrictions contained in ITU-T Rec. X.225 | ISO/IEC 8327-1. Therefore the constraints described for the mandatory support above also apply.
- 'o.n' Selectable options among a set of items (where *n* is the number which identifies the group of optionals which are linked together). The implementation shall support at least one of the given items. [For the selected item(s), the constraints described for the mandatory support above also apply.]
- 'cn' The item is conditional (where *n* is the number which identifies the condition which is applicable). The definitions for the conditional statements used in Annex A are written under the table where they are used, and indexed in Annex B. Resolution of the condition (e.g. depending on protocol version, protocol mechanism, etc.) yields to 'm', 'o' or 'n/a'.
- 'n/a' The item is not applicable.

A.2.2.3.3 Definitions applying to the tables in clause A.8 (Supported SPDU parameters)

NOTE – The status indicated for the parameters reflects static conformance requirements. The details about the use of these parameters in specific instances of communications (i.e. dynamic conformance) are to be found in the Session protocol standard (ITU-T Rec. X.225 | ISO/IEC 8327-1). It is reminded that a parameter with the Length equal to zero shall be considered as absent.

The values are as follows:

Sender item:

- 'm' Mandatory support is required. The implementation shall be able to build and to encode this parameter within the appropriate SPDU.
- 'o' Optional support is permitted for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1. According to some specific reason, the implementation is not obliged to be able to build the parameter. If implemented, it shall conform to the specifications and restrictions contained in ITU-T Rec. X.225 | ISO/IEC 8327-1. Therefore the constraints described for the mandatory support above also apply.

- 'cn' The item is conditional (where *n* is the number which identifies the condition which is applicable). The definitions for the conditional statements used in Annex A are written under the table where they are used, and indexed in Annex B. Resolution of the condition (e.g. depending on protocol version, protocol mechanism, etc.) yields to 'm', 'o' or 'n/a'.
- 'n/a' The item is not applicable.

Receiver item:

- 'm' Mandatory support is required. The implementation shall be able to syntactically and semantically identify the SPDU parameter and to process it correctly.
- 'o' Optional support is permitted for conformance to ITU-T Rec. X.225 | ISO/IEC 8327-1. If implemented, it shall conform to the specifications and restrictions contained in ITU-T Rec. X.225 | ISO/IEC 8327-1. Therefore the constraints described for the mandatory support above also apply.
- 'cn' The item is conditional (where *n* is the number which identifies the condition which is applicable). The definitions for the conditional statements used in Annex A are written under the table where they are used, and indexed in Annex B. Resolution of the condition (e.g. depending on protocol version, protocol mechanism, etc.) yields to 'm', 'o' or 'n/a'.
- 'n/a' The item is not applicable.

A.2.2.4 Support column

The 'Support' column shall be completed by the supplier or implementor to indicate the level of implementation of each feature. The proforma has been designed such that the only entries required in the 'Support' column are:

If the Status column yields to 'm' or 'o', the following answers are valid:

- 'Y' Yes, the feature has been implemented.
- 'N' No, the feature has not been implemented.

If the Status column yields to 'n/a', the unique following answer is valid:

- '-' Not applicable.

A.2.2.5 Value column

The 'Value' column requires the specification of the range of values implemented for a feature, where relevant.

A.2.2.6 Mnemonic column

The 'Mnemonic' column is given to facilitate the interpretation of the conditional statements throughout the PICS proforma.

The mnemonics are designed so that the implementor should easily understand their contents. Their names are generated as follows:

- a) a character identifying the Session layer (S);
- b) an hyphen character;
- c) a sequence of character which is derived, where possible, from the abbreviations used in the Session protocol specification.

A full alphanumerical list of all the defined 'Mnemonics' is given in Annex C.

A.2.2.7 Length column

The 'Length' column is given for information only in A.8, in order to indicate a specific length requirement for a parameter. Otherwise, it is recommended not to fill in this column.

If values are given in the 'Support' columns (Sender and/or Receiver), they shall conform to the value(s) given in the 'Status' column.

The values are as follows:

- 'x' A specific number of octets is given in ITU-T Rec. X.225 | ISO/IEC 8327-1.
- '0-y' A range of number of octets is given in ITU-T Rec. X.225 | ISO/IEC 8327-1.
- 'see Ref.' For a specific reason (total length of the SPDU), an explicit range of number of octets can not be given in the PICS proforma. For more details, the implementor shall refer to ITU-T Rec. X.225 | ISO/IEC 8327-1.

A.2.3 Instructions for completion

The supplier shall complete all entries in the column marked 'Support'. In certain clauses of the PICS proforma further guidance for completion may be necessary. Such guidance shall supplement the guidance given in this clause and shall have a scope restricted to the clause in which it appears. In addition, other specifically identified information shall be provided by the implementor where requested. No changes shall be made to the proforma except the completion as required. Recognising that the level of detail required may, in some instances, exceed the space available for responses a number of responses specifically allow for the addition of appendices to the PICS.

A.3 Identification of the implementation

A.3.1 Date of statement

1	Date of statement? (yy-mm-dd)
---	-------------------------------

A.3.2 Implementation details

The supplier of the protocol implementation shall specify the information necessary to uniquely identify the implementation and the system in which it may reside. This may include details of:

- a) supplier, implementation name, operating system, suitable hardware;
- b) system supplier and/or client of the test laboratory that is to test the implementation;
- c) information on whom to contact if there are queries concerning the content of the PICS.

1	
---	--

A.4 Protocol Identification**A.4.1 ITU-T Rec. X.225 | ISO/IEC 8327-1 protocol details**

	Identification of Protocol Specification	Support	Comment
–	ITU-T Rec. X.225 (1994) ISO/IEC 8327-1:1996		
1			
2			
3			

A.4.2 ITU-T Rec. X.225 | ISO/IEC 8327-1 protocol versions

Which version of the Session Protocol is described in this PICS?

		Status	Support	Mnemonic	Comment
1	Version 1	o.1		S-V1	
2	Version 2	o.1			
o.1: the implementation of one, and only one, version of the protocol shall be described in this proforma (see below).					

An implementation shall be described by completing a separate PICS proforma for each supported protocol version. PICS document for all versions of the protocol for which conformance is claimed should be attached to each other, and used together.

Which other versions of the Session Protocol does the implementation support?

		Status	Support	Comment
3	Version 1	o		
4	Version 2	o		

A.4.3 ITU-T Rec. X.225 | ISO/IEC 8327-1 technical corrigenda implemented

Identification of corrigenda applied to the implementation	ITU-T Rec. X.225 (1994) ISO/IEC 8327-1:1996 Corr: Corr: Corr: Corr: Corr:
--	--

A.5 Global statement of conformance

1	Are all mandatory features implemented? (yes or no)
NOTE – If a positive response is not given to this box, then the implementation does not conform to ITU-T Rec. X.225 ISO/IEC 8327-1.	

A.6 Supported functional units and protocol mechanisms

A.6.1 Functional units

	Functional Unit	Status	Support	Mnemonic	Comment
1	Kernel	m			
2	Negotiated Release	o		S-FU(NR)	
3	Half Duplex	o.2		S-FU(HD)	
4	Duplex	o.2		S-FU(FD)	
5	Expedited Data (Note)	o		S-FU(EX)	
6	Typed Data	o		S-FU(TD)	
7	Capability Data Exchange	c1		S-FU(CD)	
8	Minor Synchronize	o		S-FU(SY)	
9	Symmetric Synchronize	o		S-FU(SS)	
10	Data Separation	c2		S-FU(DS)	
11	Major Synchronize	o		S-FU(MA)	
12	Resynchronize	o		S-FU(RESYN)	
13	Exceptions	c3		S-FU(EXCEP)	
14	Activity management	o		S-FU(ACT)	
o.2: at least one of the functional units Duplex and Half Duplex shall be implemented. c1: if [S-FU(ACT)] then o else n/a. c2: if [S-FU(SY) or S-FU(SS)] then o else n/a. c3: if [S-FU(HD)] then o else n/a. NOTE – The TRANSPORT Expedited data service is required to support the SESSION Expedited data functional unit.					

A.6.2 Protocol mechanisms

	Mechanism	Status	Support	Range of values	Mnemonic	Comment
1	Use of transport expedited data (Extended control Quality of Service)	c4		–	S-EXP_T	
2	Reuse of transport connection	o		–	S-REUSE_T	
3	Basic concatenation	m		–		
4	Extended concatenation (sending)	o		–		
5	Extended concatenation (receiving)	o		–	S-XCONC_RCV	
6	Segmenting (sending)	o			S-SEG_SDR	
7	Segmenting (receiving)	o			S-SEG_RCV	
8	Max size of SS-user-data (S-CONNECT) > 512	o			S-MAXSIZE_512	
9	Max size of SS-user-data (S-CONNECT) > 10 240	o			S-MAXSIZE_10240	
10	Max size of SS-user-data (S-ABORT) > 9	o			S-MAXSIZE_9	
c4: if [S-FU(EX)] then m else o. NOTES 1 The use of the TRANSPORT Expedited data service is mandatory in order to support the SESSION Expedited data functional unit, but is also related to the Extended Control of Quality of Service. 2 Two kinds of segmentation exist in the Session protocol. Lines 6 and 7 address the segmentation of SPDUs into several TSDUs. Lines 8, 9 and 10 address Session Version 2 (Unlimited User Data and Enclosure Item) with segmentation of an SSDU into several SPDUs.						

A.7 Supported SPDUs**A.7.1 Kernel functional unit****A.7.1.1 Supported roles****A.7.1.1.1 Session Connection**

Does the implementation support the Session Connection as:

	Role	Status	Support	Mnemonic	Comment
1	Initiator	o.3		S-CON_initiator	
2	Responder	o.3		S-CON_responder	
o.3: a conforming implementation shall support at least one of the above roles.					

A.7.1.1.2 Orderly Release

Does the implementation support the Orderly Release as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.4		S-REL_requestor	
2	Acceptor	o.4		S-REL_acceptor	
o.4: a conforming implementation shall support at least one of the above roles.					

A.7.1.1.3 Normal Data Transfer

Does the implementation support the Normal Data Transfer as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.5		S-DATA_requestor	
2	Acceptor	o.5		S-DATA_acceptor	
o.5: a conforming implementation shall support at least one of the above roles.					

A.7.1.2 Support for the SPDUs associated with the Kernel functional unit

	SPDU	Sender		Receiver		Mnemonics		Comment
		Status	Support	Status	Support	Sender	Receiver	
1	Connect (CN)	c5		c6				
2	Overflow Accept (OA)	c7		c8		S-OA_SDR	S-OA_RCV	
3	Connect Data Overflow (CDO)	c9		c10		S-CDO_SDR	S-CDO_RCV	
4	Accept (AC)	c6		c5				
5	Refuse (RF)	c6		c5				
6	Finish (FN)	c11		c12				
7	Disconnect (DN)	c12		c11				
8	Abort (AB)	m		m				
9	Abort Accept (AA)	o		m				
10	Data Transfer (DT)	c13		c14				
11	Prepare (PR)	c15		c15		S-PR_SDR	S-PR_RCV	
c5: if [S-CON_initiator] then m else n/a. c6: if [S-CON_responder] then m else n/a. c7: if [S-V1 or NOT S-CON_responder] then n/a else if [S-MAXSIZE_10 240] then m else o. c8: if [NOT S-V1 and S-CON_initiator and S-MAXSIZE_10 240] then m else n/a. c9: if [S-V1 or NOT S-CON_initiator] then n/a else if [S-MAXSIZE_10 240] then m else o. c10: if [NOT S-V1 and S-CON_responder and S-MAXSIZE_10 240] then m else n/a. c11: if [S-REL_requestor] then m else n/a. c12: if [S-REL_acceptor] then m else n/a. c13: if [S-DATA_requestor] then m else n/a. c14: if [S-DATA_acceptor] then m else n/a. c15: if [NOT S-V1 and S-MAXSIZE_9 and S-EXP_T] then m else n/a.								

A.7.1.3 Support for the SPDUs associated with Token Exchange

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Give Tokens (GT)	m		m		
2	Please Tokens (PT)	m		m		
NOTE – These two SPDUs are used for Token Exchange, but they are also used as category 0 SPDUs in basic concatenation. Therefore, their implementation is mandatory even if no token is supported. (Reference to ISO/IEC 8327-1, 7.16 and 7.17.)						

A.7.2 Negotiated Release functional unit**A.7.2.1 Supported roles**

The roles supported by the implementation for the Negotiated Release functional unit are the same as for the Orderly Release (see clause A.7.1.1.2).

A.7.2.2 Support for the SPDUs associated with the Negotiated Release functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Not Finished (NF)	c16		c17		
2	Give Tokens (GT)	----- (A.7.1.3) -----				
3	Please Tokens (PT)	----- (A.7.1.3) -----				
c16: if [S-FU(NR) and S-REL_acceptor] then m else n/a. c17: if [S-FU(NR) and S-REL_requestor] then m else n/a.						

A.7.3 Half Duplex functional unit**A.7.3.1 Supported roles**

Does the implementation support the Half Duplex functional unit as:

	Role	Status	Support	Comment
1	Requestor	c18		
2	Acceptor	c18		
c18: if [S-FU(HD)] then m else n/a.				

A.7.3.2 Support for the SPDUs associated with the Half Duplex functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Give Tokens (GT)	----- (A.7.1.3) -----				
2	Please Tokens (PT)	----- (A.7.1.3) -----				

A.7.4 Duplex functional unit

No additional SPDUs (*this clause is present for completeness*).

A.7.5 Expedited Data functional unit**A.7.5.1 Supported roles**

Does the implementation support the Expedited Data functional unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.6		S-XDATA_requestor	
2	Acceptor	o.6		S-XDATA_acceptor	
o.6: if [S-FU(EX)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.5.2 Support for the SPDU associated with the Expedited Data functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Expedited Data (EX)	c19		c20		
c19: if [S-XDATA_requestor] then m else n/a. c20: if [S-XDATA_acceptor] then m else n/a.						

A.7.6 Typed Data functional unit**A.7.6.1 Supported roles**

Does the implementation support the Typed Data functional unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.7		S-TDATA_requestor	
2	Acceptor	o.7		S-TDATA_acceptor	
o.7: if [S-FU(TD)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.6.2 Support for the SPDU associated with the Typed Data functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Typed Data (TD)	c21		c22		
c21: if [S-TDATA_requestor] then m else n/a. c22: if [S-TDATA_acceptor] then m else n/a.						

A.7.7 Capability Data functional unit**A.7.7.1 Supported roles**

Does the implementation support the Capability Data functional unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.8		S-CAP_requestor	
2	Acceptor	o.8		S-CAP_acceptor	
o.8: if [S-FU(CD)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.7.2 Support for the SPDUs associated with the Capability Data functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Capability Data (CD)	c23		c24		
2	Capability Data Ack (CDA)	c24		c23		
c23: if [S-CAP_requestor] then m else n/a. c24: if [S-CAP_acceptor] then m else n/a.						

A.7.8 Minor synchronize functional unit**A.7.8.1 Supported roles**

Does the implementation support the Minor synchronize functional unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.9		S-MIN_requestor	
2	Acceptor	o.9		S-MIN_acceptor	
o.9: if [S-FU(SY)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.8.2 Support for the SPDUs associated with the Minor synchronize functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Minor Sync Point (MIP)	c25		c26		
2	Minor Sync Ack (MIA)	c27		c25		
3	Give Tokens (GT)	------(A.7.1.3)-----				
4	Please Tokens (PT)	------(A.7.1.3)-----				
c25: if [S-MIN_requestor] then m else n/a. c26: if [S-MIN_acceptor] then m else n/a. c27: if [S-MIN_acceptor] then o else n/a.						

A.7.9 Symmetric synchronize functional unit**A.7.9.1 Supported roles**

Does the implementation support the Symmetric synchronize functional unit as:

	Role	Status	Support	Comment
1	Requestor	c28		
2	Acceptor	c28		
c28: if [S-FU(SS)] then m else n/a.				

A.7.9.2 Support for the SPDUs associated with the Symmetric synchronize functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Minor Sync Point (MIP)	c28		c28		
2	Minor Sync Ack (MIA)	c29		c28		
c28: if [S-FU(SS)] then m else n/a. c29: if [S-FU(SS)] then o else n/a.						

A.7.10 Data separation functional unit

No additional SPDUs (*this clause is present for completeness*).

A.7.11 Major synchronize functional unit**A.7.11.1 Supported roles**

Does the implementation support the Major synchronize functional unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.10		S-MAJ_requestor	
2	Acceptor	o.10		S-MAJ_acceptor	
o.10: if [S-FU(MA)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.11.2 Support for the SPDUs associated with the Major synchronize functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Major Sync Point (MAP)	c30		c31		
2	Major Sync Ack (MAA)	c31		c30		
3	Give Tokens (GT)	----- (A.7.1.3) -----				
4	Please Tokens (PT)	----- (A.7.1.3) -----				
5	Prepare (PR)	c32		c33		
c30: if [S-MAJ_requestor] then m else n/a. c31: if [S-MAJ_acceptor] then m else n/a. c32: if [S-MAJ_acceptor and S-EXP_T] then m else n/a. c33: if [S-MAJ_requestor and S-EXP_T] then m else n/a.						

A.7.12 Resynchronize functional unit**A.7.12.1 Supported roles**

Does the implementation support the Resynchronize functional unit as:

	Role	Status	Support	Comment
1	Requestor	c34		
2	Acceptor	c34		
c34: if [S-FU(RESYN)] then m else n/a. NOTE – The Resynchronize functional unit provides an emergency service. Therefore, if the functional unit is supported, a conforming implementation shall support both roles (requestor and acceptor).				

A.7.12.2 Supported resynchronize types

Does the implementation support the following Resynchronize types:

	Type	Status	Support	Comment
1	Abandon	o.11		
2	Set	o.11		
3	Restart	o.11		
o.11: if [S-FU(RESYN)] then a conforming implementation shall support at least one of the above roles else n/a.				

A.7.12.3 Support for the SPDUs associated with the Resynchronize functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Resynchronize (RS)	c34		c34		
2	Resynchronize Ack (RA)	c34		c34		
3	Prepare (PR)	c35		c35		
c34: if [S-FU(RESYN)] then m else n/a. c35: if [S-FU(RESYN) and S-EXP_T] then m else n/a.						

A.7.13 Exceptions functional unit**A.7.13.1 Supported roles**

Does the implementation support the Exceptions functional unit as:

	Role	Status	Support	Comment
1	Requestor	c36		
2	Acceptor	c36		
c36: if [S-FU(EXCEP)] then m else n/a. NOTE – The Exceptions functional unit provides an emergency service. Therefore, if the functional unit is supported, a conforming implementation shall support both roles (requestor and acceptor).				

A.7.13.2 Support for the SPDUs associated with the Exceptions functional unit

	SPDU	Sender		Receiver		Mnemonic	Comment
		Status	Support	Status	Support	(Sender side only)	
1	Exception Report (ER)	c37		c36		S-ER_SDR	
2	Exception Data (ED)	c36		c36			
c36: if [S-FU(EXCEP)] then m else n/a. c37: if [S-FU(EXCEP)] then o else n/a.							

A.7.14 Activity management functional unit**A.7.14.1 Supported roles****A.7.14.1.1 Activity start**

Does the implementation support the Activity start as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.12		S-ACTS_requestor	
2	Acceptor	o.12		S-ACTS_acceptor	
o.12: if [S-FU(ACT)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.14.1.2 Activity resume

Does the implementation support the Activity resume as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.13		S-ACTR_requestor	
2	Acceptor	o.13		S-ACTR_acceptor	
o.13: if [S-FU(ACT)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.14.1.3 Activity interrupt

Does the implementation support the Activity interrupt as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.14		S-ACTI_requestor	
2	Acceptor	o.14		S-ACTI_acceptor	
o.14: if [S-FU(ACT)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.14.1.4 Activity discard

Does the implementation support the Activity discard unit as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.15		S-ACTD_requestor	
2	Acceptor	o.15		S-ACTD_acceptor	
o.15: if [S-FU(ACT)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.14.1.5 Activity end

Does the implementation support the Activity end as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	o.16		S-ACTE_requestor	
2	Acceptor	o.16		S-ACTE_acceptor	
o.16: if [S-FU(ACT)] then a conforming implementation shall support at least one of the above roles else n/a.					

A.7.14.1.6 Give Tokens Confirm

Does the implementation support the Give Tokens Confirm as:

	Role	Status	Support	Mnemonic	Comment
1	Requestor	c1		S-GTC_requestor	
2	Acceptor	c1		S-GTC_acceptor	
c1: if [S-FU(ACT)] then o else n/a.					

A.7.14.2 Support for the SPDUs associated with the Activity management functional unit

	SPDU	Sender		Receiver		Comment
		Status	Support	Status	Support	
1	Activity Start (AS)	c38		c39		
2	Activity Resume (AR)	c40		c41		
3	Activity Interrupt (AI)	c42		c43		
4	Activity Interrupt Ack (AIA)	c43		c42		
5	Activity Discard (AD)	c44		c45		
6	Activity Discard Ack (ADA)	c45		c44		
7	Activity End (AE)	c46		c47		
8	Activity End Ack (AEA)	c47		c46		
9	Prepare (PR)	c48		c48		
10	Give Tokens (GT)	----- (A.7.1.3) -----				
11	Please Tokens (PT)	----- (A.7.1.3) -----				
12	Give Tokens Confirm (GTC)	c49		c50		
13	Give Tokens Ack (GTA)	c50		c49		
c38: if [S-ACTS_requestor] then m else n/a. c39: if [S-ACTS_acceptor] then m else n/a. c40: if [S-ACTR_requestor] then m else n/a. c41: if [S-ACTR_acceptor] then m else n/a. c42: if [S-ACTI_requestor] then m else n/a. c43: if [S-ACTI_acceptor] then m else n/a. c44: if [S-ACTD_requestor] then m else n/a. c45: if [S-ACTD_acceptor] then m else n/a. c46: if [S-ACTE_requestor] then m else n/a. c47: if [S-ACTE_acceptor] then m else n/a. c48: if [S-FU(ACT) and S-EXP_T] then m else n/a. c49: if [S-GTC_requestor] then m else n/a. c50: if [S-GTC_acceptor] then m else n/a.						

A.8 Supported SPDU-parameters**A.8.1 Connect (CN) SPDU**

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.1, Table 11)

A.8.1.1 Connection Identifier

	PGI "Connection Identifier"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Calling SS-user Reference	c51		c6		0-64			
2	Common Reference	c51		c6		0-64			
3	Additional Reference Information	c51		c6		0-4			
c6: if [S-CON_responder] then m else n/a. c51: if [S-CON_initiator] then o else n/a.									

A.8.1.2 Connect/Accept Item**A.8.1.2.1 Connect/Accept Item parameters**

NOTE – If presence of the PGI "Connect/accept Item" is supported (see A.8.1.2.2) then presence of Protocol Options and Version Number parameters shall be supported.

	PGI "Connect/Accept Item"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Protocol Options	c52		c53		1			
2	TSDU maximum size	c54		c55		4			
3	Version Number	c56		c57		1			
4	Initial Serial Number	c58		c59		0-6			
5	Token Setting Item	c51		c60		1			
6	Second Initial Serial Number	c61		c62		0-6			
c51: if [S-CON_initiator] then o else n/a. c52: if [NOT S-CON_initiator] then n/a else if [S-XCONC_RCV] then m else o. c53: if [NOT S-CON_responder] then n/a else if [S-XCONC_RCV] then m else o. c54: if [NOT S-CON_initiator] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c55: if [NOT S-CON_responder] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c56: if [NOT S-CON_initiator] then n/a else if [NOT S-V1] then m else o. c57: if [NOT S-CON_responder] then n/a else if [NOT S-V1] then m else o. c58: if [NOT S-CON_initiator] then n/a else if [{S-FU(SY) or S-FU(MA) or S-FU(SS) or S-FU(RESYN)} and NOT S-FU(ACT)] then m else o. c59: if [NOT S-CON_responder] then n/a else if [{S-FU(SY) or S-FU(MA) or S-FU(SS) or S-FU(RESYN)} and NOT S-FU(ACT)] then m else o. c60: if [S-CON_responder] then o else n/a. c61: if [NOT S-CON_initiator] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o. c62: if [NOT S-CON_responder] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o.									

A.8.1.2.2 Presence of Connect/Accept Item

		Status	Support	Comment
1	Sender	c63		
2	Receiver	c6		
c6: if [S-CON_responder] then m else n/a. c63: if [NOT S-CON_initiator] then n/a else if [A.8.1.2.1/1a or A.8.1.2.1/2a or A.8.1.2.1/3a or A.8.1.2.1/4a or A.8.1.2.1/5a or A.8.1.2.1/6a] then m else o.				

A.8.1.3 Single Items

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Session User Requirements	c64		c65		2			
2	Calling Session Selector	c51		c6		0-16			
3	Called Session Selector	c5		c6		0-16			
4	Data Overflow	c9		c7		1			
5	User Data	c5		c6		0-512			
6	Extended User Data	c66		c67		0-10240			
7	Upper Limit Serial Number	c51		c60					
8	Large Initial Serial Number	c68		c69					
c5: if [S-CON_initiator] then m else n/a. c6: if [S-CON_responder] then m else n/a. c7: if [S-V1 or NOT S-CON_responder] then n/a else if [S-MAXSIZE_10 240] then m else o. c9: if [S-V1 or NOT S-CON_initiator] then n/a else if [S-MAXSIZE_10 240] then m else o. c51: if [S-CON_initiator] then o else n/a. c64: if [NOT S-CON_initiator] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c65: if [NOT S-CON_responder] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c66: if [NOT S-V1 and S-CON_initiator and S-MAXSIZE_512] then m else n/a. c67: if [NOT S-V1 and S-CON_responder and S-MAXSIZE_512] then m else n/a. c68: if [A.8.1.3/7a] then o else n/a. c69: if [A.8.1.3/7b] then o else n/a.									

A.8.2 Overflow Accept (OA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.2, Table 12)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	TSDU Maximum Size	c70		c71		4			
2	Version Number	c72		c73		1			
c70: if [NOT S-OA_SDR] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c71: if [NOT S-OA_RCV] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c72: if [S-OA_SDR] then m else n/a. c73: if [S-OA_RCV] then m else n/a.									

A.8.3 Connect Data Overflow (CDO) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.3, Table 13)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c74		c75		1			
2	User Data	c74		c75		0-65528			
c74: if [S-CDO_SDR] then m else n/a. c75: if [S-CDO_RCV] then m else n/a.									

A.8.4 Accept (AC) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.4, Table 14)

A.8.4.1 Connection Identifier

	PGI "Connection Identifier"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Called SS-user Reference	c60		c5		0-64			
2	Common Reference	c60		c5		0-64			
3	Additional Reference Information	c60		c5		0-4			
c5: if [S-CON_initiator] then m else n/a. c60: if [S-CON_responder] then o else n/a.									

A.8.4.2 Connect/Accept Item**A.8.4.2.1 Connect/Accept Item parameters**

NOTE – If presence of the PGI "Connect/accept Item" is supported (see A.8.4.2.2) then presence of Protocol Options and Version Number parameters shall be supported.

	PGI "Connect/Accept Item"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Protocol Options	c53		c52		1			
2	TSDU maximum size	c55		c54		4			
3	Version Number	c57		c56		1			
4	Initial Serial Number	c59		c58		0-6			
5	Token Setting Item	c60		c51		1			
6	Second Initial Serial Number	c62		c61		0-6			
c51: if [S-CON_initiator] then o else n/a. c52: if [NOT S-CON_initiator] then n/a else if [S-XCONC_RCV] then m else o. c53: if [NOT S-CON_responder] then n/a else if [S-XCONC_RCV] then m else o. c54: if [NOT S-CON_initiator] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c55: if [NOT S-CON_responder] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o. c56: if [NOT S-CON_initiator] then n/a else if [NOT S-V1] then m else o. c57: if [NOT S-CON_responder] then n/a else if [NOT S-V1] then m else o. c58: if [NOT S-CON_initiator] then n/a else if [{S-FU(SY) or s-FU(MA) or S-FU(SS) or S-FU(RESYN)} and NOT S-FU(ACT)] then m else o. c59: if [NOT S-CON_responder] then n/a else if [{S-FU(SY) or s-FU(MA) or S-FU(SS) or S-FU(RESYN)} and NOT S-FU(ACT)] then m else o. c60: if [S-CON_responder] then o else n/a. c61: if [NOT S-CON_initiator] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o. c62: if [NOT S-CON_responder] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o.									

A.8.4.2.2 Presence of Connect/Accept Item

	Status	Support	Comment
1 Sender	c76		
2 Receiver	c5		
c5: if [S-CON_initiator] then m else n/a. c76: if [NOT S-CON_responder] then n/a else if [A.8.4.2.1/1a or A.8.4.2.1/2a or A.8.4.2.1/3a or A.8.4.2.1/4a or A.8.4.2.1/5a or A.8.4.2.1/6a] then m else o.			

A.8.4.3 Single Items

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Token Item	c60		c5		1			
2	Session User Requirements	c65		c64		2			
3	Enclosure Item	c77		c78		1			
4	Calling Session Selector	c6		c51		0-16			
5	Responding Session Selector	c60		c5		0-16			
6	User Data	c6		c5		(Ref.)			
7	Upper Limit Serial Number	c60		c51					
8	Large Initial Serial Number	c79		c80					
c5: if [S-CON_initiator] then m else n/a. c6: if [S-CON_responder] then m else n/a. c51: if [S-CON_initiator] then o else n/a. c60: if [S-CON_responder] then o else n/a. c64: if [NOT S-CON_initiator] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c65: if [NOT S-CON_responder] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c77: if [S-CON_responder and NOT S-V1] then m else n/a. c78: if [S-CON_initiator and NOT S-V1] then m else n/a. c79: if [A.8.4.3/7a] then o else n/a. c80: if [A.8.4.3/7b] then o else n/a.									

A.8.5 Refuse (RF) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.5, Table 15)

A.8.5.1 Connection Identifier

	PGI "Connection Identifier"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Called SS-user Reference	c60		c5		0-64			
2	Common Reference	c60		c5		0-64			
3	Additional Reference Information	c60		c5		0-4			
c5: if [S-CON_initiator] then m else n/a. c60: if [S-CON_responder] then o else n/a.									

A.8.5.2 Single Items

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Transport Disconnect	c81		c82		1			
2	Session User Requirements	c65		c64		2			
3	Version Number	c57		c56		1			
4	Enclosure Item	c77		c78		1			
5	Reason Code	c6		c5		(Ref.)			
c5: if [S-CON_initiator] then m else n/a. c6: if [S-CON_responder] then m else n/a. c56: if [NOT S-CON_initiator] then n/a else if [NOT S-V1] then m else o. c57: if [NOT S-CON_responder] then n/a else if [NOT S-V1] then m else o. c64: if [NOT S-CON_initiator] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c65: if [NOT S-CON_responder] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m. c77: if [S-CON_responder and NOT S-V1] then m else n/a. c78: if [S-CON_initiator and NOT S-V1] then m else n/a. c81: if [NOT S-CON_responder] then n/a else if [S-REUSE_T] then m else o. c82: if [NOT S-CON_initiator] then n/a else if [S-REUSE_T] then m else o.									

A.8.6 Finish (FN) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.6, Table 16)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Transport Disconnect	c83		c84		1			
2	Enclosure Item	c85		c86		1			
3	User Data	c87		c12		(Ref.)			
c12: if [S-REL_acceptor] then m else n/a. c83: if [NOT S-REL_requestor] then n/a else if [S-REUSE_T] then m else o. c84: if [NOT S-REL_acceptor] then n/a else if [S-REUSE_T] then m else o. c85: if [S-REL_requestor and NOT S-V1] then m else n/a. c86: if [S-REL_acceptor and NOT S-V1] then m else n/a. c87: if [S-REL_requestor] then o else n/a.									

A.8.7 Disconnect (DN) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.7, Table 17)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c86		c85		1			
2	User Data	c88		c11		(Ref.)			
c11: if [S-REL_requestor] then m else n/a. c85: if [S-REL_requestor and NOT S-V1] then m else n/a. c86: if [S-REL_acceptor and NOT S-V1] then m else n/a. c88: if [S-REL_acceptor] then o else n/a.									

A.8.8 Not Finish (NF) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.8, Table 18)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c89		c90		1			
2	User Data	c91		c17		(Ref.)			
c17: if [S-FU(NR) and S-REL_requestor] then m else n/a. c89: if [S-FU(NR) and S-REL_acceptor and NOT S-V1] then m else n/a. c90: if [S-FU(NR) and S-REL_requestor and NOT S-V1] then m else n/a. c91: if [S-FU(NR) and S-REL_acceptor] then o else n/a.									

A.8.9 Abort (AB) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.9, Table 19)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Transport Disconnect	m		m		1			
2	Enclosure Item	c92		c92		1			
3	Reflect Parameter Values	o		o		0-9			
4	User Data	o		m		(Ref.)			
c92: if [NOT S-V1] then m else n/a.									

A.8.10 Abort Accept (AA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.10)

No parameter field.

A.8.11 Data Transfer (DT) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.11, Table 20)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c93		c94		1			
2	User Information Field	c13		c14		Unlimited			
c13: if [S-DATA_requestor] then m else n/a. c14: if [S-DATA_acceptor] then m else n/a. c93: if [S-DATA_requestor and S-SEG_SDR] then m else n/a. c94: if [S-DATA_acceptor and S-SEG_RCV] then m else n/a.									

A.8.12 Expedited Data (EX) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.12, Table 21)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	User Information Field	c19		c20		0-14			
c19: if [S-XDATA_requestor] then m else n/a. c20: if [S-XDATA_acceptor] then m else n/a.									

A.8.13 Typed Data (TD) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.13, Table 22)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c95		c96		1			
2	User Information Field	c21		c22		Unlimited			
c21: if [S-TDATA_requestor] then m else n/a. c22: if [S-TDATA_acceptor] then m else n/a. c95: if [S-TDATA_requestor and S-SEG_SDR] then m else n/a. c96: if [S-TDATA_acceptor and S-SEG_RCV] then m else n/a.									

A.8.14 Capability Data (CD) SPDU

(Ref. ITU-T Rec.X.225 | ISO/IEC 8327-1, subclause 8.3.14, Table 23)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c97		c98		1			
2	User Data	c99		c24		(Ref.)			
c24: if [S-CAP_acceptor] then m else n/a. c97: if [S-CAP_requestor and NOT S-V1] then m else n/a. c98: if [S-CAP_acceptor and NOT S-V1] then m else n/a. c99: if [S-CAP_requestor] then o else n/a.									

A.8.15 Capability Data Ack (CDA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.15, Table 24)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c98		c97		1			
2	User Data	c100		c23		(Ref.)			
c23: if [S-CAP_requestor] then m else n/a. c97: if [S-CAP_requestor and NOT S-V1] then m else n/a. c98: if [S-CAP_acceptor and NOT S-V1] then m else n/a. c100: if [S-CAP_acceptor] then o else n/a.									

A.8.16 Give Tokens (GT) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.16, Table 25)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Token Item	c101		c102		1			
2	Enclosure Item	c92		c92		1			
3	User Data	c103		c92		(Ref.)			
c92: if [NOT S-V1] then m else n/a. c101: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then o else n/a. c102: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then m else n/a. c103: if [NOT S-V1 and A.8.16/1a] then o else n/a.									

A.8.17 Please Tokens (PT) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.17, Table 26)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Token Item	c101		c102		1			
2	Enclosure Item	c92		c92		1			
3	User Data	c104		c105		(Ref.)			
c92: if [NOT S-V1] then m else n/a. c101: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then o else n/a. c102: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then m else n/a. c104: if [A.8.17/1a] then o else n/a. c105: if [A.8.17/1b] then m else n/a.									

A.8.18 Minor Sync Point (MIP) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.20, Table 28)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Sync Type Item	c106		c107		1			
2	Enclosure Item	c108		c109		1			
3	Serial Number	c110		c111		0-6			
4	User Data	c112		c111		(Ref.)			
c106: if [(S-MIN_requestor or S-FU(SS)) and S-FU(DS)] then m else if [(S-MIN_requestor or S-FU(SS)) and NOT S-FU(DS)] then o else n/a. c107: if [S-MIN_acceptor or S-FU(SS)] then o else n/a. c108: if [{S-MIN_requestor and NOT S-V1} or {S-FU(SS) and NOT S-V1}] then m else n/a. c109: if [{S-MIN_acceptor and NOT S-V1} or {S-FU(SS) and NOT S-V1}] then m else n/a. c110: if [S-MIN_requestor or S-FU(SS)] then m else n/a. c111: if [S-MIN_acceptor or S-FU(SS)] then m else n/a. c112: if [S-MIN_requestor or S-FU(SS)] then o else n/a.									

A.8.19 Minor Sync Ack (MIA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.21, Table 29)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c109		c108		1			
2	Serial Number	c111		c110		0-6			
3	User Data	c107		c110		(Ref.)			
c107: if [S-MIN_acceptor or S-FU(SS)] then o else n/a. c108: if [{S-MIN_requestor and NOT S-V1} or {S-FU(SS) and NOT S-V1}] then m else n/a. c109: if [{S-MIN_acceptor and NOT S-V1} or {S-FU(SS) and NOT S-V1}] then m else n/a. c110: if [S-MIN_requestor or S-FU(SS)] then m else n/a. c111: if [S-MIN_acceptor or S-FU(SS)] then m else n/a.									

A.8.20 Major Sync Point (MAP) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.22, Table 30)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Sync Type Item	c30		c31		1			
2	Enclosure Item	c113		c114		1			
3	Serial Number	c30		c31		0-6			
4	User Data	c115		c31		(Ref.)			
c30: if [S-MAJ_requestor] then m else n/a. c31: if [S-MAJ_acceptor] then m else n/a. c113: if [S-MAJ_requestor and NOT S-V1] then m else n/a. c114: if [S-MAJ_acceptor and NOT S-V1] then m else n/a. c115: if [S-MAJ_requestor] then o else n/a.									

A.8.21 Major Sync Ack (MAA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.23, Table 31)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c114		c113		1			
2	Serial Number	c116		c117		0-6			
3	Second Serial Number	c118		c119		0-6			
4	User Data	c120		c30		(Ref.)			
c30: if [S-MAJ_requestor] then m else n/a. c113: if [S-MAJ_requestor and NOT S-V1] then m else n/a. c114: if [S-MAJ_acceptor and NOT S-V1] then m else n/a. c116: if [NOT S-MAJ_acceptor] then n/a else if [NOT S-FU(SS)] then m else o. c117: if [NOT S-MAJ_requestor] then n/a else if [NOT S-FU(SS)] then m else o. c118: if [NOT S-MAJ_acceptor] then n/a else if [S-FU(SS)] then m else o. c119: if [NOT S-MAJ_requestor] then n/a else if [S-FU(SS)] then m else o. c120: if [S-MAJ_acceptor] then o else n/a.									

A.8.22 Resynchronize (RS) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.24, Table 32)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c121		c121		1			
2	Token Setting Item	c102		c102		1			
3	Resync Type	c122		c122		1			
4	Serial Number	c122		c122		0-6			
5	Second Resync Type	c123		c124		1			
6	Second Serial Number	c123		c124		0-6			
7	User Data	c125		c34		(Ref.)			
c34: if [S-FU(RESYN)] then m else n/a. c102: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then m else n/a. c121: if [S-FU(RESYN) and NOT S-V1] then m else n/a. c122: if [NOT S-FU(RESYN)] then n/a else if [S-FU(SY) or S-FU(MA)] then m else o. c123: if [S-FU(RESYN) and S-FU(SS)] then o else n/a. c124: if [S-FU(RESYN) and S-FU(SS)] then m else n/a. c125: if [S-FU(RESYN)] then o else n/a.									

A.8.23 Resynchronize Ack (RA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.25, Table 33)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c121		c121		1			
2	Token Setting Item	c102		c102		1			
3	Resync Type	c123		c124		1			
4	Serial Number	c126		c34		0-6			
5	Second Resync Type	c123		c124		1			
6	Second Serial Number	c123		c124		0-6			
7	User Data	c125		c34		(Ref.)			
c34: if [S-FU(RESYN)] then m else n/a. c102: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then m else n/a. c121: if [S-FU(RESYN) and NOT S-V1] then m else n/a. c123: if [S-FU(RESYN) and S-FU(SS)] then o else n/a. c124: if [S-FU(RESYN) and S-FU(SS)] then m else n/a. c125: if [S-FU(RESYN)] then o else n/a. c126: if [NOT S-FU(RESYN)] then n/a else if [NOT S-FU(SS)] then m else o.									

A.8.24 Prepare (PR) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.26, Table 34)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Prepare Type	c127		c128		1			
2	Resync Type	c129		c129		1			
3	Second Resync Type	c129		c129		1			
c127: if [{S-MAJ_acceptor and S-EXP_T} or {S-FU(RESYN) and S-EXP_T} or {S-FU(ACT) and S-EXP_T} or {S-PR_SDR}] then m else n/a. c128: if [{S-MAJ_requestor and S-EXP_T} or {S-FU(RESYN) and S-EXP_T} or {S-FU(ACT) and S-EXP_T} or {S-PR_RCV}] then m else n/a. c129: if [S-FU(SS) and S-EXP_T] then m else n/a.									

A.8.25 Exception Report (ER) SPDU

(Ref. ITU-T X.225 | ISO/IEC 8327-1, subclause 8.3.27, Table 35)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Reflect Parameter Values	c130		c36		0-65531			
c36: if [S-FU(EXCEP)] then m else n/a. c130: if [S-ER_SDR] then m else n/a.									

A.8.26 Exception Data (ED) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.28, Table 36)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c131		c131		1			
2	Reason Code	c36		c36		1			
3	User Data	c132		c36		(Ref.)			
c36: if [S-FU(EXCEP)] then m else n/a. c131: if [S-FU(EXCEP) and NOT S-V1] then m else n/a. c132: if [S-FU(EXCEP)] then o else n/a.									

A.8.27 Give Tokens Confirm (GTC) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.18, Table 27)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c133		c134		1			
2	User Data	c135		c134		(Ref.)			
c133: if [S-GTC_requestor and NOT S-V1] then m else n/a. c134: if [S-GTC_acceptor and NOT S-V1] then m else n/a. c135: if [S-GTC_requestor and NOT S-V1] then o else n/a.									

A.8.28 Give Tokens Ack (GTA) SPDU

No parameter field.

A.8.29 Activity Start (AS) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.29, Table 37)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c136		c136		1			
2	Activity Identifier	c38		c39		0-6			
3	User Data	c137		c39		(Ref.)			
c38: if [S-ACTS_requestor] then m else n/a. c39: if [S-ACTS_acceptor] then m else n/a. c136: if [S-ACTS_acceptor and NOT S-V1] then m else n/a. c137: if [S-ACTS_requestor] then o else n/a.									

A.8.30 Activity Resume (AR) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.30, Table 38)

A.8.30.1 Linking Information

	PGI "Linking Information"	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Called SS-user Reference	c138		c41		0-64			
2	Calling SS-user Reference	c138		c41		0-64			
3	Common Reference	c138		c41		0-64			
4	Additional Reference Information	c138		c41		0-4			
5	Old Activity Identifier	c40		c41		0-6			
6	Serial Number	c40		c41		0-6			
7	Second Serial Number	c139		c140		0-6			
c40: if [S-ACTR_requestor] then m else n/a. c41: if [S-ACTR_acceptor] then m else n/a. c138: if [S-ACTR_requestor] then o else n/a. c139: if [S-ACTR_requestor and S-FU(SS)] then m else n/a. c140: if [S-ACTR_acceptor and S-FU(SS)] then m else n/a.									

A.8.30.2 Single Items

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c141		c142		1			
2	New Activity Identifier	c40		c41		0-6			
3	User Data	c138		c41		(Ref.)			
c40: if [S-ACTR_requestor] then m else n/a. c41: if [S-ACTR_acceptor] then m else n/a. c138: if [S-ACTR_requestor] then o else n/a. c141: if [S-ACTR_requestor and NOT S-V1] then m else n/a. c142: if [S-ACTR_acceptor and NOT S-V1] then m else n/a.									

A.8.31 Activity Interrupt (AI) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.31, Table 39)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c143		c144		1			
2	Reason Code	c42		c43		1			
3	User Data	c145		c144		(Ref.)			
c42: if [S-ACTI_requestor] then m else n/a. c43: if [S-ACTI_acceptor] then m else n/a. c143: if [S-ACTI_requestor and NOT S-V1] then m else n/a. c144: if [S-ACTI_acceptor and NOT S-V1] then m else n/a. c145: if [S-ACTI_requestor and NOT S-V1] then o else n/a.									

A.8.32 Activity Interrupt Ack (AIA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.32, Table 40)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c144		c143		1			
2	User Data	c146		c143		(Ref.)			
c143: if [S-ACTI_requestor and NOT S-V1] then m else n/a. c144: if [S-ACTI_acceptor and NOT S-V1] then m else n/a. c146: if [S-ACTI_acceptor and NOT S-V1] then o else n/a.									

A.8.33 Activity Discard (AD) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.33, Table 41)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c147		c148		1			
2	Reason Code	c44		c45		1			
3	User Data	c149		c148		(Ref.)			
c44: if [S-ACTD_requestor] then m else n/a. c45: if [S-ACTD_acceptor] then m else n/a. c147: if [S-ACTD_requestor and NOT S-V1] then m else n/a. c148: if [S-ACTD_acceptor and NOT S-V1] then m else n/a. c149: if [S-ACTD_requestor and NOT S-V1] then o else n/a.									

A.8.34 Activity Discard Ack (ADA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.34, Table 42)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c148		c147		1			
2	User Data	c150		c147		(Ref.)			
c147: if [S-ACTD_requestor and NOT S-V1] then m else n/a. c148: if [S-ACTD_acceptor and NOT S-V1] then m else n/a. c150: if [S-ACTD_acceptor and NOT S-V1] then o else n/a.									

A.8.35 Activity End (AE) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.35, Table 43)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c151		c152		1			
2	Serial Number	c46		c47		0-6			
3	User Data	c153		c47		(Ref.)			
c46: if [S-ACTE_requestor] then m else n/a. c47: if [S-ACTE_acceptor] then m else n/a. c151: if [S-ACTE_requestor and NOT S-V1] then m else n/a. c152: if [S-ACTE_acceptor and NOT S-V1] then m else n/a. c153: if [S-ACTE_requestor] then o else n/a.									

A.8.36 Activity End Ack (AEA) SPDU

(Ref. ITU-T Rec. X.225 | ISO/IEC 8327-1, subclause 8.3.36, Table 31)

	Single Items	Sender		Receiver		Length			Comment
		Status	Support	Status	Support	Status	Spt/Sdr	Spt/Rcv	
1	Enclosure Item	c152		c151		1			
2	Serial Number	c154		c155		0-6			
3	Second Serial Number	c156		c157		0-6			
4	User Data	c158		c46		(Ref.)			
c46: if [S-ACTE_requestor] then m else n/a. c151: if [S-ACTE_requestor and NOT S-V1] then m else n/a. c152: if [S-ACTE_acceptor and NOT S-V1] then m else n/a. c154: if [NOT S-ACTE_acceptor] then n/a else if [NOT S-FU(SS)] then m else o. c155: if [NOT S-ACTE_requestor] then n/a else if [NOT S-FU(SS)] then m else o. c156: if [NOT S-ACTE_acceptor] then n/a else if [S-FU(SS)] then m else o. c157: if [NOT S-ACTE_requestor] then n/a else if [S-FU(SS)] then m else o. c158: if [S-ACTE_acceptor] then o else n/a.									

– END OF PICS PROFORMA –

(laisser en blanc)

Annexe B

Liste des déclarations conditionnelles

(Cette annexe ne fait pas partie intégrante de la présente Recommandation | Norme internationale)

- c1: if [S-FU(ACT)] then o else n/a.
- c2: if [S-FU(SY) or S-FU(SS)] then o else n/a.
- c3: if [S-FU(HD)] then o else n/a.
- c4: if [S-FU(EX)] then m else o.
- c5: if [S-CON_initiator] then m else n/a.
- c6: if [S-CON_responder] then m else n/a.
- c7: if [S-V1 or NOT S-CON_responder] then n/a else if [S-MAXSIZE_10240] then m else o.
- c8: if [NOT S-V1 and S-CON_initiator and S-MAXSIZE_10240] then m else n/a.
- c9: if [S-V1 or NOT S-CON_initiator] then n/a else if [S-MAXSIZE_10240] then m else o.
- c10: if [NOT S-V1 and S-CON_responder and S-MAXSIZE_10240] then m else n/a.
- c11: if [S-REL_requestor] then m else n/a.
- c12: if [S-REL_acceptor] then m else n/a.
- c13: if [S-DATA_requestor] then m else n/a.
- c14: if [S-DATA_acceptor] then m else n/a.
- c15: if [NOT S-V1 and S-MAXSIZE_9 and S-EXP_T] then m else n/a.
- c16: if [S-FU(NR) and S-REL_acceptor] then m else n/a.
- c17: if [S-FU(NR) and S-REL_requestor] then m else n/a.
- c18: if [S-FU(HD)] then m else n/a.
- c19: if [S-XDATA_requestor] then m else n/a.
- c20: if [S-XDATA_acceptor] then m else n/a.
- c21: if [S-TDATA_requestor] then m else n/a.
- c22: if [S-TDATA_acceptor] then m else n/a.
- c23: if [S-CAP_requestor] then m else n/a.
- c24: if [S-CAP_acceptor] then m else n/a.
- c25: if [S-MIN_requestor] then m else n/a.
- c26: if [S-MIN_acceptor] then m else n/a.
- c27: if [S-MIN_acceptor] then o else n/a.
- c28: if [S-FU(SS)] then m else n/a.
- c29: if [S-FU(SS)] then o else n/a.
- c30: if [S-MAJ_requestor] then m else n/a.
- c31: if [S-MAJ_acceptor] then m else n/a.
- c32: if [S-MAJ_acceptor and S-EXP_T] then m else n/a.
- c33: if [S-MAJ_requestor and S-EXP_T] then m else n/a.
- c34: if [S-FU(RESYN)] then m else n/a.
- c35: if [S-FU(RESYN) and S-EXP_T] then m else n/a.
- c36: if [S-FU(EXCEP)] then m else n/a.
- c37: if [S-FU(EXCEP)] then o else n/a.
- c38: if [S-ACTS_requestor] then m else n/a.
- c39: if [S-ACTS_acceptor] then m else n/a.
- c40: if [S-ACTR_requestor] then m else n/a.
- c41: if [S-ACTR_acceptor] then m else n/a.
- c42: if [S-ACTI_requestor] then m else n/a.
- c43: if [S-ACTI_acceptor] then m else n/a.
- c44: if [S-ACTD_requestor] then m else n/a.
- c45: if [S-ACTD_acceptor] then m else n/a.
- c46: if [S-ACTE_requestor] then m else n/a.
- c47: if [S-ACTE_acceptor] then m else n/a.

- c48: if [S-FU(ACT) and S-EXP_T] then m else n/a.
- c49: if [S-GTC_requestor] then m else n/a.
- c50: if [S-GTC_acceptor] then m else n/a.
- c51: if [S-CON_initiator] then o else n/a.
- c52: if [NOT S-CON_initiator] then n/a else if [S-XCONC_RCV] then m else o.
- c53: if [NOT S-CON_responder] then n/a else if [S-XCONC_RCV] then m else o.
- c54: if [NOT S-CON_initiator] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o.
- c55: if [NOT S-CON_responder] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o.
- c56: if [NOT S-CON_initiator] then n/a else if [NOT S-V1] then m else o.
- c57: if [NOT S-CON_responder] then n/a else if [NOT S-V1] then m else o.
- c58: if [NOT S-CON_initiator] then n/a else if [{ S-FU(SY) or s-FU(MA) or S-FU(SS) or S-FU(RESYN) } and NOT S-FU(ACT)] then m else o.
- c59: if [NOT S-CON_responder] then n/a else if [{ S-FU(SY) or s-FU(MA) or S-FU(SS) or S-FU(RESYN) } and NOT S-FU(ACT)] then m else o.
- c60: if [S-CON_responder] then o else n/a.
- c61: if [NOT S-CON_initiator] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o.
- c62: if [NOT S-CON_responder] then n/a else if [S-FU(SS) and NOT S-FU(ACT)] then m else o.
- c63: if [NOT S-CON_initiator] then n/a else if [A.8.1.2.1/1a or A.8.1.2.1/2a or A.8.1.2.1/3a or A.8.1.2.1/4a or A.8.1.2.1/5a or A.8.1.2.1/6a] then m else o.
- c64: if [NOT S-CON_initiator] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m.
- c65: if [NOT S-CON_responder] then n/a else if [S-FU(HD) and S-FU(SY) and S-FU(ACT) and S-FU(CD) and S-FU(EXCEP) and NOT S-FU(NR) and NOT S-FU(FD) and NOT S-FU(EX) and NOT S-FU(TD) and NOT S-FU(SS) and NOT S-FU(MA) and NOT S-FU(RESYN) and NOT S-FU(DS)] then o else m.
- c66: if [NOT S-V1 and S-CON_initiator and S-MAXSIZE_512] then m else n/a.
- c67: if [NOT S-V1 and S-CON_responder and S-MAXSIZE_512] then m else n/a.
- c68: if [A.8.1.3/7a] then o else n/a.
- c69: if [A.8.1.3/7b] then o else n/a.
- c70: if [NOT S-OA_SDR] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o.
- c71: if [NOT S-OA_RCV] then n/a else if [S-SEG_SDR or S-SEG_RCV] then m else o.
- c72: if [S-OA_SDR] then m else n/a.
- c73: if [S-OA_RCV] then m else n/a.
- c74: if [S-CDO_SDR] then m else n/a.
- c75: if [S-CDO_RCV] then m else n/a.
- c76: if [NOT S-CON_responder] then n/a else if [A.8.4.2.1/1a or A.8.4.2.1/2a or A.8.4.2.1/3a or A.8.4.2.1/4a or A.8.4.2.1/5a or A.8.4.2.1/6a] then m else o.
- c77: if [S-CON_responder and NOT S-V1] then m else n/a.
- c78: if [S-CON_initiator and NOT S-V1] then m else n/a.
- c79: if [A.8.4.3/7a] then o else n/a.
- c80: if [A.8.4.3/7b] then o else n/a.
- c81: if [NOT S-CON_responder] then n/a else if [S-REUSE_T] then m else o.
- c82: if [NOT S-CON_initiator] then n/a else if [S-REUSE_T] then m else o.
- c83: if [NOT S-REL_requestor] then n/a else if [S-REUSE_T] then m else o.
- c84: if [NOT S-REL_acceptor] then n/a else if [S-REUSE_T] then m else o.
- c85: if [S-REL_requestor and NOT S-V1] then m else n/a.
- c86: if [S-REL_acceptor and NOT S-V1] then m else n/a.
- c87: if [S-REL_requestor] then o else n/a.
- c88: if [S-REL_acceptor] then o else n/a.
- c89: if [S-FU(NR) and S-REL_acceptor and NOT S-V1] then m else n/a.
- c90: if [S-FU(NR) and S-REL_requestor and NOT S-V1] then m else n/a.
- c91: if [S-FU(NR) and S-REL_acceptor] then o else n/a.
- c92: if [NOT S-V1] then m else n/a.

- c93: if [S-DATA_requestor and S-SEG_SDR] then m else n/a.
- c94: if [S-DATA_acceptor and S-SEG_RCV] then m else n/a.
- c95: if [S-TDATA_requestor and S-SEG_SDR] then m else n/a.
- c96: if [S-TDATA_acceptor and S-SEG_RCV] then m else n/a.
- c97: if [S-CAP_requestor and NOT S-V1] then m else n/a.
- c98: if [S-CAP_acceptor and NOT S-V1] then m else n/a.
- c99: if [S-CAP_requestor] then o else n/a.
- c100: if [S-CAP_acceptor] then o else n/a.
- c101: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then o else n/a.
- c102: if [S-FU(NR) or S-FU(HD) or S-FU(SY) or S-FU(MA) or S-FU(ACT)] then m else n/a.
- c103: if [NOT S-V1 and A.8.16/1a] then o else n/a.
- c104: if [A.8.17/1a] then o else n/a.
- c105: if [A.8.17/1b] then m else n/a.
- c106: if [(S-MIN_requestor or S-FU(SS)) and S-FU(DS)] then m else if [(S-MIN_requestor or S-FU(SS)) and NOT S-FU(DS)] then o else n/a.
- c107: if [S-MIN_acceptor or S-FU(SS)] then o else n/a.
- c108: if [{S-MIN_requestor and NOT S-V1} or { S-FU(SS) and NOT S-V1}] then m else n/a.
- c109: if [{S-MIN_acceptor and NOT S-V1} or { S-FU(SS) and NOT S-V1}] then m else n/a.
- c110: if [S-MIN_requestor or S-FU(SS)] then m else n/a.
- c111: if [S-MIN_acceptor or S-FU(SS)] then m else n/a.
- c112: if [S-MIN_requestor or S-FU(SS)] then o else n/a.
- c113: if [S-MAJ_requestor and NOT S-V1] then m else n/a.
- c114: if [S-MAJ_acceptor and NOT S-V1] then m else n/a.
- c115: if [S-MAJ_requestor] then o else n/a.
- c116: if [NOT S-MAJ_acceptor] then n/a else if [NOT S-FU(SS)] then m else o.
- c117: if [NOT S-MAJ_requestor] then n/a else if [NOT S-FU(SS)] then m else o.
- c118: if [NOT S-MAJ_acceptor] then n/a else if [S-FU(SS)] then m else o.
- c119: if [NOT S-MAJ_requestor] then n/a else if [S-FU(SS)] then m else o.
- c120: if [S-MAJ_acceptor] then o else n/a.
- c121: if [S-FU(RESYN) and NOT S-V1] then m else n/a.
- c122: if [NOT S-FU(RESYN)] then n/a else if [S-FU(SY) or S-FU(MA)] then m else o.
- c123: if [S-FU(RESYN) and S-FU(SS)] then o else n/a.
- c124: if [S-FU(RESYN) and S-FU(SS)] then m else n/a.
- c125: if [S-FU(RESYN)] then o else n/a.
- c126: if [NOT S-FU(RESYN)] then n/a else if [NOT S-FU(SS)] then m else o.
- c127: if [{S-MAJ_acceptor and S-EXP_T} or {S-FU(RESYN) and S-EXP_T} or {S-FU(ACT) and S-EXP_T} or {S-PR_SDR}] then m else n/a.
- c128: if [{S-MAJ_requestor and S-EXP_T} or {S-FU(RESYN) and S-EXP_T} or {S-FU(ACT) and S-EXP_T} or {S-PR_RCV}] then m else n/a.
- c129: if [S-FU(SS) and S-EXP_T] then m else n/a.
- c130: if [S-ER_SDR] then m else n/a.
- c131: if [S-FU(EXCEP) and NOT S-V1] then m else n/a.
- c132: if [S-FU(EXCEP)] then o else n/a.
- c133: if [S-GTC_requestor and NOT S-V1] then m else n/a.
- c134: if [S-GTC_acceptor and NOT S-V1] then m else n/a.
- c135: if [S-GTC_requestor and NOT S-V1] then o else n/a.
- c136: if [S-ACTS_acceptor and NOT S-V1] then m else n/a.
- c137: if [S-ACTS_requestor] then o else n/a.
- c138: if [S-ACTR_requestor] then o else n/a.
- c139: if [S-ACTR_requestor and S-FU(SS)] then m else n/a.
- c140: if [S-ACTR_acceptor and S-FU(SS)] then m else n/a.
- c141: if [S-ACTR_requestor and NOT S-V1] then m else n/a.
- c142: if [S-ACTR_acceptor and NOT S-V1] then m else n/a.

c143: if [S-ACTI_requestor and NOT S-V1] then m else n/a.
 c144: if [S-ACTI_acceptor and NOT S-V1] then m else n/a.
 c145: if [S-ACTI_requestor and NOT S-V1] then o else n/a.
 c146: if [S-ACTI_acceptor and NOT S-V1] then o else n/a.
 c147: if [S-ACTD_requestor and NOT S-V1] then m else n/a.
 c148: if [S-ACTD_acceptor and NOT S-V1] then m else n/a.
 c149: if [S-ACTD_requestor and NOT S-V1] then o else n/a.
 c150: if [S-ACTD_acceptor and NOT S-V1] then o else n/a.
 c151: if [S-ACTE_requestor and NOT S-V1] then m else n/a.
 c152: if [S-ACTE_acceptor and NOT S-V1] then m else n/a.
 c153: if [S-ACTE_requestor] then o else n/a.
 c154: if [NOT S-ACTE_acceptor] then n/a else if [NOT S-FU(SS)] then m else o.
 c155: if [NOT S-ACTE_requestor] then n/a else if [NOT S-FU(SS)] then m else o.
 c156: if [NOT S-ACTE_acceptor] then n/a else if [S-FU(SS)] then m else o.
 c157: if [NOT S-ACTE_requestor] then n/a else if [S-FU(SS)] then m else o.
 c158: if [S-ACTE_acceptor] then o else n/a.

Annexe C

Liste des mnémoniques utilisés dans les déclarations conditionnelles et optionnelles

(Cette annexe ne fait pas partie intégrante de la présente Recommandation | Norme internationale)

Mnemonic	Clause where it is defined	Clauses where it is used
S-ACTD_acceptor	A.7.14.1.4	A.7.14.2, A.8.33, A.8.34
S-ACTD_requestor	A.7.14.1.4	A.7.14.2, A.8.33, A.8.34
S-ACTE_acceptor	A.7.14.1.5	A.7.14.2, A.8.35, A.8.36
S-ACTE_requestor	A.7.14.1.5	A.7.14.2, A.8.35, A.8.36
S-ACTI_acceptor	A.7.14.1.3	A.7.14.2, A.8.31, A.8.32
S-ACTI_requestor	A.7.14.1.3	A.7.14.2, A.8.31, A.8.32
S-ACR_acceptor	A.7.14.1.2	A.7.14.2, A.8.30.1, A.8.30.2
S-ACR_requestor	A.7.14.1.2	A.7.14.2, A.8.30.1, A.8.30.2
S-ACTS_acceptor	A.7.14.1.1	A.7.14.2, A.8.29
S-ACTS_requestor	A.7.14.1.1	A.7.14.2, A.8.29
S-CAP_acceptor	A.7.7.1	A.7.7.2, A.8.14, A.8.15
S-CAP_requestor	A.7.7.1	A.7.7.2, A.8.14, A.8.15
S-CDO_RCV	A.7.1.2	A.8.3
S-CDO_SDR	A.7.1.2	A.8.3
S-CON_initiator	A.7.1.1.1	A.7.1.2, A.8.1.1, A.8.1.2.1, A.8.1.2.2, A.8.1.3, A.8.4.1, A.8.4.2.1, A.8.4.2.2, A.8.4.3, A.8.5.1, A.8.5.2
S-CON_responder	A.7.1.1.1	A.7.1.2, A.8.1.1, A.8.1.2.1, A.8.1.2.2, A.8.1.3, A.8.4.1, A.8.4.2.1, A.8.4.2.2, A.8.4.3, A.8.5.1, A.8.5.2
S-DATA_acceptor	A.7.1.1.3	A.7.1.2, A.8.11
S-DATA_requestor	A.7.1.1.3	A.7.1.2, A.8.11
S-ER_SDR	A.7.13.2	A.8.25
S-EXP_T	A.6.2	A.7.1.2, A.7.11.2, A.7.12.3, A.7.14.2, A.8.24
S-FU(ACT)	A.6.1	A.6.1, A.7.14.1.1, A.7.14.1.2, A.7.14.1.3, A.7.14.1.4, A.7.14.1.5, A.7.14.1.6, A.7.14.2, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.16, A.8.17, A.8.22, A.8.23, A.8.24
S-FU(CD)	A.6.1	A.7.7.1, A.8.1.3, A.8.4.3, A.8.5.2
S-FU(DS)	A.6.1	A.8.1.3, A.8.4.3, A.8.5.2, A.8.18
S-FU(EX)	A.6.1	A.6.2, A.7.5.1, A.8.1.3, A.8.4.3, A.8.5.2
S-FU(EXCEP)	A.6.1	A.7.13.1, A.7.13.2, A.8.1.3, A.8.4.3, A.8.5.2, A.8.25, A.8.26
S-FU(FD)	A.6.1	A.8.1.3, A.8.4.3, A.8.5.2
S-FU(HD)	A.6.1	A.6.1, A.7.3.1, A.8.1.3, A.8.4.3, A.8.5.2, A.8.16, A.8.17, A.8.22, A.8.23
S-FU(MA)	A.6.1	A.7.11.1, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.16, A.8.17, A.8.22, A.8.23
S-FU(NR)	A.6.1	A.7.2.2, A.8.1.3, A.8.4.3, A.8.5.2, A.8.8, A.8.16, A.8.17, A.8.22, A.8.23
S-FU(RESYN)	A.6.1	A.7.12.1, A.7.12.2, A.7.12.3, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.22, A.8.23, A.8.24
S-FU(SS)	A.6.1	A.6.1, A.7.9.1, A.7.9.2, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.18, A.8.19, A.8.21, A.8.22, A.8.23, A.8.24, A.8.30.1, A.8.36
S-FU(SY)	A.6.1	A.6.1, A.7.8.1, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.16, A.8.17, A.8.22, A.8.23
S-FU(TD)	A.6.1	A.7.6.1, A.8.1.3, A.8.4.3, A.8.5.2
S-GTC_acceptor	A.7.14.1.6	A.7.14.2, A.8.27
S-GTC_requestor	A.7.14.1.6	A.7.14.2, A.8.27
S-MAJ_acceptor	A.7.11.1	A.7.11.2, A.8.20, A.8.21, A.8.24
S-MAJ_requestor	A.7.11.1	A.7.11.2, A.8.20, A.8.21, A.8.24
S-MAXSIZE_9	A.6.2	A.7.1.2
S-MAXSIZE_512	A.6.2	A.8.1.3
S-MAXSIZE_10240	A.6.2	A.7.1.2, A.8.1.3
S-MIN_acceptor	A.7.8.1	A.7.8.2, A.8.18, A.8.19

Mnemonic	Clause where it is defined	Clauses where it is used
S-MIN_requestor	A.7.8.1	A.7.8.2, A.8.18, A.8.19
S-OA_RCV	A.7.1.2	A.8.2
S-OA_SDR	A.7.1.2	A.8.2
S-PR_RCV	A.7.1.2	A.8.24
S-PR_SDR	A.7.1.2	A.8.24
S-REL_acceptor	A.7.1.1.2	A.7.1.2, A.7.2.2, A.8.6, A.8.7, A.8.8
S-REL_requestor	A.7.1.1.2	A.7.1.2, A.7.2.2, A.8.6, A.8.7, A.8.8
S-REUSE_T	A.6.2	A.8.5.2, A.8.6
S-SEG_RCV	A.6.2	A.8.1.2.1, A.8.2, A.8.4.2.1, A.8.11, A.8.13
S-SEG_SDR	A.6.2	A.8.1.2.1, A.8.2, A.8.4.2.1, A.8.11, A.8.13
S-TDATA_acceptor	A.7.6.1	A.7.6.2, A.8.13
S-TDATA_requestor	A.7.6.1	A.7.6.2, A.8.13
S-V1	A.4.2	A.7.1.2, A.8.1.2.1, A.8.1.3, A.8.4.2.1, A.8.4.3, A.8.5.2, A.8.6, A.8.7, A.8.8, A.8.9, A.8.14, A.8.15, A.8.16, A.8.17, A.8.18, A.8.19, A.8.20, A.8.21, A.8.22, A.8.23, A.8.26, A.8.27, A.8.29, A.8.30.2, A.8.31, A.8.32, A.8.33, A.8.34, A.8.35, A.8.36
S-XCONC_RCV	A.6.2	A.8.1.2.1, A.8.4.2.1
S-XDATA_acceptor	A.7.5.1	A.7.5.2, A.8.12
S-XDATA_requestor	A.7.5.1	A.7.5.2, A.8.12